

# Agilent E1510A

## 4-Channel Sample and Hold Input SCP

### Data Sheet

- Use with Agilent E1413C/E1415A/E1419A
- Four sample and hold channels
- Four direct input channels
- Samples all channels simultaneously, reduces skew



Agilent E1510A

### Description

The Agilent E1510A 4-Channel Sample and Hold SCP provides four channels of sample and hold inputs, and four channels of direct inputs for the A/Ds. The sample and hold inputs sample all four channels simultaneously to reduce the skew introduced by scanning.


The SCP circuitry provides a voltage gain of 0.5, 8, 64, or 512 for each channel.

The low-pass filter on each sample and hold channel is a 6th order Bessel active RC filter used to provide alias protection and noise reduction. The filter cutoff frequencies are 1 kHz, 500 Hz, 250 Hz, 100 Hz, and 15 Hz.

Use the E1510A with the following VXI modules:

Model	Description
E1413C	64-Channel Scanning A/D Converter
E1415A	Algorithmic Closed Loop Controller
E1419A	Multifunction Measurement and Control Module

Refer to the Agilent Technologies Website for recent product updates, if applicable.



## Product Specifications

These specifications for the E1510A reflect the combined performance of the scanning A/D and the E1510A SCP.

### Measurement Ranges

**DC Volts:** 0 V to  $\pm 8$  V Full Scale

### Input Characteristics

**Maximum input voltage (normal mode plus common mode):**

**Operating:**  $< \pm 16$  V peak  
**Damage level:**  $> \pm 42$  V peak

**Maximum common mode voltage:**

**Operating:**  $< \pm 16$  V peak  
**Damage level:**  $> \pm 42$  V peak

**Common mode rejection (0 to 60 Hz):**

**x0.5 gain:**  $> 60$  dB  
**x8 gain:**  $> 78$  dB  
**x64 gain:**  $> 100$  dB  
**x512 gain:**  $> 100$  dB

**Input impedance:**  $> 100$  M $\Omega$

### Maximum Tare Cal Offset

*Maximum tare cal offset depends on A/D range and SCP gain.*

Gain	Maximum Offset
x0.5	$\pm 25\%$ of full scale
x8	$\pm 90$ mV
x64	$\pm 95$ mV
x512	$\pm 95$ mV

### Filter Characteristics (6-pole Bessel filter)

**Normal mode rejection:**

**15 Hz filter:**

**15 Hz:**  $-3$  dB  
**50 Hz:**  $> 33$  dB  
**60 Hz:**  $> 43$  dB

**100 Hz filter:**

**100 Hz:**  $-3$  dB  
**400 Hz:**  $> 43$  dB

**250 Hz filter:**

**250 Hz:**  $-3$  dB  
**1000 Hz:**  $> 43$  dB

**500 Hz filter:**

**500 Hz:**  $-3$  dB  
**2000 Hz:**  $> 43$  dB

**1000 Hz filter:**

**1000 Hz:**  $-3$  dB  
**4000 Hz:**  $> 43$  dB

### Sample Time Skew Between Channels

Because the low-pass filter precedes the sample and hold, the interchannel sample time skew is primarily determined by the matching of the filter propagation delay times. The table below lists the propagation delay for a step function input (measured at 50% of the final value) for each filter setting, as well as the matching between channels programmed to the same filter setting.

Bandwidth	Step propagation delay (nominal)	Delay matching ( $\pm$ from nominal)
1 kHz:	427.5 $\mu$ sec	10 $\mu$ sec
500 Hz:	854.9 $\mu$ sec	20 $\mu$ sec
250 Hz:	1.710 msec	40 $\mu$ sec
100 Hz:	4.275 msec	100 $\mu$ sec
15 Hz:	28.50 msec	670 $\mu$ sec

### Maximum Filter Overshoot

$< 1\%$  of input step size.

---

### Measurement Accuracy DC Voltage

For autorange, add .05% of reading for input voltages  $>\pm 4$  V.

#### Accuracy — Gain x0.5

Range $\pm$ FS	Linearity % of Reading:	Offset Error:	Noise 3 $\sigma$ :
125 mV:	0.02	488 $\mu$ V	1.5 $\mu$ V
0.5 V:	0.02	488 $\mu$ V	1.5 $\mu$ V
2.0 V:	0.02	488 $\mu$ V	1.5 $\mu$ V
8.0 V:	0.02	488 $\mu$ V	1.5 $\mu$ V

**Temperature Coefficients:** *add tempco error to above table*

**Gain:** 10 ppm/ $^{\circ}$ C (after \*CAL)

**Offset:**

0-30  $^{\circ}$ C: 0  $\mu$ V/ $^{\circ}$ C

30-55  $^{\circ}$ C: 0.75  $\mu$ V/ $^{\circ}$ C

#### Accuracy — Gain x8

Range $\pm$ FS	Linearity % of Reading:	Offset Error:	Noise 3 $\sigma$ :
7.8 mV:	0.02	30.5 $\mu$ V	95 $\mu$ V
31.25 m V:	0.02	30.5 $\mu$ V	95 $\mu$ V
125 mV:	0.02	30.5 $\mu$ V	95 $\mu$ V
0.5 V:	0.02	30.5 $\mu$ V	95 $\mu$ V

**Temperature Coefficients:** *add tempco error to above table*

**Gain:** 10 ppm/ $^{\circ}$ C (after \*CAL)

**Offset:**

0-30  $^{\circ}$ C: 0  $\mu$ V/ $^{\circ}$ C

30-55  $^{\circ}$ C: 0.75  $\mu$ V/ $^{\circ}$ C

#### Accuracy — Gain x64

Range $\pm$ FS	Linearity % of Reading:	Offset Error:	Noise 3 $\sigma$ :
3.9 mV:	0.02	15 $\mu$ V	12 $\mu$ V
15.6 m V:	0.02	15 $\mu$ V	12 $\mu$ V
62.5 mV:	0.02	15 $\mu$ V	12 $\mu$ V

**Temperature Coefficients:** *add tempco error to above table*

**Gain:** 10 ppm/ $^{\circ}$ C (after \*CAL)

**Offset:**

0-40  $^{\circ}$ C: 0.14  $\mu$ V/ $^{\circ}$ C

40-55  $^{\circ}$ C: 0.38  $\mu$ V/ $^{\circ}$ C

#### Accuracy — Gain x512

Range $\pm$ FS	Linearity % of Reading:	Offset Error:	Noise 3 $\sigma$ :
7.81 mV:	0.04	15 $\mu$ V	2 $\mu$ V

**Temperature Coefficients:** *add tempco error to above table*

**Gain:** 10 ppm/ $^{\circ}$ C (after \*CAL)

**Offset:**

0-40  $^{\circ}$ C: 0.14  $\mu$ V/ $^{\circ}$ C

40-55  $^{\circ}$ C: 0.38  $\mu$ V/ $^{\circ}$ C

---

### Current Requirements (Amps)

5 V max	24 V max	-24 V max
0.01	0.125	0.125

---

### Ordering Information

Description	Product No.
4-Channel Sample & Hold Input SCP	E1510A

## Related Literature

*2000 Test System and VXI Catalog CD-ROM*,  
Agilent Pub. No. 5980-0308E (detailed specifications for VXI products)

*2000 Test System and VXI Catalog*,  
Agilent Pub. No. 5980-0307E (overview of VXI products )

*1998 Test System and VXI Products Data Book*,  
Agilent Pub. No. 5966-2812E

## Online

Internet access for Agilent product information, services and support  
[www.agilent.com/find/tmdir](http://www.agilent.com/find/tmdir)

VXI product information  
[www.agilent.com/find/vxi](http://www.agilent.com/find/vxi)

Defense Electronics Applications  
[www.agilent.com/find/defense\\_ATE](http://www.agilent.com/find/defense_ATE)

Agilent Technologies VXI Channel Partners  
[www.agilent.com/find/vxichanpart](http://www.agilent.com/find/vxichanpart)

Agilent Technologies' HP VEE Application Website  
[www.agilent.com/find/vee](http://www.agilent.com/find/vee)

Agilent Technologies Data Acquisition and Control Website  
[www.agilent.com/find/data\\_acq](http://www.agilent.com/find/data_acq)

Agilent Technologies Instrument Driver Downloads  
[www.agilent.com/find/inst\\_drivers](http://www.agilent.com/find/inst_drivers)

Agilent Technologies Electronics Manufacturing Test Solutions  
[www.agilent.com/go/manufacturing](http://www.agilent.com/go/manufacturing)

**Get assistance with all your test and measurement needs at  
[www.agilent.com/find/assist](http://www.agilent.com/find/assist)  
or check your local phone book for the Agilent office  
near you.**

## Agilent Technologies' test and measurement service/support commitment

Agilent strives to maximize the value our test and measurement products give you, while minimizing your risk and service/support problems. We work to ensure that each product is realistically described in the literature, meets its stated performance and functionality, has a clearly stated global warranty, and is supported at least five years beyond its production life. Our extensive self-help tools include many online resources ([www.agilent.com](http://www.agilent.com)).

Experienced Agilent test engineers throughout the world offer practical recommendations for product evaluation and selection. After you purchase an Agilent product, they can provide no-charge assistance with operation verification and basic measurement setups for advertised capabilities. To enhance the features, performance, and flexibility of your test and measurement products—and to help you solve application challenges—Agilent offers free or extra-cost product options and upgrades, and sell expert engineering, calibration, and other consulting services.

### Phone and fax

United States:  
Agilent Technologies  
(tel) 1 800 452 4844

Canada:  
Agilent Technologies Canada Inc.  
(tel) 1 877 894 4414

Europe:  
Agilent Technologies  
Test & Measurement  
European Marketing Organisation  
(tel) (31 20) 547 2000


Japan:  
Agilent Technologies Japan Ltd.  
(tel) (81) 426 56 7832  
(fax) (81) 426 56 7840

Latin America:  
Agilent Technologies  
Latin American Region Headquarters, U.S.A.  
(tel) (305) 267 4245  
(fax) (305) 267 4286

Australia/New Zealand:  
Agilent Technologies Australia Pty Ltd.  
(tel) 1 800 629 485 (Australia)  
(fax) (61 3) 9272 0749  
(tel) 0 800 738 378 (New Zealand)  
(fax) (64 4) 802 6881

Asia Pacific:  
Agilent Technologies, Hong Kong  
(tel) (852) 3197-7777  
(fax) (852) 2506-9284

Data Subject to Change  
© Agilent Technologies 2000  
Printed in the U.S.A. 04/2000  
Publication No.: 5966-2392E



**Agilent Technologies**  
Innovating the HP Way