



Single / Dual / Triple / Quad  
FCB100



## Features

- L-Band IF
- Cost effective solution
- Fully compliant with IESS 308/309
- High linearity
- Low group delay
- Front panel control (local)
- Full remote control (remote)

## Overview

The Advantech HP range of converters uses the latest technology in conversion, local and remote control thus providing the ultimate in performance and user friendly operation at a very competitive price.

The spectral purity, low phase noise and stability exceed the requirements of all major international satellite network operators.

The flexible and comprehensive monitor and control features on the HP converter ensure that it will fit into any network management system architecture. The user-friendly front panel or the RS485 remote interface will provide full set-up and fault monitoring facilities. The RS232 will provide the Monitor and Control functions via a PC and will also allow for software upgrades downloading.

The PLL oscillator used in the converter is either locked to a highly stable internal 10 MHz reference or if the external reference option is fitted and the proper level of signal is present, the PLL will automatically lock to the external reference.

## Application

The HP range of converters is particularly suited for use in VSAT, SCPC Networks, SNG, DVB-RCS and Hub systems. This makes them an ideal choice for large earth stations requiring cost effective solutions for frequency conversion. The lightweight, rugged and compact design also ensures that the HP converter provides the ideal solution for mobile truck or flyaway DSNG systems. With a fully welded aluminum chassis and robust modular internal construction the converter can even meet the demands of military installations.

The HP range of converters provides an industry leading MTBF of over 120,000 hours.

## Operating Bands Up-Converters

Model Number	Type	RF Output	IF Frequency
ARUN-LC	single	5.850 - 6.425 GHz Non-inverted	950-1525 MHz
ARUD-LC	dual		
ARUT-LC	triple		
ARUQ-LC	quad		
ARUN-LCX	single	5.850 - 6.725 GHz Non-inverted	950-1825 MHz
ARUD-LCX	dual		
ARUT-LCX	triple		
ARUQ-LCX	quad		

## Down-Converters

Model Number	Type	RF Input	IF Frequency
AREN-CXL	single	3.40 - 4.20 GHz	950 – 1750 MHz Inverted
ARED-CXL	dual		
ARET-CXL	triple		
AREQ-CXL	quad		
ARDN-CXL	single	3.40 - 4.20 GHz	950 - 1750 MHz Non-inverted
ARDD-CXL	dual		
ARDT-CXL	triple		
ARDQ-CXL	quad		

## Up/Down -Converters

Model Number	Type	RF Output	IF Frequency
ARMT-LCE	Up/ Down	5.850 - 6.425 GHz Non- inverted 3.40 - 4.20 GHz Inverted	950-1525 MHz or 950-1750 MHz
ARMT-LC	Up/ Down	5.850 -6.425 GHz Non- inverted 3.40 - 4.20 GHz Non-Inverted	950-1525 MHz or 950-1750 MHz
ARMT-LCX	Up/ Down	5.850 -6.725 GHz Non- inverted 3.40 - 4.20 GHz Non-Inverted	950-1825 MHz or 950-1750 MHz
ARMT-LCXE	Up/ Down	5.850 -6.725 GHz Non- inverted 3.40 - 4.20 GHz -Inverted	950-1825 MHz or 950-1750 MHz

## Options

- Ethernet port and SNMP Interface
- External 10 MHz with Autosensing
- Spectrum INV or NINV on down converter
- Dual, quad, Up/Down, or 1:1 redundant hot swap converters in single 1RU chassis
- Redundant Ready (for 1:N)

# C-Band Block Frequency Converters

## Technical Specifications

Up-Converter		Down-Converter	
<b>IF Input</b>		<b>RF Input</b>	
Frequency range	(See table on front page)	Frequency range	(See table on front page)
Impedance	50 Ω	Impedance	50 Ω
Input Connector	BNC (female)	Input Connector	Type N (female)
Return loss	16 dB	Return loss	18 dB
<b>RF Output</b>		<b>IF Output</b>	
Output power (P1dB)	0 dBm	Frequency range	(See table on front page)
Frequency range	(See table on front page)	Output level	+5 dBm at P1dB
IMD3 (two tone)	-40 dBc max @ -10 dBm output	Output Connector	BNC female
Output connector	Type N (female)	Connector Impedance	50 Ω
Connector Impedance	50 Ω	Return Loss	16 dB
Return loss	18 dB		
<b>Transfer Characteristics</b>		<b>Transfer Characteristics</b>	
Conversion Gain	20 dB @ max gain setting	Conversion Gain	40 dB @ max gain setting
Gain adjustment	20 dB	Gain adjustment	20 dB
Attenuator step size	0.1 dB	Attenuator step size	0.1 dB
Gain flatness	±1.5 dB p-p over 575 MHz	Gain flatness	±2.0 dB p-p over 800 MHz (NINV Down Converters)
	1.0 dB p-p over 40 MHz		+ 1.0 dB p-p over 40 MHz
Gain stability	±0.25 dB max. /24 hours	Gain stability	±0.25 dB max. / 24 hours
	±1 dB over temp. range		±1 dB over temp. range
Spurious	-55 dBc carrier related @ -10 dBm < -60 dBm non-carrier related	Spurious	-55 dBc @ -10 dBm
		Image rejection	60 dB
		Noise Figure	20 dB
Phase noise	Meets or Exceeds IESS 308/309	Phase noise	Meets or Exceeds IESS 308/309
<b>Reference</b>		<b>Mechanical</b>	
External Reference	10 MHz, +/- 3 dBm input level	Dimensions	Width 19" (482.6 mm)
Internal reference stability	± 2 x 10 <sup>-10</sup> / day		Height 1U 1.75" (44.5 mm)
Aging	± 5 x 10 <sup>-8</sup> / year		Depth 22" (558.8 mm)
<b>Environmental</b>		<b>Power Supply</b>	
Operational	0°C to +50°C standard	Voltage	90 – 265 VAC (47 – 63 Hz)
Storage	-55°C to +85°C	Power	50W (typical, single converter)
Humidity	Non-condensing	Connector	IEC 603320 10A
Altitude	3,000m AMSL		
<b>Monitor and Control</b>			
		RS 485	DB9
		RS 232	DB9
		Discrete	DB9
		Ethernet (optional)	RJ45 F

**NORTH AMERICA**  
**USA**  
 Tel: +1 703 659 9796  
 Fax: +1 703 635 2212  
 info.usa@advantechwireless.com

**CANADA**  
 Tel: +1 514 420 0045  
 Fax: +1 514 420 0073  
 info.canada@advantechwireless.com

**EUROPE**  
**UNITED KINGDOM**  
 Tel: +44 1480 357 600  
 Fax: +44 1480 357 601  
 info.uk@advantechwireless.com

**RUSSIA & CIS**  
 Tel: +7 495 971 59 18  
 info.russia@advantechwireless.com

**INDIA**  
 Tel: +91 33 2415 5922  
 info.india@advantechwireless.com

**SOUTH AMERICA**  
 Tel: +1 514 420 0045  
 Fax: +1 514 420 0073  
 info.latam@advantechwireless.com

**BRAZIL**  
 Tel: +55 11 3054 5701  
 Fax: +55 11 3054 5701  
 info.brazil@advantechwireless.com

An ISO 9001 : 2008 Company



Ref.: PB-FCB100-C-13150