



Features

- Operating Ku-Band Tx: 14.00 - 14.50 GHz
 - 13.75 - 14.50 GHz (optional)
 - Rx: 10.95 - 12.75 GHz (sub-bands)
- L band Tx and Rx interface
- Easy to install and operate
- Compact light weight design
- Weatherproof package
- Phase-locked LNB
- Low phase noise
- Remote Monitor & Control (RS-232/RS-485)
- Relay alarm indicators
- LED status indicators
- Automatic high reflected power protection
- Harmonic Filter
- High stability internal 10MHz reference
- Downloadable PC GUI
- Redundant ready operation
- Power supply with PFC

OPTIONS

- Extended Ku-band (13.75 – 14.50 GHz)
- LNA operation
- Remote M&C panel
- External 10 MHz reference with auto sensing
- Ethernet interface

OVERVIEW

The Advantech range of transceivers uses the latest technology, thus providing the ultimate in performance and user friendly operation at a very competitive price.

AWMT-6000KL-G® is a family of hub-mount transceivers operating in the Ku-band from 300W to 400 W. These transceivers are designed for continuous operation in the harshest outdoor environment. The built-in microprocessor controller provides for external monitoring and control of the operating parameters, and for the redundancy control. The LNB is connected to the transceiver with a single coaxial cable. Apart from the LNB, the complete unit is available in a single integrated package.

The flexible and comprehensive monitor and control features on the transceiver ensure that it will fit into any network management system architecture. The user-friendly RS-232 interface will provide full set-up and fault monitoring facilities via a PC terminal mode communication or a hand-held terminal. The RS-485 interface will provide functional remote Monitor & Control, using the Graphic User Interface (GUI) or the Monitor & Control Panel.

Ku-BAND TRANSCEIVER 300W TO 400 W
L-BAND INTERFACE
AWMT-6000KL-G® series
GaN Technology



APPLICATION

The AWMT-6000KL-G® is designed to operate in the Ku-band with L-band interface. The unit is self-contained and is intended for mounting outdoors, close to the OMT of an antenna.

REDUNDANCY

The AWMT-6000KL-G® series of transceivers may be configured to operate in 1:1 redundancy mode. No extra controller is required for redundancy operation, as the built-in controller in each amplifier provides this function. Redundancy kits are required for redundant operation.

ACCESSORIES

- Mounting kits for transceiver installation
- Redundancy kits
- Mounting frame for redundancy applications
- Transmit Reject Filter and/or Receive Reject Filter (external)
- Remote Control Panel
- Hand-Held terminal

PRODUCT FEATURES & SPECIFICATIONS

Transmit Path		
Model	300W	400W
Psat min. (dBm)	55	56
Plinear (dBm)	52	53
Gain min @ max. gain set (dB)	74	76
Power Consumption	1500w	1900w
Unit Weight	55lbs (25kg)	
Dimensions (L x W x H)	26.7" x 13.7" x 5.0" (670 x 348 x 127 mm)	

Ku-BAND TRANSCEIVER 300W TO 400 W
L-BAND INTERFACE
AWMT-6000KL-G® series
GaN Technology



Transmit Path			
L-Band Input		RF Output	
Frequency range	950-1450 MHz	Frequency range	14.00 – 14.50 GHz
	950 – 1700 MHz (optional)	(Non-inverting)	13.75 – 14.50 GHz (optional)
Input Connector	N Type female / 50 Ω	Output connector	WR 75
Input Return Loss	18 dB / 50 Ω	Output Return Loss	20 dB (18 dB for coaxial output)
Gain Specification		Third order IMD (2 tones 5 MHz apart)	-25 dBc max at 3dB total back-off from rated Psat
Gain control range	20 dB (0.1 dB step size)	Spurious	-55 dBc max at Plin
Gain flatness	3.0 dB p-p	Noise Power Density	-70 dBm/Hz max in TX band
Gain stability	3.0 dB p-p max over temp. range		-135 dBm/Hz max in 10.95 – 12.75 GHz in RX band
		Spectrum Regrowth	30dB @ Plin

Receive Path			
RF Input		Gain Specification	
RF Input Frequency	10.95 – 12.75 GHz in sub-bands	Gain (LNB + Receiver)	80 dB @ max gain set
Bands	1) 10.95 – 11.70 GHz 2) 11.70-12.20 GHz 3) 12.25-12.75 GHz	Gain control range	20 dB (0.1 dB step size)
		Gain flatness	±2.5 dB max over full RF band
		Gain stability	±3.0 dB max over temp. range
		Spurious	-55 dBc max
		Image Rejection	50 dB
L-Band Output		LNB Parameters	
Frequency range	950 – 1450 MHz	LNB type	Phase locked to 10 MHz ref. (from Transceiver via coax. cable)
	950 – 1700 MHz (optional)	Noise Temperature	65°K
Output P1dB, min	+10 dBm	L-band Output Frequency	950-1750 MHz
Output Connector	N Type female / 50 Ω	L-band Output Interface	N Type female / 50 Ω
Output Return Loss	18 dB/50 Ω	Conversion Gain	60 dB
		DC power	12÷18V DC (via coaxial cable)
		LNA Parameters(optional)	
		Noise Temperature	60°K
		Output Interface	Type N female 50 Ω
		Gain	60 dB
		DC Power	12÷18V DC (via coaxial cable)

Common Parameters (Tx & Rx)			
		Environmental	
Frequency Stability	(With internal 10MHz reference)	Cooling	Forced Air
-40°C to +55°C	±2 x 10 ⁻⁸	Operational	-30°C to +55°C standard (-40°C to +55°C option)
Aging	±1 x 10 ⁻⁷ /year	Storage	-55°C to +85°C
Phase Noise	(With internal 10MHz reference)	Humidity	Up to 100% condensing
Offset frequency	Phase noise (max)	Altitude	3,000 m AMSL (derated 2°C/300m)
100 Hz	-63 dBc/Hz		
1000 Hz	-73 dBc/Hz	Power Requirements	
10 KHz	-83 dBc/Hz	AC input voltage	180-264 VAC (47-63 Hz)
100 KHz	-93 dBc/Hz	AC Connector	MS3102R20-19P
Monitor & Control		Mechanical	
Serial port (RS-485/Ethernet)	MS3112E12-10P	Dimensions	See Table above
Serial port (RS-232)	MS3112E10-6P	Packaging	Weatherproof for outdoor use
Redundancy Port	MS3112E16-26P		
Discrete Port	MS3112E12-10P		

**NORTH AMERICA
USA**
Tel: +1 703 659 9796
Fax: +1 703 635 2212
info.usa@advantechwireless.com

CANADA
Tel: +1 514 420 0045
Fax: +1 514 420 0073
info.canada@advantechwireless.com

**EUROPE
UNITED KINGDOM**
Tel: +44 1480 357 600
Fax: +44 1480 357 601
info.uk@advantechwireless.com

RUSSIA & CIS
Tel: +7 495 971 59 18
info.russia@advantechwireless.com

INDIA
Tel: +91 33 2415 5922
info.india@advantechwireless.com

SOUTH AMERICA
Tel: +1 514 420 0045
Fax: +1 514 420 0073
info.latam@advantechwireless.com

BRAZIL
Tel: +55 11 3054 5701
Fax: +55 11 3054 5701
info.brazil@advantechwireless.com

An ISO 9001 : 2008 Company



Ref.: PB-WMT600-01-13150