


IR2183(4)(S) & (PbF)

HALF-BRIDGE DRIVER

Features

- Floating channel designed for bootstrap operation
Fully operational to +600V
Tolerant to negative transient voltage
dV/dt immune
- Gate drive supply range from 10 to 20V
- Undervoltage lockout for both channels
- 3.3V and 5V input logic compatible
- Matched propagation delay for both channels
- Logic and power ground +/- 5V offset.
- Lower di/dt gate driver for better noise immunity
- Output source/sink current capability 1.4A/1.8A
- Also available LEAD-FREE (PbF)

Packages



Description


The IR2183(4)(S) are high voltage, high speed power MOSFET and IGBT drivers with dependent high and low side referenced output channels. Proprietary HVIC and latch immune CMOS technologies enable ruggedized monolithic construction. The logic input is compatible with standard CMOS or LSTTL output, down to 3.3V

logic. The output drivers feature a high pulse current buffer stage designed for minimum driver cross-conduction. The floating channel can be used to drive an N-channel power MOSFET or IGBT in the high side configuration which operates up to 600 volts.

IR2181/IR2183/IR2184 Feature Comparison

Part	Input logic	Cross-conduction prevention logic	Dead-Time	Ground Pins	Ton/Toff
2181	HIN/LIN	no	none	COM	180/220 ns
21814				VSS/COM	
2183	HIN/LIN	yes	Internal 500ns	COM	180/220 ns
21834			Program 0.4 ~ 5 us	VSS/COM	
2184	IN/S ^D	yes	Internal 500ns	COM	680/270 ns
21844			Program 0.4 ~ 5 us	VSS/COM	

Typical Connection



IR2183(4)(S)&(PbF)

International
IR Rectifier

Absolute Maximum Ratings

Absolute maximum ratings indicate sustained limits beyond which damage to the device may occur. All voltage parameters are absolute voltages referenced to COM. The thermal resistance and power dissipation ratings are measured under board mounted and still air conditions.

Symbol	Definition	Min.	Max.	Units
V_B	High side floating absolute voltage	-0.3	625	V
V_S	High side floating supply offset voltage	$V_B - 25$	$V_B + 0.3$	
V_{HO}	High side floating output voltage	$V_S - 0.3$	$V_B + 0.3$	
V_{CC}	Low side and logic fixed supply voltage	-0.3	25	
V_{LO}	Low side output voltage	-0.3	$V_{CC} + 0.3$	
DT	Programmable dead-time pin voltage (IR21834 only)	$V_{SS} - 0.3$	$V_{CC} + 0.3$	
V_{IN}	Logic input voltage (HIN & \bar{LIN})	$V_{SS} - 0.3$	$V_{SS} + 10$	
V_{SS}	Logic ground (IR21834 only)	$V_{CC} - 25$	$V_{CC} + 0.3$	
dV_S/dt	Allowable offset supply voltage transient	—	50	V/ns
P_D	Package power dissipation @ $T_A \leq +25^\circ C$	—	1.0	W
	(8-lead PDIP)	—	0.625	
	(14-lead PDIP)	—	1.6	
	(14-lead SOIC)	—	1.0	
R_{thJA}	Thermal resistance, junction to ambient	(8-lead PDIP)	125	°C/W
		(8-lead SOIC)	200	
		(14-lead PDIP)	75	
		(14-lead SOIC)	120	
T_J	Junction temperature	—	150	°C
T_S	Storage temperature	-50	150	
T_L	Lead temperature (soldering, 10 seconds)	—	300	

Recommended Operating Conditions

The Input/Output logic timing diagram is shown in figure 1. For proper operation the device should be used within the recommended conditions. The V_S and V_{SS} offset rating are tested with all supplies biased at 15V differential.

Symbol	Definition	Min.	Max.	Units
V_B	High side floating supply absolute voltage	$V_S + 10$	$V_S + 20$	V
V_S	High side floating supply offset voltage	Note 1	600	
V_{HO}	High side floating output voltage	V_S	V_B	
V_{CC}	Low side and logic fixed supply voltage	10	20	
V_{LO}	Low side output voltage	0	V_{CC}	
V_{IN}	Logic input voltage (HIN & \bar{LIN})	V_{SS}	$V_{SS} + 5$	
DT	Programmable dead-time pin voltage (IR21834 only)	V_{SS}	V_{CC}	
V_{SS}	Logic ground (IR21834 only)	-5	5	
T_A	Ambient temperature	-40	125	°C

Note 1: Logic operational for V_S of -5 to +600V. Logic state held for V_S of -5V to $-V_{BS}$. (Please refer to the Design Tip DT97-3 for more details).

Note 2: HIN and \bar{LIN} pins are internally clamped with a 5.2V zener diode.

Dynamic Electrical Characteristics

V_{BIAS} (V_{CC} , V_{BS}) = 15V, V_{SS} = COM, C_L = 1000 pF, T_A = 25°C, DT = V_{SS} unless otherwise specified.



Symbol	Definition	Min.	Typ.	Max.	Units	Test Conditions
t_{on}	Turn-on propagation delay	—	180	270	nsec	$V_S = 0V$
t_{off}	Turn-off propagation delay	—	220	330		$V_S = 0V$ or 600V
MT	Delay matching $ t_{on} - t_{off} $	—	0	35		
t_r	Turn-on rise time	—	40	60		$V_S = 0V$
t_f	Turn-off fall time	—	20	35		$V_S = 0V$
DT	Deadtime: LO turn-off to HO turn-on(DT _{LO-HO}) & HO turn-off to LO turn-on (DT _{HO-LO})	280	400	520		RDT= 0
MDT	Deadtime matching = $ DT_{LO-HO} - DT_{HO-LO} $	4	5	6		μ sec RDT = 200k (IR21834)
		—	0	50		nsec RDT=0
		—	0	600		RDT = 200k (IR21834)

Static Electrical Characteristics

V_{BIAS} (V_{CC} , V_{BS}) = 15V, V_{SS} = COM, DT= V_{SS} and T_A = 25°C unless otherwise specified. The V_{IL} , V_{IH} and I_{IN} parameters are referenced to V_{SS} /COM and are applicable to the respective input leads: HIN and LIN. The V_O , I_O and R_{on} parameters are referenced to COM and are applicable to the respective output leads: HO and LO.

Symbol	Definition	Min.	Typ.	Max.	Units	Test Conditions
V_{IH}	Logic "1" input voltage for HIN & logic "0" for LIN	2.7	—	—	V	$V_{CC} = 10V$ to 20V
V_{IL}	Logic "0" input voltage for HIN & logic "1" for LIN	—	—	0.8		$V_{CC} = 10V$ to 20V
V_{OH}	High level output voltage, $V_{BIAS} - V_O$	—	—	1.2		$I_O = 0A$
V_{OL}	Low level output voltage, V_O	—	—	0.1		$I_O = 0A$
I_{LK}	Offset supply leakage current	—	—	50	μ A	$V_B = V_S = 600V$
I_{QBS}	Quiescent V_{BS} supply current	20	60	150		$V_{IN} = 0V$ or 5V
I_{QCC}	Quiescent V_{CC} supply current	0.4	1.0	1.6		$V_{IN} = 0V$ or 5V
I_{IN+}	Logic "1" input bias current	—	25	60		$HIN = 5V$, $LIN = 0V$
I_{IN-}	Logic "0" input bias current	—	—	1.0	μ A	$HIN = 0V$, $LIN = 5V$
V_{CCUV+} V_{BSUV+}	V_{CC} and V_{BS} supply undervoltage positive going threshold	8.0	8.9	9.8		
V_{CCUV-} V_{BSUV-}	V_{CC} and V_{BS} supply undervoltage negative going threshold	7.4	8.2	9.0		
V_{CCUVH} V_{BSUVH}	Hysteresis	0.3	0.7	—		
I_{O+}	Output high short circuit pulsed current	1.4	1.9	—	A	$V_O = 0V$, $PW \leq 10 \mu s$
I_{O-}	Output low short circuit pulsed current	1.8	2.3	—		$V_O = 15V$, $PW \leq 10 \mu s$





Functional Block Diagrams



Lead Definitions

Symbol	Description
HIN	Logic input for high side gate driver output (HO), in phase (referenced to COM for IR2183 and VSS for IR21834)
LIN	Logic input for low side gate driver output (LO), out of phase (referenced to COM for IR2183 and VSS for IR21834)
DT	Programmable dead-time lead, referenced to VSS. (IR21834 only)
VSS	Logic Ground (21834 only)
V _B	High side floating supply
HO	High side gate driver output
V _S	High side floating supply return
V _{CC}	Low side and logic fixed supply
LO	Low side gate driver output
COM	Low side return

Lead Assignments

 8-Lead PDIP	 8-Lead SOIC
IR2183	IR2183S
 14-Lead PDIP	 14-Lead SOIC
IR21834	IR21834S

IR2183(4)(S)&(PbF)

International
IR Rectifier




Figure 1. Input/Output Timing Diagram





Figure 2. Switching Time Waveform Definitions




Figure 3. Deadtime Waveform Definitions




Figure 4A. Turn-on Propagation Delay vs. Temperature




Figure 4B. Turn-on Propagation Delay vs. Supply Voltage




Figure 5A. Turn-off Propagation Delay vs. Temperature




Figure 5B. Turn-off Propagation Delay vs. Supply Voltage

IR2183(4)(S)&(PbF)

International
IR Rectifier




Figure 6A. Turn-on Rise Time vs. Temperature




Figure 6B. Turn-on Rise Time vs. Supply Voltage




Figure 7A. Turn-off Fall Time vs. Temperature




Figure 7B. Turn-off Fall Time vs. Supply Voltage




Figure 8A. Deadtime vs. Temperature




Figure 8B. Deadtime vs. Supply Voltage




Figure 8C. Deadtime vs. R_{DT}




Figure 9A. Logic "1" Input Voltage vs. Temperature

IR2183(4)(S)&(PbF)

International
IR Rectifier




Figure 9B. Logic "1" Input Voltage vs. Supply Voltage




Figure 10A. Logic "0" Input Voltage vs. Temperature




Figure 10B. Logic "0" Input Voltage vs. Supply Voltage




Figure 11A. High Level Output vs. Temperature




Figure 11B. High Level Output vs. Supply Voltage




Figure 12A. Low Level Output vs. Temperature




Figure 12B. Low Level Output vs. Supply Voltage




Figure 13A. Offset Supply Leakage Current vs. Temperature

IR2183(4)(S)&(PbF)

International
IR Rectifier




Figure 13B. Offset Supply Leakage Current vs. V_B Boost Voltage




Figure 14A. V_{BS} Supply Current vs. Temperature




Figure 14B. V_{BS} Supply Current vs. V_{BS} Floating Supply Voltage




Figure 15A. V_{CC} Supply Current vs. Temperature




Figure 15B. V_{CC} Supply Current vs. V_{CC} Supply Voltage




Figure 16A. Logic "1" Input Bias Current vs. Temperature




Figure 16B. Logic "1" Input Bias Current vs. Supply Voltage




Figure 17A. Logic "0" Input Bias Current vs. Temperature

IR2183(4)(S)&(PbF)

International
IR Rectifier




Figure 17B. Logic "0" Input Bias Current vs. Supply Voltage




Figure 18. V_{CC} and V_{BS} Undervoltage Threshold (+) vs. Temperature




Figure 19. V_{CC} and V_{BS} Undervoltage Threshold (-) vs. Temperature




Figure 20A. Output Source Current vs. Temperature

IR2183(4)(S) & (PbF)




Figure 20B. Output Source Current vs. Supply Voltage




Figure 21A. Output Sink Current vs. Temperature




Figure 21B. Output Sink Current vs. Supply Voltage




Figure 22. IR2183 vs. Frequency (IRFBC20),
 $R_{gate}=33\Omega$, $V_{cc}=15V$

IR2183(4)(S)&(PbF)

International
IR Rectifier




Figure 23. IR2183 vs. Frequency (IRFBC30),
 $R_{gate}=22\Omega$, $V_{cc}=15V$




Figure 24. IR2183 vs. Frequency (IRFBC40),
 $R_{gate}=15\Omega$, $V_{cc}=15V$




Figure 25. IR2183 vs. Frequency (IRFPE50),
 $R_{gate}=10\Omega$, $V_{cc}=15V$




Figure 26. IR21834 vs. Frequency (IRFBC20),
 $R_{gate}=33\Omega$, $V_{cc}=15V$

IR2183(4)(S) & (PbF)




Figure 27. IR21834 vs. Frequency (IRFBC30),
 $R_{\text{gate}}=22\Omega$, $V_{\text{cc}}=15\text{V}$




Figure 28. IR21834 vs. Frequency (IRFBC40),
 $R_{\text{gate}}=15\Omega$, $V_{\text{cc}}=15\text{V}$




Figure 29. IR21834 vs. Frequency (IRFPE50),
 $R_{\text{gate}}=10\Omega$, $V_{\text{cc}}=15\text{V}$




Figure 30. IR2183s vs. Frequency (IRFBC20),
 $R_{\text{gate}}=33\Omega$, $V_{\text{cc}}=15\text{V}$

IR2183(4)(S)&(PbF)

International
IR Rectifier




Figure 31. IR2183s vs. Frequency (IRFBC30),
 $R_{gate}=22\Omega$, $V_{cc}=15V$




Figure 32. IR2183s vs. Frequency (IRFBC40),
 $R_{gate}=15\Omega$, $V_{cc}=15V$




Figure 33. IR2183s vs. Frequency (IRFPE50),
 $R_{gate}=10\Omega$, $V_{cc}=15V$






Figure 34. IR21834s vs. Frequency (IRFBC20),
 $R_{gate}=33\Omega$, $V_{cc}=15V$


IR2183(4)(S) & (PbF)



**Figure 35. IR21834s vs. Frequency (IRFBC30),
 $R_{gate}=22\Omega$, $V_{cc}=15V$**



**Figure 36. IR21834s vs. Frequency (IRFBC 40),
 $R_{gate}=15\Omega$, $V_{cc}=15V$**





**Figure 37. IR21834s vs. Frequency (IRFPE50),
 $R_{gate}=10\Omega$, $V_{cc}=15V$**



IR2183(4)(S)&(PbF)

International
IR Rectifier


Case outlines



IR2183(4)(S) & (PbF)



LEADFREE PART MARKING INFORMATION



ORDER INFORMATION

Basic Part (Non-Lead Free)

8-Lead PDIP IR2183 order IR2183
8-Lead SOIC IR2183S order IR2183S
14-Lead PDIP IR21834 order IR21834
14-Lead SOIC IR21834 order IR21834S

Leadfree Part

8-Lead PDIP IR2183 order IR2183PbF
8-Lead SOIC IR2183S order IR2183SPbF
14-Lead PDIP IR21834 order IR21834PbF
14-Lead SOIC IR21834 order IR21834SPbF

International
IR Rectifier

This product has been designed and qualified for the industrial market.
Qualification Standards can be found on IR's Web Site <http://www.irf.com>

Data and specifications subject to change without notice.

IR WORLD HEADQUARTERS: 233 Kansas St., El Segundo, California 90245 Tel: (310) 252-7105
4/4/2006