



TSV6191, TSV6191A, TSV6192, TSV6192A

Rail-to-rail input/output 10 μ A, 450 kHz
CMOS operational amplifiers

Features

- Rail-to-rail input and output
- Low power consumption: 10 μ A typ at 5 V
- Low supply voltage: 1.5 to 5.5 V
- Gain bandwidth product: 450 kHz typ
- Stable when used in gain configuration
- Low input offset voltage: 800 μ V max (A version)
- Low input bias current: 1 pA typ
- Temperature range: -40 to +85° C

Applications

- Battery-powered applications
- Smoke detectors
- Proximity sensors
- Portable devices
- Signal conditioning
- Active filtering
- Medical instrumentation


Description

The TSV619x family of single and dual operational amplifiers offers low voltage, low power operation and rail-to-rail input and output.

The devices also feature an ultra-low input bias current as well as a low input offset voltage.

The TSV619x have a gain bandwidth product of 450 kHz while consuming only 10 μ A at 5 V. They must be used in a gain configuration (equal or above +4 or -3).

These features make the TSV619x family ideal for sensor interfaces, battery supplied and portable applications, as well as active filtering.



1 Absolute maximum ratings and operating conditions

Table 1. Absolute maximum ratings

Symbol	Parameter	Value	Unit
V_{CC}	Supply voltage ⁽¹⁾	6	V
V_{id}	Differential input voltage ⁽²⁾	$\pm V_{CC}$	V
V_{in}	Input voltage ⁽³⁾	$V_{CC} - 0.2$ to $V_{CC+} + 0.2$	V
T_{stg}	Storage temperature	-65 to +150	°C
R_{thja}	Thermal resistance junction to ambient ⁽⁴⁾⁽⁵⁾		°C/W
	SC70-5	205	
	SOT23-5	250	
	MiniSO-8	190	
	SO-8	125	
T_j	Maximum junction temperature	150	°C
ESD	HBM: human body model ⁽⁶⁾	4	kV
	MM: machine model ⁽⁷⁾	200	V
	CDM: charged device model ⁽⁸⁾	1.5	kV
	Latch-up immunity	200	mA

1. All voltage values, except differential voltage are with respect to network ground terminal.
2. Differential voltages are the non-inverting input terminal with respect to the inverting input terminal.
3. V_{CC} - V_{in} must not exceed 6 V.
4. Short-circuits can cause excessive heating and destructive dissipation.
5. R_{th} are typical values.
6. Human body model: 100 pF discharged through a 1.5 k Ω resistor between two pins of the device, done for all couples of pin combinations with other pins floating.
7. Machine model: a 200 pF cap is charged to the specified voltage, then discharged directly between two pins of the device with no external series resistor (internal resistor < 5 Ω), done for all couples of pin combinations with other pins floating.
8. Charged device model: all pins plus package are charged together to the specified voltage and then discharged directly to ground.

Table 2. Operating conditions

Symbol	Parameter	Value	Unit
V_{CC}	Supply voltage	1.5 to 5.5	V
V_{icm}	Common mode input voltage range	$V_{CC} - 0.1$ to $V_{CC+} + 0.1$	V
T_{oper}	Operating free air temperature range	-40 to +85	°C

2 Electrical characteristics

**Table 3. Electrical characteristics at $V_{CC+} = +1.8\text{ V}$
with $V_{CC-} = 0\text{ V}$, $V_{icm} = V_{CC}/2$, $T_{amb} = 25^\circ\text{ C}$, and R_L connected to $V_{CC}/2$ (unless
otherwise specified)**

Symbol	Parameter	Conditions	Min.	Typ.	Max.	Unit
DC performance						
V _{io}	Offset voltage	TSV619x			4	mV
		TSV619xA			0.8	
		T _{min.} < T _{op} < T _{max.} TSV619x			5	
		T _{min.} < T _{op} < T _{max.} TSV619xA			2	
DV _{io}	Input offset voltage drift			2		μV/°C
I _{io}	Input offset current (V _{out} = V _{cc} /2)			1	10 ⁽¹⁾	pA
		T _{min.} < T _{op} < T _{max.}		1	25	pA
I _{ib}	Input bias current (V _{out} = V _{cc} /2)			1	10 ⁽¹⁾	pA
		T _{min.} < T _{op} < T _{max.}		1	25	pA
CMR	Common mode rejection ratio 20 log (ΔV _{ic} /ΔV _{io})	0 V to 1.8 V, V _{out} = 0.9 V	55	71		dB
		T _{min.} < T _{op} < T _{max.}	53			dB
A _{vd}	Large signal voltage gain	R _L = 10 kΩ, V _{out} = 0.5 V to 1.3 V	78	83		dB
		T _{min.} < T _{op} < T _{max.}	74			dB
V _{OH}	High level output voltage	R _L = 10 kΩ T _{min.} < T _{op} < T _{max.}	35 50	4		mV
V _{OL}	Low level output voltage	R _L = 10 kΩ T _{min.} < T _{op} < T _{max.}		7	35 50	mV
I _{out}	Isink	V _o = 1.8 V T _{min.} < T _{op} < T _{max.}	9 9	13		mA
	Isource	V _o = 0 V T _{min.} < T _{op} < T _{max.}	8 8	10		
I _{CC}	Supply current (per operator)	No load, V _{out} = V _{cc} /2	6.5	9	12	μA
		T _{min.} < T _{op} < T _{max.}	6		12.5	μA
AC performance						
GBP	Gain bandwidth product	R _L = 10 kΩ, C _L = 20 pF		380		kHz
Gain	Minimum gain for stability	Phase margin = 60°, R _f = 10kΩ, R _L = 10 kΩ, C _L = 20 pF, T _{op} = 25° C		5		
SR	Slew rate	R _L = 10 kΩ, C _L = 20 pF, V _{out} = 0.5V to 1.3V		0.06		V/μs
e _n	Equivalent input noise voltage	f = 1 kHz		110		$\frac{nV}{\sqrt{Hz}}$
THD+N	Total harmonic distortion + noise	F _{in} = 1 kHz, A _v = 5, V _{out} = 1 V _{pp} , R _L = 100 kΩ, BW = 22 kHz		0.1		%

1. Guaranteed by design.

Table 4. $V_{CC+} = +3.3\text{ V}$, $V_{CC-} = 0\text{ V}$, $V_{icm} = V_{CC}/2$, $T_{amb} = 25^{\circ}\text{ C}$,
 R_L connected to $V_{CC}/2$ (unless otherwise specified)

Symbol	Parameter		Min.	Typ.	Max.	Unit
DC performance						
V _{io}	Offset voltage	TSV619x TSV619xA			4 0.8	mV
		T _{min} <T _{op} <T _{max} TSV619x T _{min} <T _{op} <T _{max} TSV619xA			5 2	
DV _{io}	Input offset voltage drift			2		μV/°C
I _{io}	Input offset current			1	10 ⁽¹⁾	pA
		T _{min.} < T _{op} < T _{max.}		1	25	pA
I _{ib}	Input bias current			1	10 ⁽¹⁾	pA
		T _{min.} < T _{op} < T _{max.}		1	25	pA
CMR	Common mode rejection ratio 20 log (ΔV _{ic} /ΔV _{io})	0 V to 3.3 V, V _{out} = 1.75 V	61	76		dB
		T _{min.} < T _{op} < T _{max.}	58			dB
A _{vd}	Large signal voltage gain	R _L = 10 kΩ, V _{out} = 0.5 V to 2.8 V	85	92		dB
		T _{min.} < T _{op} < T _{max.}	83			dB
V _{OH}	High level output voltage	R _L = 10 kΩ T _{min.} < T _{op} < T _{max.}	35 50	5		mV
V _{OL}	Low level output voltage	R _L = 10 kΩ T _{min.} < T _{op} < T _{max.}		10	35 50	mV
I _{out}	Isink	V _o = V _{CC} T _{min.} < T _{op} < T _{max.}	37 35	44		mA
	Isource	V _o = 0 V T _{min.} < T _{op} < T _{max.}	32 30	38		
I _{CC}	Supply current (per operator)	No load, V _{out} = V _{CC} /2	6.5	9.5	12.5	μA
		T _{min.} < T _{op} < T _{max.}	6		13	μA
AC performance						
GBP	Gain bandwidth product	R _L = 10 kΩ, C _L = 20 pF		400		kHz
Gain	Minimum gain for stability	Phase margin = 60°, R _f = 10kΩ, R _L = 10 kΩ, C _L = 20 pF, T _{op} = 25° C		5		V/V
SR	Slew rate	R _L = 10 kΩ, C _L = 20 pF, V _{out} = 0.5V to 2.8V		0.07		V/μs
e _n	Equivalent input noise voltage	f = 1 kHz		110		$\frac{nV}{\sqrt{Hz}}$

1. Guaranteed by design.

Table 5. $V_{CC+} = +5\text{ V}$, $V_{CC-} = 0\text{ V}$, $V_{icm} = V_{CC}/2$, $T_{amb} = 25^{\circ}\text{ C}$, R_L connected to $V_{CC}/2$
(unless otherwise specified)

Symbol	Parameter		Min.	Typ.	Max.	Unit
DC performance						
V _{io}	Offset voltage	TSV619x TSV619xA			4 0.8	mV
		T _{min} <T _{op} <T _{max} TSV619x T _{min} <T _{op} <T _{max} TSV619xA			5 2	
DV _{io}	Input offset voltage drift			2		μV/°C
I _{io}	Input offset current			1	10 ⁽¹⁾	pA
		T _{min.} < T _{op} < T _{max.}		1	25	pA
I _{ib}	Input bias current			1	10 ⁽¹⁾	pA
		T _{min.} < T _{op} < T _{max.}		1	25	pA
CMR	Common mode rejection ratio 20 log (ΔV _{ic} /ΔV _{io})	0 V to 5 V, V _{out} = 2.5 V	64	80		dB
		T _{min.} < T _{op} < T _{max.}	63			dB
SVR	Supply voltage rejection ratio 20 log (ΔV _{cc} /ΔV _{io})	V _{cc} = 1.8 to 5 V	76	93		dB
		T _{min.} < T _{op} < T _{max.}	74			dB
A _{vd}	Large signal voltage gain	R _L = 10 kΩ, V _{out} = 0.5 V to 4.5 V	88	93		dB
		T _{min} <T _{op} <T _{max}	85			dB
V _{OH}	High level output voltage	R _L = 10 kΩ T _{min.} < T _{op} < T _{max.}	35 50	7		mV
V _{OL}	Low level output voltage	R _L = 10 kΩ T _{min.} < T _{op} < T _{max.}		16	35 50	mV
I _{out}	Isink	V _o = V _{CC} T _{min.} < T _{op} < T _{max.}	52 42	57		mA
	Isource	V _o = 0 V T _{min.} < T _{op} < T _{max.}	58 49	63		
I _{CC}	Supply current (per operator)	No load, V _{out} = V _{CC} /2	7.5	10.5	14	μA
		T _{min.} < T _{op} < T _{max.}	7		15	μA
AC performance						
GBP	Gain bandwidth product	R _L = 10 kΩ, C _L = 20 pF		450		kHz
Gain	Minimum gain for stability	Phase margin = 60°, R _f = 10kΩ, R _L = 10 kΩ, C _L = 20 pF, T _{op} = 25° C		5		V/V
SR	Slew rate	R _L = 10 kΩ, C _L = 20 pF, V _{out} = 0.5V to 4.5V		0.08		V/μs
e _n	Equivalent input noise voltage	f = 1 kHz		105		$\frac{nV}{\sqrt{Hz}}$
THD+N	Total harmonic distortion + noise	F _{in} = 1 kHz, A _v = 5, V _{out} = 1 V _{pp} , R _L = 100 kΩ BW = 22kHz		0.1		%

1. Guaranteed by design.

Figure 1. Supply current vs. supply voltage at $V_{icm} = V_{CC}/2$




Figure 2. Output current vs. output voltage at $V_{CC} = 1.5\text{ V}$




Figure 3. Output current vs. output voltage at $V_{CC} = 5\text{ V}$




Figure 4. Voltage gain and phase vs. frequency at $V_{CC} = 1.5\text{ V}$




Figure 5. Voltage gain and phase vs. frequency at $V_{CC} = 5\text{ V}$




Figure 6. Positive slew rate vs. time at $V_{CC} = 1.5\text{ V}$,




Figure 7. Negative slew rate vs. time at $V_{CC} = 1.5\text{ V}$




Figure 8. Positive slew rate vs. time at $V_{CC} = 5.5\text{ V}$




Figure 9. Negative slew rate vs. time, $V_{CC} = 5.5\text{ V}$, $C_{Load} = 100\text{ pF}$, $R_{Load} = 100\text{ k}\Omega$




Figure 10. Noise vs. frequency at $V_{CC} = 5\text{ V}$, $T = 25\text{ C}$




Figure 11. Distortion + noise vs. frequency





Figure 12. Distortion + noise vs. output voltage



3 Application information

3.1 Operating voltages

The TSV619x can operate from 1.5 to 5.5 V. Their parameters are fully specified for 1.8, 3.3 and 5 V power supplies. However, the parameters are very stable in the full V_{CC} range and several characterization curves show the TSV619x characteristics at 1.5 V. Additionally, the main specifications are guaranteed in extended temperature ranges from -40°C to $+85^{\circ}\text{C}$.

3.2 Rail-to-rail input

The TSV619x are built with two complementary PMOS and NMOS input differential pairs. The devices have a rail-to-rail input, and the input common mode range is extended from $V_{CC-} - 0.1\text{ V}$ to $V_{CC+} + 0.1\text{ V}$. The transition between the two pairs appears at $V_{CC+} - 0.7\text{ V}$. In the transition region, the performance of CMRR, PSRR, V_{io} and THD is slightly degraded (as shown in [Figure 13](#) and [Figure 14](#) for V_{io} vs. V_{icm}).

Figure 13. Input offset voltage vs input common mode at $V_{CC} = 1.5\text{ V}$





Figure 14. Input offset voltage vs input common mode at $V_{CC} = 5\text{ V}$



The device is guaranteed without phase reversal.

3.3 Rail-to-rail output

The operational amplifiers' output levels can go close to the rails: less than 35 mV above GND rail and less than 35 mV below V_{CC} rail when connected to 10 k Ω load to $V_{CC}/2$.

3.4 PCB layouts

For correct operation, it is advised to add 10 nF decoupling capacitors as close as possible to the power supply pins.

3.5 Macromodel

An accurate macromodel of the TSV619x is available on STMicroelectronics' web site at www.st.com. This model is a trade-off between accuracy and complexity (that is, time simulation) of the TSV619x operational amplifiers. It emulates the nominal performances of a typical device within the specified operating conditions mentioned in the datasheet. It also helps to validate a design approach and to select the right operational amplifier, *but it does not replace on-board measurements*.

4 Package information

In order to meet environmental requirements, ST offers these devices in different grades of ECOPACK[®] packages, depending on their level of environmental compliance. ECOPACK[®] specifications, grade definitions and product status are available at: www.st.com. ECOPACK[®] is an ST trademark.

4.1 SOT23-5 package information

Figure 15. SOT23-5 package mechanical drawing




Table 6. SOT23-5 package mechanical data

Ref.	Dimensions					
	Millimeters			Inches		
	Min.	Typ.	Max.	Min.	Typ.	Max.
A	0.90	1.20	1.45	0.035	0.047	0.057
A1			0.15			0.006
A2	0.90	1.05	1.30	0.035	0.041	0.051
B	0.35	0.40	0.50	0.013	0.015	0.019
C	0.09	0.15	0.20	0.003	0.006	0.008
D	2.80	2.90	3.00	0.110	0.114	0.118
D1		1.90			0.075	
e		0.95			0.037	
E	2.60	2.80	3.00	0.102	0.110	0.118
F	1.50	1.60	1.75	0.059	0.063	0.069
L	0.10	0.35	0.60	0.004	0.013	0.023
K	0 degrees		10 degrees			

4.2 SC70-5 (SOT323-5) package information

Figure 16. SC70-5 (SOT323-5) package mechanical drawing




Table 7. SC70-5 (SOT323-5) package mechanical data

Ref	Dimensions					
	Millimeters			Inches		
	Min	Typ	Max	Min	Typ	Max
A	0.80		1.10	0.315		0.043
A1			0.10			0.004
A2	0.80	0.90	1.00	0.315	0.035	0.039
b	0.15		0.30	0.006		0.012
c	0.10		0.22	0.004		0.009
D	1.80	2.00	2.20	0.071	0.079	0.087
E	1.80	2.10	2.40	0.071	0.083	0.094
E1	1.15	1.25	1.35	0.045	0.049	0.053
e		0.65			0.025	
e1		1.30			0.051	
L	0.26	0.36	0.46	0.010	0.014	0.018
<	0°		8°			

4.3 SO-8 package information

Figure 17. SO-8 package mechanical drawing




Table 8. SO-8 package mechanical data

Ref.	Dimensions					
	Millimeters			Inches		
	Min.	Typ.	Max.	Min.	Typ.	Max.
A			1.75			0.069
A1	0.10		0.25	0.004		0.010
A2	1.25			0.049		
b	0.28		0.48	0.011		0.019
c	0.17		0.23	0.007		0.010
D	4.80	4.90	5.00	0.189	0.193	0.197
E	5.80	6.00	6.20	0.228	0.236	0.244
E1	3.80	3.90	4.00	0.150	0.154	0.157
e		1.27			0.050	
h	0.25		0.50	0.010		0.020
L	0.40		1.27	0.016		0.050
L1		1.04			0.040	
k	1°		8°	1°		8°
ccc			0.10			0.004

4.4 MiniSO-8 package information

Figure 18. MiniSO-8 package mechanical drawing




Table 9. MiniSO-8 package mechanical data

Ref.	Dimensions					
	Millimeters			Inches		
	Min.	Typ.	Max.	Min.	Typ.	Max.
A			1.1			0.043
A1	0		0.15	0		0.006
A2	0.75	0.85	0.95	0.030	0.033	0.037
b	0.22		0.40	0.009		0.016
c	0.08		0.23	0.003		0.009
D	2.80	3.00	3.20	0.11	0.118	0.126
E	4.65	4.90	5.15	0.183	0.193	0.203
E1	2.80	3.00	3.10	0.11	0.118	0.122
e		0.65			0.026	
L	0.40	0.60	0.80	0.016	0.024	0.031
L1		0.95			0.037	
L2		0.25			0.010	
k	0°		8°	0°		8°
ccc			0.10			0.004

5 Ordering information

Table 10. Order codes

Order code	Temperature range	Package	Packing	Marking
TSV6191ILT	-40° C to 85° C	SOT23-5	Tape & reel	K110
TSV6191AILT				K115
TSV6191ICT		SC70-5		K10
TSV6191AICT				K13
TSV6192ID/DT		SO-8	Tube & tape & reel	V6192I
TSV6192AID/DT				V6192AI
TSV6192IST		MiniSO-8	Tape & reel	K130
TSV6192AIST				K129

6 Revision history

Table 11. Document revision history

Date	Revision	Changes
04-Oct-2010	1	Initial release.

Please Read Carefully:

Information in this document is provided solely in connection with ST products. STMicroelectronics NV and its subsidiaries ("ST") reserve the right to make changes, corrections, modifications or improvements, to this document, and the products and services described herein at any time, without notice.

All ST products are sold pursuant to ST's terms and conditions of sale.

Purchasers are solely responsible for the choice, selection and use of the ST products and services described herein, and ST assumes no liability whatsoever relating to the choice, selection or use of the ST products and services described herein.

No license, express or implied, by estoppel or otherwise, to any intellectual property rights is granted under this document. If any part of this document refers to any third party products or services it shall not be deemed a license grant by ST for the use of such third party products or services, or any intellectual property contained therein or considered as a warranty covering the use in any manner whatsoever of such third party products or services or any intellectual property contained therein.

UNLESS OTHERWISE SET FORTH IN ST'S TERMS AND CONDITIONS OF SALE ST DISCLAIMS ANY EXPRESS OR IMPLIED WARRANTY WITH RESPECT TO THE USE AND/OR SALE OF ST PRODUCTS INCLUDING WITHOUT LIMITATION IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE (AND THEIR EQUIVALENTS UNDER THE LAWS OF ANY JURISDICTION), OR INFRINGEMENT OF ANY PATENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT.

UNLESS EXPRESSLY APPROVED IN WRITING BY AN AUTHORIZED ST REPRESENTATIVE, ST PRODUCTS ARE NOT RECOMMENDED, AUTHORIZED OR WARRANTED FOR USE IN MILITARY, AIR CRAFT, SPACE, LIFE SAVING, OR LIFE SUSTAINING APPLICATIONS, NOR IN PRODUCTS OR SYSTEMS WHERE FAILURE OR MALFUNCTION MAY RESULT IN PERSONAL INJURY, DEATH, OR SEVERE PROPERTY OR ENVIRONMENTAL DAMAGE. ST PRODUCTS WHICH ARE NOT SPECIFIED AS "AUTOMOTIVE GRADE" MAY ONLY BE USED IN AUTOMOTIVE APPLICATIONS AT USER'S OWN RISK.

Resale of ST products with provisions different from the statements and/or technical features set forth in this document shall immediately void any warranty granted by ST for the ST product or service described herein and shall not create or extend in any manner whatsoever, any liability of ST.

ST and the ST logo are trademarks or registered trademarks of ST in various countries.

Information in this document supersedes and replaces all information previously supplied.

The ST logo is a registered trademark of STMicroelectronics. All other names are the property of their respective owners.

© 2010 STMicroelectronics - All rights reserved

STMicroelectronics group of companies

Australia - Belgium - Brazil - Canada - China - Czech Republic - Finland - France - Germany - Hong Kong - India - Israel - Italy - Japan - Malaysia - Malta - Morocco - Philippines - Singapore - Spain - Sweden - Switzerland - United Kingdom - United States of America

www.st.com

