

Discontinued Product—Support Information Only

This literature was published years prior to the establishment of Agilent Technologies as a company independent from Hewlett-Packard and describes products or services now available through Agilent. It may also refer to products/services no longer supported by Agilent. We regret any inconvenience caused by obsolete information. For the latest information on Agilent's test and measurement products go to:


www.agilent.com/find/products

Or in the US, call Agilent Technologies at 1-800-452-4844 (8am–8pm EST)



HP 11835A Data Buffer Option 001- GSM Option 002 - NADC, JDC

Technical Data



The HP 11835A Data Buffer
with HP 8657A Option 001

Configurable buffer designed to provide a programmable, serial bit stream and clock.

The HP 11835A Data Buffer is designed to be a configurable data output device. Its primary function is to buffer data from a computer, and output the data as a serial bit stream. The HP 11835A can output this serial data at any rate from dc to approximately 4 MHz with a user supplied bit clock. Optionally, an internal reference board will provide the bit clock used by the GSM digital cellular system (Option 001), or the bit or symbol clock used in the North American Digital Cellular System and the Japanese Digital Cellular System (Option 002).

In addition, the HP 11835A has a large memory which can be configured as a programmable state machine, allowing it to support digital mobile radio applications utilizing TDMA

techniques. The HP 11835A also can drive a fast-hopping signal generator such as the HP 8662A-H25 to simulate frequency hopping. Flexibility and configurability make the HP 11835A the perfect choice for testing new digital mobile communication systems.

Data is downloaded to the HP 11835A via the included GPIO cable (General Purpose Input output) from an external controller (HP 9000 Series 300 with GPIO interface card). The data for the active timeslot(s) is stored in a large first-in, first-out (FIFO) RAM memory. The FIFO memory consists of two banks each having a capacity of 1.024 Mbits. The FIFO memory can be loaded from GPIO while the active data is clocked out. This allows the HP

11835A to continuously output changing data during the active timeslot(s) to simulate radio transmissions. In addition to the FIFO memory, there is a 128K x 16 bit frame control RAM. This memory essentially implements a state machine which controls the operation of the HP 11835A. The frame control RAM outputs data (stored during configuration) during inactive timeslot(s), clocks the memory (64K x 8 bit) used for the Hop Control Bus, and selects the FIFO output as the data source during the active timeslot(s). Three additional frame control RAM outputs are available on the rear-panel as programmable outputs with bit period resolution.

HP 11835A SPECIFICATIONS

Inputs (TTL levels)

Bit Clock Input: BNC, rear-panel.

GPIO Input: 50-pin, front-panel.

Trigger Input: BNC, rear-panel.

Outputs (TTL levels)

Data Output: BNC, front-panel.

Clock Output: BNC, front-panel.

Program Outputs: 25-pin, front-panel.

Parallel Bus Output: 25-pin, rear-panel.

Hop Control Bus: 50-pin, rear-panel.

Programmable Outputs: 3 BNCs, rear-panel.

Option 001 Specifications

Option 001 adds a reference board to generate the required bit clock (270.833 kHz) for use in the GSM digital cellular system.

Reference Modes: Reference Lock, Bit Clock Lock, Frame Clock Lock, or Free Run.

Inputs: (rear panel BNCs)

Reference: 1, 2, 5, 10, 13 MHz, >0 dBm (50Q nominal).

Frame Clock: 216.67 Hz, TTL levels.

Bit Clock: 270.833 kHz, TTL levels.

Outputs: (rear panel BNCs) 10 MHz, 13 MHz, 270.833 kHz (Bit Clock), 216.67 Hz (Frame Clock)

Option 002 Specifications

Option 002 adds a reference board to generate the required symbol or bit clocks for use in the NADC (North American Digital Cellular) system or the JDC (Japanese Digital Cellular) system.

Reference Modes: Reference Lock, Bit Clock Lock, Symbol Clock Lock, or Free Run.

Reference Input (rear panel BNC): accepts

21 kHz, 24.3 kHz, 42 kHz, 48.6 kHz at TTL levels or 1 MHz, 2 MHz, 5 MHz, or 10 MHz into 50Q.

Outputs (rear panel BNCs):

Reference: 10 MHz (50Q nominal).

Symbol Clock: 24.3 kHz or 21 kHz, TTL levels.

Bit Clock: 48.6 kHz or 42 kHz, TTL levels.

Frame Clock: 25 Hz or 50 Hz, TTL levels.

General

Operating Temperature Range: 0° to +55°C.

Storage Temperature Range: -55° to +75° C.

Power Requirements: 90 to 264 volts from 48 to 66 Hz; 75 VA maximum. Weight: Net 6 kg (14 lb); shipping 11 kg (24 lb).

Dimensions: 88.1H x 425W x 346D mm. (3.5 x 16.75 x 13.6 inches).

Cables: includes GPIO cable to connect HP 11835A to host computer and a ribbon cable to connect the HP 11835A to a HP 8662-H25 Fast-Hop Signal Generator.

Ordering Information

HP 11835A Data Buffer

Option 001 - GSM Reference*

Option 002 - NADC/JDC Reference*

*Only one option can be ordered

For more information on Hewlett-Packard Test & Measurement products, applications or services please call your local Hewlett-Packard sales offices. A current listing is available via Web through Access HP at <http://www.hp.com>. If you do not have access to the internet please contact one of the HP centers listed below and they will direct you to your nearest HP representative.

United States:

Hewlett-Packard Company
Test and Measurement Organization
5301 Stevens Creek Blvd.
Bldg. 51L-SC
Santa Clara, CA 95052-8059
1- 800-452-4844

Canada:

Hewlett-Packard Canada Ltd.
5150 Spectrum Way
Mississauga, Ontario
L4W 5G1
(905) 206- 4725

Europe:

Hewlett-Packard
European Marketing Centre
P.O. Box 999
1180 AZ Amstelveen
The Netherlands

Japan:

Hewlett-Packard Japan Ltd.
Measurement Assistance Center
9-1, Takakura-cho, Hachioji-shi,
Tokyo 192, Japan
(81) 426 48 0722
Fax (81) 426 48 1073

Latin America:

Hewlett-Packard
Latin American Region Headquarters
5200 Blue Lagoon Drive
9th Floor
Miami, Florida 33126 U.S.A.
(305) 267 4245/4220

Australia/New Zealand:

Hewlett-Packard Australia Ltd.
31-41 Joseph Street
Blackburn, Victoria 3130
Australia
1 800 629 485

Asia Pacific:

Hewlett-Packard Asia Pacific Ltd.
17-21/F Shell Tower, Times Square,
1 Matheson Street, Causeway Bay,
Hong Kong
Fax: (852) 2506 9285

Data subject to change

©Hewlett-Packard Company 1996

Printed in U.S.A. 12/96

5091-1239E