

Technical Data Sheet

CAR15A Car/Truck Power Adapter



15 Watt automobile power adapter

Features:

- Wide input voltage range
- Max. output power 15 Watt
- Car/Truck input connector

Applications

- Suitable for use with PDA's, GSM & GPRS navigation systems, handheld devices (e.g. payment terminals) etc.

Specification

Input

Voltage range	9 - 32VDC
Standby current	typical 62mA @ 9V input typical 36mA @ 32V input
Input fuse	3.15A
Protection	Reverse polarity (input fuse)

Environmental

Cooling	convection cooled
Temperature	Operating: -20°C to 40°C Non-operating -40°C to 85°C
Pressure & altitude	Operating: 1200hPa to 570hPa max. 4600m above sea level Non-operating: 1200hPa to 115hPa max. 15000m above sea level
Humidity	5 to 95% r.H., non-condensing

Output

Voltage range	10 – 15V
Power	15W cont.
Initial set tolerance	±3% max.
Load regulation ⁽¹⁾	-4% max.
Line regulation	±1% max.
Ripple & Noise ⁽²⁾	< 90mVpk-pk
Current Limit	Constant Current
Protection	Short circuit Over temperature protection

General

Input connector	Cigarette lighter adapter
Output connector	Customer-specific
Efficiency ⁽³⁾	typical 85% at 100% load
MTBF	>20000h @ 25°C ambient temperature and G ₈ per MIL-HDBK217F
Green procurement	WEEE RoHS
Indicator	Single green LED
Ingress protection rating	IEC60529, IP40

Technical Data Sheet

CAR15A Car/Truck Power Adapter



Safety & EMC

Regulatory approvals	Europe	CE
Electromagnetic emissions	Europe	EN55022 class B
Electromagnetic Immunity	ESD immunity	IEC61000-4-2, 4kV contact, 8kV air
	Electromagnetic field immunity	IEC61000-4-3, 80-1000MHz, 10V/m, modulation 80%/200Hz
	Electrical fast transient/burst immunity test	IEC61000-4-4, +/-1kV, 5/50ns
	Surge immunity test	IEC61000-4-5, +/-1kV, 1.2/50(8/20) μ s
	Conducted Immunity	IEC61000-4-6, 0.15-230MHz, 10V, 80%, 1KHz, AM
	UNECE vehicle regulation	E13 ECE Reg. 10

- other approvals on request

Mechanical Details

Housing dimensions (LxWxH)	61 x 41 x 29mm, without cables and connectors
Input cable length	100cm $\pm$ 5%
Output cable length	180cm $\pm$ 5%
Weight	44g, without cables and connectors

Notes

1. Load regulation is measured at the output connector and includes the voltage drop across the output cable.
2. Measured with a 0.1 μ F ceramic and a 10 μ F electrolytic capacitors across the output terminals. The oscilloscope bandwidth is set at 20MHz a co-axial cable will be used to measure it. The test condition is maximum load.
3. Power losses of input and output cables are not considered here.

Germany / Headquarters	France	USA	Hong Kong / China
RRC power solutions GmbH Technologiepark 1 D-66424 Homburg / Saar	RRC power solutions SAS 69, rue Louise Michel F-92300 Levallois-Perret	RRC power solutions Inc. 18340 Yorba Linda Blvd., Suite 107-437 Yorba Linda, CA 92886-4104	RRC power solutions Ltd. 9/F Park Tower, 15 Austin Road Tsim Sha Tsui, Kowloon, Hong Kong
Tel.: +49 6841 98090 Fax: +49 6841 9809280 Email: sales@rrc-ps.de Web: www.rrc-ps.de	Tel.: +33 13005 6100 Fax: +33 13005 6101 Email: france@rrc-ps.com Web: www.rrc-ps.com	Tel.: +1 714 777 3604 Fax: +1 714 777 3658 Email: usa@rrc-ps.com Web: www.rrc-ps.com	Tel.: +852 2376 0106 Fax: +852 2376 0107 Email: hkrrc@rrc-ps.cn Web: www.rrc-ps.com