

ISOLATED DC/DC CONVERTERS

48 Vdc Input 68 Vdc /1.2 A Output

bel
POWER PRODUCTS

0RXW-80T68L

RoHS Compliant

Rev.A

- Fixed Frequency (230 kHz)
- Isolated
- High Efficiency
- Output Voltage Trim
- Input Under-Voltage Lockout
- Low Cost
- UL60950-1 Recognized(UL/cUL)
- Output Over-Voltage Shut Down
- Over Temperature Protection
- SCP/OCP
- Remote On/Off
- Excellent Thermal Performance
- Basic Insulation



Description

The 0RXW-80T68L is an isolated dc/dc converter that operates from a nominal 48 Vdc source. This unit provides up to 86 W of output power from a nominal 48 Vdc input. This unit is designed to be highly efficient and low cost. The converter is provided in an industry standard quarter brick package.

Part Selection

Output Voltage	Input Voltage	Max. Output Current	Max. Output Power	Typical Efficiency	Model Number
68 Vdc	36 Vdc - 75 Vdc	1.2 A	86 W	92.5%	0RXW-80T68L

Notes: 1. Add "G" suffix at the end of the model number to indicate "Tray Packaging".

2. All part numbers above indicate RoHS 6. Change the second letter "R" to "7" for RoHS 5 part numbers.

Absolute Maximum Ratings

Parameter	Min	Typ	Max	Notes
Input Voltage (continuous)	-0.3 V	-	80 V	
Remote On/Off	-0.3 V	-	15 V	
I/O Isolation Voltage	-	-	2200 V	
Ambient Temperature	-40 °C	-	85 °C	
Storage Temperature	-55 °C	-	125 °C	

Note: All specifications are typical at 25 °C unless otherwise stated.

Input Specifications

Parameter	Min	Typ	Max	Notes
Input Voltage	36 V	48 V	75 V	
Input Current (no load)	-	40 mA	60 mA	
Input Current (full load)	-	-	2.7 A	
Remote Off Input Current	-	10 mA	20 mA	
Input Reflected Ripple Current (pk-pk)	-	15 mA	30 mA	With simulated source impedance of 12 uH, 5 Hz to 20 MHz; use a 100uF/100 V electrolytic capacitor with ESR = 1 ohm max at 200 kHz
Input Reflected Ripple Current (rms)	-	5 mA	10 mA	
I ² t Inrush Current Transient	-	TBD	-	
Turn-on Voltage Threshold	32 V	33.5 V	35 V	
Under Voltage Threshold	30 V	31.5 V	33 V	

Note: All specifications are typical at nominal input, full load at 25 °C unless otherwise stated

ISOLATED DC/DC CONVERTERS

48 Vdc Input 68 Vdc /1.2 A Output



Output Specifications

Parameter		Min	Typ	Max	Notes	
Output Voltage Set Point		67.5 V	68.0 V	68.5 V	V _{in} =48 V, I _o =100%Load	
Line Regulation		-	0.25%Vo	0.5%Vo		
Load Regulation		-	0.05%Vo	0.5%Vo		
Regulation Over Temperature (-40 °C to 85 °C)		-	-	0.02%Vo/C		
Output Current		0 A	-	1.2 A		
Current Limit Threshold (V _O = 90% V _{O, nom})		1.32 A	1.5 A	1.62 A		
Ripple and Noise (rms)		-	40 mV	60 mV	0-20 MHz BW, with a 1μF ceramic capacitor and a 100 uF Aluminum cap at output.	
Ripple and Noise (pk-pk)		-	80 mV	150 mV		
Turn on Time		-	-	500 mS		
Rise Time		-	400 mS	600 mS		
Overshoot at Turn on		-	0%	3%		
Output Capacitance		100 uF	1500 uF	-		
Transient Response						
50% ~ 75% Max Load	Overshoot	V _O =68 V	-	800 mV	1500 mV	di/dt=0.1A/us, V _{in} =48 V, T _a =25 °C, with a 1 μF ceramic capacitor and a 100 uF Aluminum cap at output.
	Settling Time		-	3 mS	5 mS	
75% ~ 50% Max Load	Overshoot		-	800 mV	1500 mV	
	Settling Time		-	3 mS	5 mS	

Note: All specifications are typical at nominal input, full load at 25 °C unless otherwise stated.

General Specifications

Parameter	Min	Typ	Max	Notes
Efficiency	90%	92.5%	-	V _{in} =48 V, full load
Switching Frequency	200 kHz	230 kHz	250 kHz	
Isolation Capacitance	-	3300 pF	-	
Output Voltage Trim Range	57 V	-	72 V	
Over Temperature Protection	-	120 °C	-	
Over Voltage Protection	72.5 V	-	76 V	V _{in} =48 V, I _o =full load
MTBF	-	TBD	-	Calculated Per Bell Core SR-332 (V _{in} =48 V, V _o =68 V, I _o =0.96 A, T _a = 25 °C)
Dimensions Inches (L × W × H) Millimeters (L × W × H)	2.28 x 1.45 x 0.50 57.88 x 36.83 x 12.70			
Weight	-	TBD	-	

Note: All specifications are typical at 25 °C unless otherwise stated.

ISOLATED DC/DC CONVERTERS

48 Vdc Input 68 Vdc /1.2 A Output



Control Specifications



Parameter	Min	Typ	Max	Notes
Remote On/Off				
Signal Low (Unit On)	Active Low	-0.3 V	-	The remote on/off pin open, Unit Off.
Signal High (Unit Off)		3 V	-	

Output Trim Equations


Equations for calculating the trim resistor are shown below. The Trim Down resistor should be connected between the Trim pin and Vout pin. The Trim Up resistor should be connected between the Trim pin and the GND pin. Only one of the resistors should be used for any given application.

$$R_{trimdown} = \frac{65.5 * 65.5}{\Delta U} - 73(K\Omega)$$

$$R_{trimup} = \frac{163.75}{\Delta U} - 7.5(K\Omega)$$



Efficiency Data




ISOLATED DC/DC CONVERTERS


48 Vdc Input 68 Vdc /1.2 A Output

bel
POWER PRODUCTS

Thermal Derating Curve




Open-frame module




The module is covered with a heat sink

Ripple and Noise Waveform




Note: Ripple and noise at full load, 48 V input, 68 V/1.2 A output, with a 1 µF ceramic cap and a 100 µF Aluminum cap at output, and Ta=25 °C.

Transient Response Waveforms



50%-75% Load Transients at Vin=48 V, Vo=68 V



75%-50% Load Transients at Vin=48 V, Vo=68 V


Note: Transients response with a 1 µF ceramic cap and a 100 µF/100 V Aluminum cap at output, Ta=25 °C.

ISOLATED DC/DC CONVERTERS


48 Vdc Input 68 Vdc /1.2 A Output

bel
POWER PRODUCTS


Mechanical Outline




TOP VIEW




SIDE VIEW



BOTTOM VIEW



BOTTOM VIEW



Pin Connections

Pin	Function
1	Vin(+)
2	On/OFF
3	Vin(-)
4	Vo(-)
5	Sense(-)
6	Trim
7	Sense(+)
8	Vo(+)

RoHS Compliance

Complies with the European Directive 2002/95/EC, calling for the elimination of lead and other hazardous substances from electronic products.



©2007 Bel Fuse Inc. Specifications subject to change without notice. 031407

CORPORATE

Bel Fuse Inc.
206 Van Vorst Street
Jersey City, NJ 07302
Tel 201-432-0463
Fax 201-432-9542
www.belfuse.com

FAR EAST

Bel Fuse Ltd.
8F/ 8 Luk Hop Street
San Po Kong
Kowloon, Hong Kong
Tel 852-2328-5515
Fax 852-2352-3706
www.belfuse.com

EUROPE

Bel Fuse Europe Ltd.
Preston Technology Management Centre
Marsh Lane, Suite G7, Preston
Lancashire, PR1 8UD, U.K.
Tel 44-1772-556601
Fax 44-1772-888366
www.belfuse.com