

NON-ISOLATED DC/DC CONVERTERS

12 Vdc Input

Vddq/2 / 8 A Output



Feb. 26, 2010

Bel Power Inc., a subsidiary of Bel Fuse Inc.

VRAF-08xT50

RoHS Compliant

Rev.I

- Non-Isolated
- High Efficiency
- Fixed Frequency
- Low Cost
- Tracking a Reference for Output Voltage
- High Power Density
- Under-Voltage Lockout
- Output Enable
- OCP/SCP
- Current Source/Sink Capability
- Over Voltage Protection (Hiccup Mode)



Description

The Bel VRAF-08xT50 module is a non-isolated, step down dc/dc power converter that operates from a nominal 12 Vdc or wide range 5 Vdc to 13.8 Vdc source. This converter is designed specifically to provide bus termination voltages in applications such as DDR (double data rate) memory where the bus termination voltage must closely track the I/O bus voltage. The converter accepts a reference input and uses this to program its output voltage to 50% of the reference. The unit is packaged in compact single-in-line footprint and provides a maximum 8 A output. Standard features include remote on/off, input under-voltage lockout, output over voltage protection.

Part Selection

Output Voltage	Input Voltage	Max. Output Current	Max. Output Power	Typical Efficiency	Model Number
0.9 V	5.0 V - 13.8 V	8 A	7.2 W	69%	VRAF-08AT50
0.9 V	5.0 V - 13.8 V	8 A	7.2 W	69%	VRAF-08ET50

- Notes:** 1. All part numbers above indicate RoHS 6. Change the second letter "R" to "7" for RoHS 5 part numbers.
2. Add "G" suffix at the end of the model numbers listed above to indicate "Tray Packaging".
3. Part number VRAF-08ET50 is better suited for applications where start up is guaranteed at 5V input.

Absolute Maximum Ratings

Parameter	Min	Typ	Max	Notes
Input Supply Voltage	-0.5 V	-	15 V	
Input Signal Voltage	-0.3 V		5.25 V	
Operating Temperature	0 °C	-	70 °C	
Storage Temperature	-40 °C	-	85 °C	

Note: All specifications are typical at 25 °C unless otherwise stated.

Input Specifications

Parameter	Min	Typ	Max	Notes
Operating Input Voltage				
VRAF-08AT50	5.0 V	12 V	13.8 V	
VRAF-08ET50	5.0 V	12 V	13.8 V	
Input Current (full load)				
VRAF-08AT50	-	-	2.2 A	
VRAF-08ET50	-	-	2.2 A	
Input Current (no load)	-	25 mA	35 mA	
Reference Voltage Range (Vddq)	1.2 V	1.8 V	1.89 V	
Remote Off Input Current	-	7 mA	10 mA	

NON-ISOLATED DC/DC CONVERTERS

12 Vdc Input

Vddq/2 / 8 A Output



Feb. 26, 2010

Bel Power Inc., a subsidiary of Bel Fuse Inc.

Input Specifications (continued)

Parameter	Min	Typ	Max	Notes
Input Reflected Ripple Current (pk-pk)	-	110 mA	180 mA	With simulated source impedance of 1000 nH, 5 Hz to 20 MHz. Use a 100 uF/25 V Tan cap with ESR=0.025 ohm max, at 100 kHz@25°C.
Input Reflected Ripple Current (rms)	-	25 mA	60 mA	
I ² t Inrush Current Transient	-	0.006 A ² s	0.012 A ² s	
Turn on Voltage Threshold	2.6 V	-	3.9 V	
Turn off Voltage Threshold	2.4 V	-	3.7 V	

Notes: 1. All specifications are typical at 25 °C unless otherwise stated.

2. This power module is not internally fused. An input line fuse must always be used.

Output Specifications

Parameter	Min	Typ	Max	Notes	
Output Voltage Set Point	-	Vddq/2	-	Vin=12 V, Iout=full load	
Tracking Tolerance (Vddq/2-Vout)/Vout	-1.5%	-	1.5%		
Load Regulation	-	3 mV	6 mV		
Line Regulation	-	3 mV	6 mV		
Output Current	0 A	-	8 A		
Output DC Current Limit	9.2 A	-	14 A		
Output Ripple and Noise (pk-pk)	-	25 mV	50 mV	Test conditions: 0-20 MHz BW, with a 22 uF / 6.3 V ceramic capacitor at the output.	
Output Ripple and Noise (rms)	-	8 mV	15 mV		
Short Circuit Surge Transient	-	1.1 A ² s	2.2 A ² s		
Turn on Time VRAF-08AT50 VRAF-08ET50	-	2.5 mS 5 mS	5 mS 8 mS	Start up from ENABLE.	
Overshoot at Turn on	-	0%	3%		
Output Capacitance	0 uF	-	2200 uF		
Transient Response					
50% ~ 100% Max Load	Vo =0.9 V	-	100 mV	200 mV	di/dt=0.3 A/uS; Vin12 V; and with a 22 uF / 6.3 V ceramic capacitor at the output.
Settling Time		-	20 uS	50 uS	
100% ~ 50% Max Load		-	100 mV	200 mV	
Settling Time		-	20 uS	50 uS	

Note: All specifications are typical at Vin =12 V, Vddq=1.8 V, Io=8 A, Ta= 25°C unless otherwise stated.

General Specifications

Parameter	Min	Typ	Max	Notes
Efficiency	68%	69%	-	Vin=12 V, Vddq=1.8 V, Io=8 A
Switching Frequency	260 kHz	300 kHz	340 kHz	
MTBF	6,416,286 hours			Calculated Per Bell Core SR-332 (Io = 80% load; Vin=12 V; Ta = 25 °C)
Dimensions Inches (L × W × H) Millimeters (L × W × H)	0.65 x 0.41 x 0.40 16.51 x 10.41 x 10.16			
Weight	-	2.5 g	-	

Note: All specifications are typical at 25 °C unless otherwise stated.

NON-ISOLATED DC/DC CONVERTERS

12 Vdc Input

Vddq/2 / 8 A Output




Feb. 26, 2010

Bel Power Inc., a subsidiary of Bel Fuse Inc.


Control Specifications

Parameter	Min	Typ	Max	Notes
Output Enable				
ENABLE High	2 V	-	5.5 V	Enable Pin open, the module is off.
ENABLE Low	0 V	-	0.8 V	

Efficiency Data



VRAF-08AT50



VRAF-08ET50

NON-ISOLATED DC/DC CONVERTERS

12 Vdc Input


Vddq/2 / 8 A Output




Feb. 26, 2010

Bel Power Inc., a subsidiary of Bel Fuse Inc.

Thermal Derating Curve



The thermal reference point T_{ref} is shown above. For reliable operation this temperature should not exceed 115°C. The output power of the module should not exceed the rated power for the module.



$V_{in}=12\text{ V}$, $V_{ddq}=1.8\text{ V}$

NON-ISOLATED DC/DC CONVERTERS

12 Vdc Input


Vddq/2 / 8 A Output



Feb. 26, 2010


Bel Power Inc., a subsidiary of Bel Fuse Inc.

Ripple and Noise Waveform




Note: Ripple and noise at $V_{in}=12$ V, $V_{ddq}=1.8$ V, $I_o=8$ A, with a 22 μ F/6.3 V X5R ceramic capacitor at the output, $T_a=25$ °C.

Transient Response Waveforms



50% to 100% load step at $V_{in}=12$ V, $V_{ddq}=1.8$ V



100% to 50% load step at $V_{in}=12$ V, $V_{ddq}=1.8$ V

Note: Transient response at $di/dt=0.3$ A/ μ S, with 22 μ F/6.3 V X5R ceramic capacitor at the output, $T_a=25$ °C.


12 Vdc Input Vddq/2 / 8 A Output



Feb. 26, 2010

Bel Power Inc., a subsidiary of Bel Fuse Inc.

Output Tracking



Test condition: $V_{in}=12\text{ V}$, $V_{ddq}=1.8\text{ V}$, $I_o=8\text{ A}$.

NON-ISOLATED DC/DC CONVERTERS

12 Vdc Input


Vddq/2 / 8 A Output



Feb. 26, 2010


Bel Power Inc., a subsidiary of Bel Fuse Inc.

Mechanical Outline




UNIT: INCH [MM]

RECOMMENDED PAD LAYOUT



HOLE SIZE: $\varnothing 0.035 \pm 0.003$ [0.89 $\pm$ 0.08]

PAD SIZE: $\varnothing 0.055 \pm 0.002$ [1.40 $\pm$ 0.05]



Pin Connections

Pin	Function
1	Vin
2	Vddq
3	Vout (Vtt)
4	GND
5	Enable

NON-ISOLATED DC/DC CONVERTERS

12 Vdc Input

Vddq/2 / 8 A Output



Feb. 26, 2010

Bel Power Inc., a subsidiary of Bel Fuse Inc.

Revision History

Date	Revision	Changes Detail	Approval
2010-2-26	I	Update the input range for VRAF-08AT50 and add note 3 for VRAF-08ET50 on first page.	HL

RoHS Compliance

Complies with the European Directive 2002/95/EC, calling for the elimination of lead and other hazardous substances from electronic products.



©2010 Bel Fuse Inc. Specifications subject to change without notice. 022610

CORPORATE

Bel Fuse Inc.
206 Van Vorst Street
Jersey City, NJ 07302
Tel 201-432-0463
Fax 201-432-9542
www.belfuse.com

FAR EAST

Bel Fuse Ltd.
8F/ 8 Luk Hop Street
San Po Kong
Kowloon, Hong Kong
Tel 852-2328-5515
Fax 852-2352-3706
www.belfuse.com

EUROPE

Bel Fuse Europe Ltd.
Preston Technology Management Centre
Marsh Lane, Suite G7, Preston
Lancashire, PR1 8UD, U.K.
Tel 44-1772-556601
Fax 44-1772-888366
www.belfuse.com