


J309 / J310 / MMBFJ309 / MMBFJ310 N-Channel RF Amplifier

Features

- This device is designed for VHF/UHF amplifier, oscillator and mixer applications.
- As a common gate amplifier, 16 dB at 100 MHz and 12 dB at 450 MHz can be realized.
- Sourced from Process 92.
- Source & Drain are interchangeable.



Absolute Maximum Ratings * $T_a = 25^\circ\text{C}$ unless otherwise noted

Symbol	Parameter	Value	Units
V_{DS}	Drain-Source Voltage	25	V
V_{GS}	Gate-Source Voltage	-25	V
I_{GF}	Forward Gate Current	10	mA
T_J, T_{stg}	Operating and Storage Junction Temperature Range	- 55 to +150	$^\circ\text{C}$

* These ratings are limiting values above which the serviceability of any semiconductor device may be impaired.

NOTES:

- 1) These ratings are based on a maximum junction temperature of 150 degrees C.
- 2) These are steady state limits. The factory should be consulted on applications involving pulsed or low duty cycle operations.

Thermal Characteristics $T_a = 25^\circ\text{C}$ unless otherwise noted

Symbol	Parameter	Max.		Units
		J309-J310	*MMBFJ309-310	
P_D	Total Device Dissipation	625	350	mW
	Derate above 25°C	5.0	2.8	mW/ $^\circ\text{C}$
$R_{\theta JC}$	Thermal Resistance, Junction to Case	127		$^\circ\text{C}/\text{W}$
$R_{\theta JA}$	Thermal Resistance, Junction to Ambient	357	556	$^\circ\text{C}/\text{W}$







* Device mounted on FR-4 PCB 1.6" X 1.6" X 0.06".

Electrical Characteristics $T_a = 25^\circ\text{C}$ unless otherwise noted







Symbol	Parameter	Test Condition	Min.	Typ.	Max.	Units
Off Characteristics						
$BV_{(BR)GSS}$	Gate-Source Breakdown Voltage	$I_G = -1.0\mu\text{A}$, $V_{DS} = 0$	-25			V
I_{GSS}	Gate Reverse Current	$V_{GS} = -15\text{V}$, $V_{DS} = 0$ $V_{GS} = -15\text{V}$, $V_{DS} = 0$, $T_a = 125^\circ\text{C}$			-1.0 -1.0	nA μA
$V_{GS(off)}$	Gate-Source Cutoff Voltage	$V_{DS} = 10\text{V}$, $I_D = 1.0\text{nA}$	309 310	-1.0 -2.0	-4.0 -6.5	V V
On Characteristics						
I_{DSS}	Zero-Gate Voltage Drain Current*	$V_{DS} = 10\text{V}$, $V_{GS} = 0$	309 310	12 24	30 60	mA mA
$V_{GS(f)}$	Gate-Source Forward Voltage	$V_{DS} = 0$, $I_G = 1.0\text{mA}$			1.0	V
Small Signal Characteristics						
$Re_{(vis)}$	Common-Source Input Conductance	$V_{DS} = 10\text{V}$, $I_D = 10\text{mA}$, $f = 100\text{MHz}$	309 310	0.7 0.5		mmhos mmhos
$Re_{(yos)}$	Common-Source Output Conductance	$V_{DS} = 10\text{V}$, $I_D = 10\text{mA}$, $f = 100\text{MHz}$		0.25		mmhos
G_{pg}	Common-Gate Power Gain	$V_{DS} = 10\text{V}$, $I_D = 10\text{mA}$, $f = 100\text{MHz}$		16		dB
$Re_{(yfs)}$	Common-Source Forward Transconductance	$V_{DS} = 10\text{V}$, $I_D = 10\text{mA}$, $f = 100\text{MHz}$		12		mmhos
$Re_{(yig)}$	Common-Gate Input Conductance	$V_{DS} = 10\text{V}$, $I_D = 10\text{mA}$, $f = 100\text{MHz}$		12		mmhos
g_{fs}	Common-Source Forward Transconductance	$V_{DS} = 10\text{V}$, $I_D = 10\text{mA}$, $f = 1.0\text{kHz}$	309 310	10,000 8,000	20,000 18,000	μmhos μmhos
g_{oss}	Common-Source Output Conductance	$V_{DS} = 10\text{V}$, $I_D = 10\text{mA}$, $f = 1.0\text{kHz}$			150	μmhos
g_{fg}	Common-Gate Forward Conductance	$V_{DS} = 10\text{V}$, $I_D = 10\text{mA}$, $f = 1.0\text{kHz}$	309 310	13,000 12,000		μmhos μmhos
g_{og}	Common-Gate Output Conductance	$V_{DS} = 10\text{V}$, $I_D = 10\text{mA}$, $f = 1.0\text{kHz}$	309 310	100 150		μmhos μmhos
C_{dg}	Drain-Gate Capacitance	$V_{DS} = 0$, $V_{GS} = -10\text{V}$, $f = 1.0\text{MHz}$		2.0	2.5	pF
C_{sg}	Source-Gate Capacitance	$V_{DS} = 0$, $V_{GS} = -10\text{V}$, $f = 1.0\text{MHz}$		4.1	5.0	pF
NF	Noise Figure	$V_{DS} = 10\text{V}$, $I_D = 10\text{mA}$, $f = 450\text{MHz}$		3.0		dB
e_n	Equivalent Short-Circuit Input Noise Voltage	$V_{DS} = 10\text{V}$, $I_D = 10\text{mA}$, $f = 100\text{Hz}$		6.0		nV/ $\sqrt{\text{Hz}}$

* Pulse Test: Pulse Width $\leq 300\mu\text{s}$, Duty Cycle $\leq 2.0\%$




Typical Performance Characteristics



Typical Performance Characteristics (continued)







Typical Performance Characteristics (continued)





TRADEMARKS

The following includes registered and unregistered trademarks and service marks, owned by Fairchild Semiconductor and/or its global subsidiaries, and is not intended to be an exhaustive list of all such trademarks.

AccuPower™	F-PFS™	Power-SPM™	SYSTEM GENERAL®
Auto-SPM™	FRFET®	PowerTrench®	The Power Franchise®
Build it Now™	Global Power Resource™	PowerXST™	the power franchise
CorePLUS™	Green FPS™	Programmable Active Droop™	TinyBoost™
CorePOWER™	Green FPS™ e-Series™	QFET®	TinyBuck™
CROSSVOLT™	Gmax™	QS™	TinyCalc™
CTL™	GTO™	Quiet Series™	TinyLogic®
Current Transfer Logic™	IntelliMAX™	RapidConfigure™	TINYOPTO™
DEUXPEED®	ISOPLANAR™	 ™	TinyPower™
Dual Cool™	MegaBuck™	Saving our world, 1mW/W/kW at a time™	TinyPWM™
EcoSPARK®	MICROCOUPLER™	SignalWise™	TinyWire™
EfficientMax™	MicroFET™	SmartMax™	TriFault Detect™
ESBC™	MicroPak™	SMART START™	TRUECURRENT™*
 Fairchild®	MicroPak2™	SPM®	µSerDes™
Fairchild Semiconductor®	MillerDrive™	STEALTH™	 SerDes™
FACT Quiet Series™	MotionMax™	SuperFET®	UHC®
FACT®	Motion-SPM™	SuperSOT™-3	Ultra FRFET™
FAST®	OptoHiT™	SuperSOT™-6	UniFET™
FastvCore™	OPTOLOGIC®	SuperSOT™-8	VCX™
FETBench™	OPTOPLANAR®	SupreMOS®	VisualMax™
FlashWriter®*	 PDP SPM™	SyncFET™	XST™
FPS™		Sync-Lock™	

* Trademarks of System General Corporation, used under license by Fairchild Semiconductor.

DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION, OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS. THESE SPECIFICATIONS DO NOT EXPAND THE TERMS OF FAIRCHILD'S WORLDWIDE TERMS AND CONDITIONS, SPECIFICALLY THE WARRANTY THEREIN, WHICH COVERS THESE PRODUCTS.

LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION.

As used herein:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury of the user.
2. A critical component in any component of a life support, device, or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

ANTI-COUNTERFEITING POLICY

Fairchild Semiconductor Corporation's Anti-Counterfeiting Policy. Fairchild's Anti-Counterfeiting Policy is also stated on our external website, www.fairchildsemi.com, under Sales Support.

Counterfeiting of semiconductor parts is a growing problem in the industry. All manufacturers of semiconductor products are experiencing counterfeiting of their parts. Customers who inadvertently purchase counterfeit parts experience many problems such as loss of brand reputation, substandard performance, failed applications, and increased cost of production and manufacturing delays. Fairchild is taking strong measures to protect ourselves and our customers from the proliferation of counterfeit parts. Fairchild strongly encourages customers to purchase Fairchild parts either directly from Fairchild or from Authorized Fairchild Distributors who are listed by country on our web page cited above. Products customers buy either from Fairchild directly or from Authorized Fairchild Distributors are genuine parts, have full traceability, meet Fairchild's quality standards for handling and storage and provide access to Fairchild's full range of up-to-date technical and product information. Fairchild and our Authorized Distributors will stand behind all warranties and will appropriately address any warranty issues that may arise. Fairchild will not provide any warranty coverage or other assistance for parts bought from Unauthorized Sources. Fairchild is committed to combat this global problem and encourage our customers to do their part in stopping this practice by buying direct or from authorized distributors.

PRODUCT STATUS DEFINITIONS

Definition of Terms

Datasheet Identification	Product Status	Definition
Advance Information	Formative / In Design	Datasheet contains the design specifications for product development. Specifications may change in any manner without notice.
Preliminary	First Production	Datasheet contains preliminary data; supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve design.
No Identification Needed	Full Production	Datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve the design.
Obsolete	Not In Production	Datasheet contains specifications on a product that is discontinued by Fairchild Semiconductor. The datasheet is for reference information only.

Rev. 150