



## DATASHEET Lighting Solutions

### CEP301AXE, CEP301BXE, CEP301CXE, CEP301AHX, CEP301BHX, and CEP301CHX

## 300W Xenon Power Supply with 12V and 5V Auxiliary Outputs



#### Key Features

- Line Input: 100 - 240 VAC,  $\pm 10\%$ , 50 - 60 Hz, 6.5 Arms max.
- Environmental: 0° C to 50° C operating.
- Altitude: 0 ft. to 6,000 ft. (0 m to 1830 m) MSL.
- Weight: 2.7 lbs. (1.2 Kg).
- Dimensions: 6.50" x 4.55" x 2.25" tall (165 mm x 116 mm x 57 mm tall).

#### Ignitor:

- $\pm 15$  kV ignition spike ( $\pm 3$  kV). Bilateral ignition.
- Minimum repetition rate is 6 strikes/second ( $\pm 2$  strikes)
- Ignition pulses will continue for  $6 \pm 1$  seconds. This feature may be disabled via jumper, in which case the ignition pulses will continue until the lamp ignites.
- Ignitor Life: > 80,000 strikes.



*The CEP301AXE, CEP301BXE, CEP301CXE, CEP301AHX, CEP301BHX, and CEP301CHX power supplies are designed to run Xenon arc lamps in a constant-power mode or constant current mode.*

The CEP301 power supply is designed to run Xenon arc lamps in a constant-power mode (Default) or constant current mode (By Factory Request Only). The supply is designed to run the Osram XBO and Cermax® family lamps. The output power is adjustable from 75 to 300 Watts in power mode with a built-in potentiometer. EMI line-filtering is built-in to the unit. The supply includes an isolated +12V output for powering external fans or electronics and an isolated +5V for powering CMOS level circuitry.

Active Power Factor Correction meets EMC limits for harmonic current emissions, and limitations of voltage fluctuations and flicker.



# CEP301AXE, CEP301BXE, CEP301CXE, CEP301AHX, CEP301BHX, and CEP301CHX

## 300W XENON POWER SUPPLY with 12V and 5V AUXILIARY OUTPUTS

**Output power:** 75 - 300 Watts, constant power

**Output voltage compliance:** 10 to 25 V operating,  
> 110 VDC during ignition.

**Output regulation:** output power held to within  
± 5% over all input, output, and environmental  
conditions.

**Output current:** 4.0 to 22.0 Adc

**Output ripple:** <5% @ 300W\*

**Efficiency:** >80% at 300 W output, 120 VAC input

**Thermal protection:** Ballast is disabled when heat-  
sink temperature exceeds 90°C. Unit will  
automatically restart after cooling down.

**Isolated Auxiliary output 1 (SELV rated):** +12 VDC  
± 5%, 2.5A max.

**Isolated Auxiliary output 2 (SELV rated):** +5 VDC  
± 5%, 0.5A max.

**Optically Isolated Status and Control Connector  
(SELV rated):**

- Remote enable
- Lamp lit status
- Lamp over-voltage/under-voltage indicator

**Ground leakage:**

- CEP301AXE/AHX < 300 µA
- CEP301BXE/BHX < 30 µA
- CEP301CXE/CHX < 100 µA

\* ripple is measured in a DC to 20MHz bandwidth.

### Regulatory Compliance

Approved to UL60601/IE60601, 2<sup>nd</sup> and 3<sup>rd</sup> Edition (E177225)

Complies with EN55011 Class B Emissions.

Meets EN 61000-3-2 and EN61000-3-3. CE-marked.



### About Excelitas Technologies

Excelitas Technologies is a global technology leader  
focused on delivering innovative, customized solutions to  
meet the lighting, detection and other high-performance  
technology needs of OEM customers.

From medical lighting to analytical instrumentation,  
clinical diagnostics, industrial, safety and security and  
aerospace and defense applications, Excelitas  
Technologies is committed to enabling our customers'  
success in their end-markets.

Excelitas Technologies has approximately 3,000  
employees in North America, Europe and Asia,  
serving customers across the world.

**Excelitas Technologies  
Illumination, Inc.**  
44370 Christy Street  
Fremont, California  
94538-3180 USA  
Telephone: (+1) 510.979.6500  
Toll-free: (+1) 800.775.6786  
Fax: (+1) 510.687.1140  
shortarcxenon.na@excelitas.com

**Excelitas Technologies**  
47 Ayer Rajah Crescent #06-12  
Singapore 139947  
Telephone: (+65) 6775 2022 (Main Line)  
Telephone: (+65) 6770 4366  
(Customer Service Hotline)  
Fax: (+65) 6778 1752  
shortarcxenon.asia@excelitas.com

**Excelitas Technologies  
GmbH & Co. KG**  
Wenzel-Jaksch-Str. 31  
D-65199 Wiesbaden  
Germany  
Telephone: (+49) 611 492 430  
Fax: (+49) 611 492 165  
shortarcxenon.europe@excelitas.com

**Excelitas Technologies**  
East Tower 4th Floor,  
Otemachi First Square  
1-5-1 Otemachi, Chiyoda-ku,  
Tokyo 100-0004  
Telephone: (+81) 3-5219-1228  
Fax: (+81) 3-5219-120  
shortarcxenon.asia@excelitas.com

For a complete listing of our global offices, visit [www.excelitas.com/locations](http://www.excelitas.com/locations)

© 2012 Excelitas Technologies Corp. All rights reserved. The Excelitas logo and design are registered trademarks of Excelitas Technologies Corp. All other trademarks  
not owned by Excelitas Technologies or its subsidiaries that are depicted herein are the property of their respective owners. Excelitas reserves the right to change this  
document at any time without notice and disclaims liability for editorial, pictorial or typographical errors.

