

PCI-8158 / PCI-8154

Advanced 8/4-axis Servo & Stepper Motion Controllers with Modular Design



Features

- 3 axes helical interpolation
- Hardware-controlled position compare and trigger (with DB-8150, up to 1 MHz)
- One HSL network support (with DB-8151)
- One Motionnet master support (with DB-8153)
- 32-bit PCI bus, Rev. 2.2, 33 MHz
- High density (200-pin) 8-axis motion controller
- Pulse output rate: up to 6.55 MHz
- Pulse output options: OUT/DIR, CW/CCW, AB Phase
- 2 to 4 axes linear interpolation
- 2 axes circular interpolation
- Helical interpolation
- Multi-axis continuous interpolation
- Position/Speed change override
- 13 home return modes and auto home search
- High speed position latch function
- Programmable acceleration and deceleration time
- Trapezoidal and S-curve velocity profiles
- 28-bit up/down counter for incremental encoder
- Multi-axis, simultaneous start/stop
- Programmable interrupt sources
- Hardware backlash compensator
- Manual pulser input interface
- Softwares limit function
- Hardware emergency input
- More than 100 thread safe API functions
- Security protection for user's program
- Easy interface to any stepping motors, AC or DC servo, linear or rotary motors
- All digital inputs and outputs are 2500 V_{RMS} isolated
- Supports up to 12 cards in one system

Software Support

- OS Information**
 - Windows® 8/7/XP
 - Linux
 - RTX 5.x/6.x/8.1a
- Software Compatibility**
 - VB/VC++/BCB/Delphi/VB.NET
 - Various sample programs with source codes
- Software Recommendations**
 - MotionCreatorPro2

Specifications

Pulse Type Motion Control

Max. Number of Axes	8
Pulse Output Rate	0.01 pps to 6.5 Mpps
Max. Acceleration Rate	245 Mpps ²
Speed Resolution	16-bit
Encoder Input Rate	6.55 MHz under 4 x AB phase @ 1 M cable
Encoder Counter Resolution	28-bit
Positioning Range	-134,217,728 to +134,217,727 pulses (28-bit)
Counters	x 4 for each axis
Comparators	x 5 for each axis

Motion Interface I/O Signals

Position Latch Input Pin	LTC
Position Compare Output Pin	CMP
I/O Pin	Differential and 2500 V _{RMS} optically isolated
Incremental Encoder Signals Input Pin	EA and EB
Encoder Index Signal Input	EZ
Mechanical Signal Input Pin	±EL, SD, and ORG
Servomotor Interface I/O Pin	INP, ALM, ERC, RDY, SVON
General DO Pin	DO x 8 for DO/CMP
General DI Pin	GDI x 8 for DI/LTC/PCS/SD/CLR/EMG
Pulser Signal Input	PA and PB
Simultaneous Start/Stop Signal I/O Pin	STA and STP

Ordering Information

- PCI-8158**
Advanced 8-axis servo & stepper motion controller
- PCI-8154**
Advanced 4-axis servo & stepper motion controller
- DB-8150**
High-speed triggering daughter board
- DB-8151**
Single HSL master controller daughter board
- DB-8153**
Single Motionnet master controller daughter board

Accessories

For more information on terminal boards & cables, please refer to page 6-31.

Terminal Boards

- DIN-100S-01**
Terminal board with one 100-pin SCSI-II connector and DIN-rail mounting
- DIN-814-GP**
Terminal board for general purpose with 100-pin SCSI-II connector
- DIN-814M0**
Terminal board for Mitsubishi MR-J2S-A servo amplifier
- DIN-814M -J3A0**
Terminal board for Mitsubishi MR-J3A/J4A servo amplifiers
- DIN-814Y0**
Terminal board for Yaskawa Sigma V servo amplifier
- DIN-814P-A00**
Terminal board for Panasonic MINAS A4/A5 servo amplifiers with 100-pin SCSI-II connector

Cabling

- ACL-102100-1 (for PCI-8154)**
100-pin SCSI-II cable (mating with AMP-787082-9), 1 M
- SCSI-VHDCI 100P (for PCI-8158)**
100-pin SCSI-VHDCI cable, available for 2 M, 3 M

Pin Assignment

PCI-8158/PCI-8154 100-pin Mini SCSI Connector Pin Assignment

VDD	1	51	VDD
EXGND	2	52	EXGND
OUT0+	3	53	OUT2+
OUT0-	4	54	OUT2-
DIR0+	5	55	DIR2+
DIR0-	6	56	DIR2-
SVON0	7	57	SVON2
ERC0	8	58	ERC2
ALM0	9	59	ALM2
INP0	10	60	INP2
RDY0	11	61	RDY2
EXGND	12	62	EXGND
EA0+	13	63	EA2+
EA0-	14	64	EA2-
EB0+	15	65	EB2+
EB0-	16	66	EB2-
EZ0+	17	67	EZ2+
EZ0-	18	68	EZ2-
VDD	19	69	VDD
EXGND	20	70	EXGND
OUT1+	21	71	OUT3+
OUT1-	22	72	OUT3-
DIR1+	23	73	DIR3+
DIR1-	24	74	DIR3-
SVON1	25	75	SVON3
ERC1	26	76	ERC3
ALM1	27	77	ALM3
INP1	28	78	INP3
RDY1	29	79	RDY3
EXGND	30	80	EXGND
EA1+	31	81	EA3+
EA1-	32	82	EA3-
EB1+	33	83	EB3+
EB1-	34	84	EB3-
EZ1+	35	85	EZ3+
EZ1-	36	86	EZ3-
PEL0	37	87	PEL2
MEL0	38	88	MEL2
GDI0	39	89	GDI2
DO0	40	90	DO2
ORG0	41	91	ORG2
EXGND	42	92	EXGND
PEL1	43	93	PEL3
MEL1	44	94	MEL3
GDI1	45	95	GDI3
DO1	46	96	DO3
ORG1	47	97	ORG3
EXGND	48	98	EXGND
EXGND	49	99	E_24V
EXGND	50	100	E_24V