

## S-Band 6-bit Digital Phase Shifter

### GaAs Monolithic Microwave IC


#### Description

The CHP4012a98F is a 6-bit phase shifter monolithic circuit, which integrates a CMOS and TTL compatible interface.

It is designed for a wide range of applications, typically defence and space systems.


The circuit is manufactured with a pHEMT process, 0.25µm gate length, via holes through the substrate, air bridges and electron beam gate lithography.

It is supplied in chip form and RoHS compliant SMD package.



#### Main Features

- Frequency range: 2.7-3.5GHz
- 5.625° phase shifter step
- 0-360° phase shift range
- RMS phase error: 1°
- Digital interface
- Chip size: 3.61x1.84x0.1mm



#### Main Electrical Characteristics

Tamb.= +25°C

Symbol	Parameter	Min	Typ	Max	Unit
Freq	Frequency range	2.7		3.5	GHz
IL	Insertion Loss		6		dB
RMS_PE	RMS Phase Error		1		°
P1dB	Input Power at 1dB gain compression		24.5		dBm

## Electrical Characteristics

Tamb.= +25°C

Symbol	Parameter	Min	Typ	Max	Unit
Freq	Frequency range	2.7		3.5	GHz
PhS	Phase Shift Range	0		360	°
PhS_step	Phase Shift Step		5.625		°
PPE	Peak Phase Error		-2 / +4		°
RMS_PE	RMS Phase Error		1		°
IL	Insertion Loss (all states)		6.0		dB
Av	Amplitude Variation		+/-0.5		dB
RMS_Av	RMS Amplitude Variation		0.2		dB
S11	Input Reflection Coefficient (all states)		-15		dB
S22	Output Reflection Coefficient (all states)		-15		dB
P1dB	Input Power at 1dB gain compression		24.5		dBm
Vctrl_L	Control Input Voltage (P1-P6) – low level	0		0.4	V
Vctrl_H	Control Input Voltage (P1-P6) – high level	2.4	3.3	7	V
V+	Positive Supply Voltage		+5		V
V-	Negative Supply Voltage		-5		V
I+	Positive Supply Current		5		mA
I-	Negative Supply Current		5		mA
SwT	Switching Time		15		ns
Top	Operating Temperature	-40		+85	°C

### Peak Phase Error (PPE) definition

$PPE(i) = \text{measured\_Phase}(S21)@state(i) - \text{measured\_Phase}(S21)@state(0) - \text{theoretical PhaseValue@State}(i)$

### Amplitude Variation (Av) definition

$Av(i) = \text{Measured\_dB}(S21)@state(i) - \text{Measured\_dB}(S21)@state(0)$

### RMS Phase Error (RMS\_PE) definition

$$RMS\_PE = \sqrt{\frac{\sum_{i=0}^{63} PPE^2(i)}{64}}$$

### RMS Amplitude variation (RMS\_Av) definition

$$RMS\_AV = \frac{\sum_{i=0}^{63} Av(i)}{64}$$

where (i) is the state number (from 0 to 63)

**Absolute Maximum Ratings**T<sub>amb.</sub> = +25 °C<sup>(1)</sup>

Symbol	Parameter	Values	Unit
V+	Maximum DC positive supply voltage	8	V
V-	Maximum DC negative supply voltage	-8	V
Vctrl	Phase shifter control voltage (Vlow, Vhigh)	-2 to +8	V
Pin	Maximum peak input power overdrive	30	dBm
Tj	Junction temperature	175	°C
Ta	Operating temperature range	-40 to +85	°C
Tstg	Storage temperature range	-55 to +150	°C

<sup>(1)</sup> Operation of this device above anyone of these parameters may cause permanent damage.

**Typical Bias Conditions**

Two options are possible for the bonding of biasing and control pads without impact on the RF performances.

## Option 1

Pad name	Pad number	Parameter	Values	Unit
V+	3	Positive Supply Voltage	+5	V
V-	13	Negative Supply Voltage	-5	V
Vctrl	4, 7, 11, 14, 16, 18	Control Input Voltage	0 / +3.3	V

## Option 2

Pad name	Pad number	Parameter	Values	Unit
V+	17	Positive Supply Voltage	+5	V
V-	15	Negative Supply Voltage	-5	V
Vctrl	5, 6, 8, 9, 10, 12	Control Input Voltage	0 / +3.3	V

## Phase shifter control table


Voltage to apply on the pads P1 to P6

State	Phase (deg)	P6	P5	P4	P3	P2	P1	State	Phase (deg)	P6	P5	P4	P3	P2	P1
0	0	0	0	0	0	0	0	32	180	3.3	0	0	0	0	0
1	5.625	0	0	0	0	0	3.3	33	185.625	3.3	0	0	0	0	3.3
2	11.25	0	0	0	0	3.3	0	34	191.25	3.3	0	0	0	3.3	0
3	16.875	0	0	0	0	3.3	3.3	35	196.875	3.3	0	0	0	3.3	3.3
4	22.5	0	0	0	3.3	0	0	36	202.5	3.3	0	0	3.3	0	0
5	28.125	0	0	0	3.3	0	3.3	37	208.125	3.3	0	0	3.3	0	3.3
6	33.75	0	0	0	3.3	3.3	0	38	213.75	3.3	0	0	3.3	3.3	0
7	39.375	0	0	0	3.3	3.3	3.3	39	219.375	3.3	0	0	3.3	3.3	3.3
8	45	0	0	3.3	0	0	0	40	225	3.3	0	3.3	0	0	0
9	50.625	0	0	3.3	0	0	3.3	41	230.625	3.3	0	3.3	0	0	3.3
10	56.25	0	0	3.3	0	3.3	0	42	236.25	3.3	0	3.3	0	3.3	0
11	61.875	0	0	3.3	0	3.3	3.3	43	241.875	3.3	0	3.3	0	3.3	3.3
12	67.5	0	0	3.3	3.3	0	0	44	247.5	3.3	0	3.3	3.3	0	0
13	73.125	0	0	3.3	3.3	0	3.3	45	253.125	3.3	0	3.3	3.3	0	3.3
14	78.75	0	0	3.3	3.3	3.3	0	46	258.75	3.3	0	3.3	3.3	3.3	0
15	84.375	0	0	3.3	3.3	3.3	3.3	47	264.375	3.3	0	3.3	3.3	3.3	3.3
16	90	0	3.3	0	0	0	0	48	270	3.3	3.3	0	0	0	0
17	95.625	0	3.3	0	0	0	3.3	49	275.625	3.3	3.3	0	0	0	3.3
18	101.25	0	3.3	0	0	3.3	0	50	281.25	3.3	3.3	0	0	3.3	0
19	106.875	0	3.3	0	0	3.3	3.3	51	286.875	3.3	3.3	0	0	3.3	3.3
20	112.5	0	3.3	0	3.3	0	0	52	292.5	3.3	3.3	0	3.3	0	0
21	118.125	0	3.3	0	3.3	0	3.3	53	298.125	3.3	3.3	0	3.3	0	3.3
22	123.75	0	3.3	0	3.3	3.3	0	54	303.75	3.3	3.3	0	3.3	3.3	0
23	129.375	0	3.3	0	3.3	3.3	3.3	55	309.375	3.3	3.3	0	3.3	3.3	3.3
24	135	0	3.3	3.3	0	0	0	56	315	3.3	3.3	3.3	0	0	0
25	140.625	0	3.3	3.3	0	0	3.3	57	320.625	3.3	3.3	3.3	0	0	3.3
26	146.25	0	3.3	3.3	0	3.3	0	58	326.25	3.3	3.3	3.3	0	3.3	0
27	151.875	0	3.3	3.3	0	3.3	3.3	59	331.875	3.3	3.3	3.3	0	3.3	3.3
28	157.5	0	3.3	3.3	3.3	0	0	60	337.5	3.3	3.3	3.3	3.3	0	0
29	163.125	0	3.3	3.3	3.3	0	3.3	61	343.125	3.3	3.3	3.3	3.3	0	3.3
30	168.75	0	3.3	3.3	3.3	3.3	0	62	348.75	3.3	3.3	3.3	3.3	3.3	0
31	174.375	0	3.3	3.3	3.3	3.3	3.3	63	354.375	3.3	3.3	3.3	3.3	3.3	3.3


Typical on wafer Measurements

Temperature = -40°C, +25°C, +85°C, V+ = +5V, V- = -5V


Insertion Losses versus Frequency @ States 0



Input Return Loss @ States 0




Output Return Loss @ States 0




## Typical on wafer Measurements

Temperature = +25°C, V+ = +5V, V- = -5V


### Insertion Losses versus Frequency @ All States



### Input Return Loss @ All States




### Output Return Loss @ All States




Typical on wafer Measurements

V+ = +5V, V- = -5V


Peak Phase Error versus Frequency  
(All States)



Peak Phase Error versus States  
2.7GHz < frequency < 3.5GHz




RMS Phase Error versus Frequency



— -40°C    ..... +25°C    - - - - +85°C


Phase Shift versus States  
2.7GHz < frequency < 3.5GHz




## Typical on wafer Measurements

V+ = +5V, V- = -5V


**Amplitude Variation versus Frequency  
(All States)**



**Amplitude Variation versus States  
2.7GHz < frequency < 3.4GHz**




**RMS Amplitude Variation versus Frequency**




— -40°C    ..... +25°C    - - - +85°C

**Input Power at 1dB gain compression  
versus Frequency**



— -40°C    ..... +25°C    - - - +85°C

## Mechanical data



Chip thickness: 100µm.  
 Chip size: 3610x1840 ±35µm  
 All dimensions are in micrometers



Chip thickness = 100µm +/- 10µm.

RF pads (1, 21) = 142 x 200µm<sup>2</sup>

DC and control pads (3 to 18) = 100 x 100µm<sup>2</sup>

Pad number	Pad name	Description
1	IN	Input RF
5 or 18	P6	Phase Shift bit 6
6 or 16	P5	Phase Shift bit 5
8 or 14	P4	Phase Shift bit 4
9 or 11	P3	Phase Shift bit 3
10 or 7	P2	Phase Shift bit 2
12 or 4	P1	Phase Shift bit 1
15 or 13	V-	-5V supply voltage: interface
17 or 3	V+	+5V supply voltage: interface
21	OUT	Output RF
2, 19, 20, 22, 23	GND	NC

## Recommended assembly plan : Option 1



25µm wedge bonding is preferred



### Bonding recommendations

Port	Connection
IN (1) OUT (21)	Inductance (L <sub>bonding</sub> ) = 0.3nH one wire: diameter 25µm, length 0.4mm
DC and Interface pads	Inductance (L <sub>bonding</sub> ) = 0.8nH one wire: diameter 25µm, length 1.0mm

### Recommended circuit bonding table

Pad name	Type	Decoupling	Comment
V-, V+	Bias	100pF	Supply Voltage
P1 to P6	Control	Not Required	Phase Shift Control

**Recommended assembly plan : Option 2**



25µm wedge bonding is preferred

Bonding recommendations

Port	Connection
IN (1) OUT (21)	Inductance (L <sub>bonding</sub> ) = 0.3nH one wire: diameter 25µm, length 0.4mm
DC and Interface pads	Inductance (L <sub>bonding</sub> ) = 0.8nH one wire: diameter 25µm, length 1.0mm

**Recommended circuit bonding table**

Pad name	Type	Decoupling	Comment
V-, V+	Bias	100pF	Supply Voltage
P1 to P6	Control	Not Required	Phase Shift Control

## Recommended ESD management

Refer to the application note AN0020 available at <http://www.ums-gaas.com> for ESD sensitivity and handling recommendations for the UMS products.

## Ordering Information

Chip form:

CHP4012a98F/00

Information furnished is believed to be accurate and reliable. However **United Monolithic Semiconductors S.A.S.** assumes no responsibility for the consequences of use of such information nor for any infringement of patents or other rights of third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of **United Monolithic Semiconductors S.A.S.** Specifications mentioned in this publication are subject to change without notice. This publication supersedes and replaces all information previously supplied. **United Monolithic Semiconductors S.A.S.** products are not authorised for use as critical components in life support devices or systems without express written approval from **United Monolithic Semiconductors S.A.S.**