



**Tripp Lite**  
1111 West 35th Street  
Chicago, IL 60609 USA  
Telephone: +(773) 869 1234  
E-mail: [saleshelp@tripplite.com](mailto:saleshelp@tripplite.com)

## Model #: APS750

### PowerVerter® APS 750W Inverter/Charger with Auto-Transfer Switching and 2 Outlets



#### Highlights

- 12V DC or 120V AC input; 120V AC output; 2 outlets
- 750 watts continuous, 1125 watts OverPower™ and 1500 watts DoubleBoost™ inverter output
- 3 stage, 20 amp selectable wet/dry cell battery charger
- Auto Transfer Switching option for battery backup / UPS operation
- Reliability enhanced large-transformer design with protected DC wiring terminals

#### Description

Tripp Lite's APS750 DC-to-AC inverter with automatic line-to-battery transfer and integrated charging system serves as an extended run UPS, a standalone power source or an automotive inverter. Supplies up to 750 watts of continuous 120V AC power to 2 AC outlets from any 12V battery or automotive DC source. OverPower™ inverter output feature temporarily provides up to 150% of the continuous output for 1-60 minutes and DoubleBoost™ inverter output feature delivers up to 200% of the continuous output for up to 10 seconds, providing the extra power needed to cold start heavy-duty tools and motorized equipment. When AC cable is connected to a live wall socket, commercial power passes through to connected equipment and the battery set is recharged via 3 stage, 20 amp charging system. In UPS mode, the APS system responds to blackouts and voltage fluctuations with a near instantaneous automatic transfer to battery-derived AC output. Includes a set of high current DC input terminals for simple installation (user supplies batteries and cabling - see owner's manual for recommendations). Passes sine wave utility or generator power during battery charging and UPS line power operation, plus efficient PWM sine wave AC output in inverter and UPS backup modes. Reliable large transformer design, with frequency control powers resistive electronic loads or large inductive motors, compressors and other items with high current needs on start-up. Optional APSRM4 wired remote power switch with full status LEDs provides remote power inverter on/off switching and continuous status information (APSRM4 sold separate). Supports an unlimited amount of runtime with any number of user-supplied batteries connected. Highly adaptable to a variety of applications and site conditions with adjustable charger settings for wet/gel battery types and selectable line to battery power transfer voltages.

#### Applications

Versatile inverter/charger system with auto-transfer switching serves as an automotive inverter for RVs, over-the-road trucking, conversion vans and fleet service vehicles; a standalone alternative power source for off-grid, alternative energy or export applications and as an uninterruptible power supply (UPS) for items compatible with a 16.6 millisecond transfer time. NOTE: For sump pump applications, Tripp Lite recommends its "UT" Utility Truck Inverter/Chargers.

#### Package Includes

- APS750 Inverter/Charger
- Instruction manual with warranty information

#### Features

- APS750 serves as an automotive or stationary DC-to-AC inverter with automatic line-to-battery transfer and integrated battery charger
- Supports 120V AC output from a 120V AC line power source or 12V DC battery source
- 16.6 millisecond automatic transfer between line and battery power supports UPS protection during blackouts and voltage fluctuations for equipment compatible with a one cycle transfer time

- 750 watts continuous AC output in inverter mode, 1500 watts continuous AC output in AC mode
- Double Boost™ inverter output supports momentary start-up loads up to 200% of the continuous rating for up to 10 seconds
- OverPower™ inverter output supports longer duration overloads to 150% for 1-60 minutes under ideal battery and temperature conditions. (For best results, utilize OverPower usage for as short of a duration as possible, ensure battery bank and cabling is able to provide full nominal DC voltage under load and allow inverter/charger to fully cool before and after OverPower usage.)
- 3 stage, 20 amp battery charger with adjustable settings for wet/gel battery types offers fast, reliable battery recharging
- Protected hardwire bolt-down input lugs safely accept heavy gauge input wiring from attached battery bank
- Two built-in NEMA 5-15R output receptacles pass 120V line power or inverter output through to connected equipment
- Reliability enhanced large-transformer design with secure mounting flanges and protected DC wiring terminals
- Moisture-resistant construction enables vehicular or marine operation in high humidity environments
- 3 position operating mode switch supports "AUTO" mode to enable automatic transfer between DC and AC modes, CHARGE-ONLY to maintain a full battery charge when AC is present without auto transfer and SYSTEM OFF settings.
- Set of six front panel LEDs display AC/DC operational modes, overload status, DC voltage level, shutdown status and system fault status
- Set of 4 configuration dip-switches support wet/gel battery charging profiles, adjustable 135/145V high voltage auto transfer during overvoltages and selectable 75/85/95/105V AC low voltage auto transfer during brownouts
- Resettable 6A charger AC input breaker and resettable 8A AC output breaker and automatic 2 speed cooling fan protect the inverter from load and temperature related failures
- Grounding lug properly connects the inverter/charger system to earth ground or vehicle grounding system
- Automatic overload and thermal shutoff safely turns off inverter as excessive loads or overheating conditions develop
- Front panel remote control connector enables remote off/on switching (requires APSRM4 switch accessory). Optional APSRM4 accessory also includes user configurable jacks to support inverter shutoff or start-up as a vehicle ignition is engaged.

## Specifications

OVERVIEW	
Intended Application	Emergency Home Power
OUTPUT	
Frequency compatibility	60 Hz
Output watts	750
Continuous output capacity (watts)	750
Peak output capacity (watts)	1500
Output nominal voltage	120V
Output voltage regulation	LINE POWER (AC): Maintains 120V nominal sine wave output from line power source. INVERTER POWER (AC): Maintains PWM sine wave output voltage of 120 V AC (+/-5%).
Output frequency regulation	60 Hz (+/- 0.3 Hz)
Overload protection	Includes 6A AC input breaker dedicated to the charging system and 8A output breaker for AC output loads
Outlet quantity / type	2 NEMA 5-15R
INPUT	
Nominal Input Voltage(s) Supported	120V AC
Recommended Electrical Service	DC INPUT: Requires 12V DC input source capable of delivering 72A for the required duration (when used at full continuous capacity - DC requirements increase during Over-Power and Double-Boost operation). AC INPUT: 15A 120V AC recommended
Maximum input amps / watts	DC INPUT: Full continuous load - 72A at 12V DC. AC INPUT: 8 amps at 120VAC with full inverter and charger load (4.2A max charger-only)
Input connection type	DC INPUT: Set of 2 DC bolt-down terminals. AC INPUT: NEMA 5-15P input plug

Voltage compatibility (VAC)	120
Voltage compatibility (VDC)	12
<b>BATTERY</b>	
Expandable battery runtime	Runtime is expandable with any number of user supplied wet, gel or SLA batteries
DC system voltage (VDC)	12
Battery charge	20A
<b>UPC ASSIGNMENT</b>	
Unit Carton UPC#	037332090119
<b>LEDS ALARMS &amp; SWITCHES</b>	
Switches	3 position on/off/remote switch enables simple on/off power control plus "auto/remote" setting that enables distant on/off control of the inverter system when used in conjunction with optional <a href="#">APSRM4</a> accessory when used in inverter mode. In AC uninterrupt
Front panel LEDs	Set of 6 LEDs offer continuous status information on load percentage (6 levels reported) and battery charge level (7 levels reported). See manual for sequences.
<b>SURGE / NOISE SUPPRESSION</b>	
AC suppression joule rating	450
<b>PHYSICAL</b>	
Shipping Dimensions (HWD/in)	12.5 x 11 x 10.75
Shipping Dimensions (HWD/cm)	31.75 x 27.94 x 27.31
Shipping weight (lbs)	18.6
Shipping weight (kg)	8.4
Unit Dimensions (HWD/in)	7 x 8.75 x 9
Unit Dimensions (HWD/cm)	17.78 x 22.23 x 22.86
Unit weight (lbs)	17
Unit weight (kg)	7.7
Cooling method	Multi-speed fan
Material of construction	Polycarbonate
Receptacle Color	BLACK
Style	Heavy-duty with built-in battery charger
Form factors supported	Mounting slots enable permanent placement of inverter on any horizontal surface (see manual for additional mounting information)
<b>ENVIRONMENTAL</b>	
Relative Humidity	0-95% non-condensing

<b>LINE / BATTERY TRANSFER</b>	
<b>Transfer time from line power to battery mode</b>	16.6 milliseconds (typical - compatible with many computers, servers and networking equipment - verify transfer time compatibility of loads for UPS applications)
<b>Low voltage transfer to battery power</b>	In AC "auto" mode, inverter/charger switches to battery mode as line voltage drops to 75V (user adjustable to 85, 95, 105V - see manual)
<b>High voltage transfer to battery power</b>	In AC "auto" mode, inverter/charger switches to battery mode as line voltage increases to 135V (user adjustable to 145 - see manual)
<b>SPECIAL FEATURES</b>	
<b>Remote control capability</b>	Yes
<b>WARRANTY</b>	
<b>Product Warranty Period (U.S. &amp; Canada)</b>	1-year limited warranty
<b>Product Warranty Period (International)</b>	2-year limited warranty
<b>Product Warranty Period (Mexico)</b>	2-year limited warranty
<b>Product Warranty Period (Puerto Rico)</b>	1-year limited warranty

## Related Items

### Optional Products

<b>Related Model</b>	<b>Description</b>	<b>Qty.</b>
<a href="#">APSRM4</a>	Remote Control Module - for Tripp Lite Inverters and Inverter/Chargers	1
<a href="#">BP-260</a>	Ideal battery housing for use with Tripp Lite PowerVerter APS inverter/charger systems with a 12 or 24V DC system voltage.	1
<a href="#">98-121</a>	12V DC Sealed, Maintenance-Free Battery	1

More information, including related products, owner's manuals, and additional technical specifications, can be found online at [www.tripplite.com/en/products/model.cfm?txtModelID=2938](http://www.tripplite.com/en/products/model.cfm?txtModelID=2938).

Copyright © 2013 Tripp Lite. All rights reserved. All trademarks are the sole property of their respective owners. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Photos may differ slightly from final products.