



## Single FCS301



## Features

- **Built-in instrumentation RMS output detector**
- **Adjustable output power threshold alarms**
- Outperforms IESS 308/309 phase noise by 3dB
- Superior linearity
- 125 kHz step size
- 40dB attenuation control range
- On-site reference aging correction capability
- Intuitive front panel user interface
- RS232 terminal and RS485 packet mode remote interface
- 10 operating gain and frequency

## Overview

Converters from FCS301 series are packaged in a compact standard 1RU enclosure.

Their built-in instrumentation detector associated with discrete power thresholds alarms allows evolved system monitoring configurations.

The straightforward front panel operation, and RS232 terminal mode enables quick on-site setup

Offered remote management interfaces ensure complete flexibility of integration into existing or new installations. The user-friendly front panel or the RS485 remote interface will provide full set-up and fault monitoring facilities Ethernet option will allow the operator to pilot system operation either through SNMP or Web based interface.

Delivered spectral purity, low phase noise and stability exceed the requirements of all major international satellite network operators.

The system reference guaranteeing conversion function's accuracy can optionally be provided externally, internally as a highly stable temperature compensated oscillator, or with auto-detection capacity that will use internal reference only in the absence of an externally provided one.

## Application

The FCS301 range of converters operates in VSAT, SCPC Networks, DSNG/SNG, DVB-RCS and Hub systems. This makes them an ideal choice for large earth stations requiring cost effective solutions while maintaining equipment configuration flexibility. The lightweight and compact design makes the FCB100 converter as an ideal solution for mobile truck or flyaway DSNG systems. Its rugged construction can even meet the demands of military installations. The FCB100 range of converters provides an industry leading MTBF of over 120,000 hours.

## Operating Bands

Model Number	RF Output	IF Frequency
ARUN-70KS-A	14.0 – 14.5 GHz	70 MHz (36 MHz BW)
ARUN-70KX-A	13.75 GHz – 14.5GHz	
ARUN-140KS-A	14.0 – 14.5 GHz	140 MHz (72 MHz BW)
ARUN-140KX-A	13.75 GHz – 14.5GHz	

## Options

- 1kHz step size
- 30dB maximum gain
- 75 ohms IF impedance
- Group Delay equalization
- Ethernet port with SNMP and Web interface
- Autosensing Internal /External Reference
- Input Monitor and Output Monitor
- 1:1 Redundant Ready
- 1:N Redundant Ready

## Redundancy

The FCS-100 converter series redundancy options allow their incorporation in redundant system from 1:1 up to 1:12. 1:1 redundancy is performed with an additional redundancy shelf for a system size of 3RU. Higher order redundancy operates through a redundancy controller shelf with the extra benefit of a single bus for complete system M&C. Given each Switch Panel can handle up to four (4) converter units; a complete 1:12 system requires a space of 17U.

## Associated documents

- 1:N Switch Controller for Frequency Converters
- 1:1 Redundancy for Frequency Converters

# Ku-Band Synthesized Frequency Up-Converter

## Technical Specifications

### Up-Converter

#### IF Input

Impedance	50 Ω (75Ω *)
Input Connector	BNC (female)
Return loss	18 dB
Input monitor coupling*	20dB +/- 1dB
Input monitor connector*	BNC (female)

#### RF Output

Output level	0 dBm at P1dB
IMD3 (two tone)	-40 dBc max @ -10 dBm output
Output connector	Type N (female)
Connector Impedance	50 Ω
Return loss	18 dB
Output monitor coupling*	24 +/- 1dB
Output monitor connector*	SMA (female)
Power detection range	-25 to +11dBm, +/-1dB

#### Transfer Characteristics

Frequency range	(See table on front page)			
Conversion Gain	20 dB (30dB *)			
Gain adjustment	40 dB (0.1 dB step size)			
Gain flatness	1.2 dB p-p max. 36 MHz 1.8 dB p-p max. 72 MHz			
Gain stability	±0.25 dB max. /24 hours ±1 dB over temp. range			
Spurious	< -55 dBc related @ -10 dBm output < -60 dBm non-related			
Group delay	8 ns p-p typical			
Group delay equalization*	36MHz	Linear	0.03 ns/MHz	Parabolic 0.01 ns/MHz <sup>2</sup>
	72MHz	Linear	0.025 ns/MHz	Parabolic 0.003 ns/MHz <sup>2</sup>
Phase noise (dBc/Hz)	100Hz	-63	1kHz	-73
	10kHz	-83	100kHz	-100
Synthesizer step size	125k kHz (1kHz option)			

#### Reference

External Reference	10 MHz, +/- 5 dBm input level	Mechanical	Width 19" (482.6 mm)	
Internal reference stability	± 2 x 10 <sup>-8</sup> over 0°C to +50°C		Dimensions	Height 1U 1.75" (44.5 mm)
Aging	± 2 x 10 <sup>-10</sup> / day ± 5 x 10 <sup>-8</sup> / year			Depth 22" (558.8 mm)

#### Environmental

Operational	0°C to +50°C standard	Power Supply	Voltage	90 – 265 VAC (47 – 63 Hz)
Storage	-55°C to +85°C	Power	Connector	40W (typical, single converter)
Humidity	Non-condensing	Connector		IEC 603320 10A
Altitude	3,000m AMSL			

#### Monitor and Control

RS 485	DB9
RS 232	DB9
Discrete	DB9
Ethernet *	RJ45 F

(\*) offered as option

#### NORTH AMERICA USA

Tel: +1 703 659 9796  
Fax: +1 703 635 2212  
info.usa@advantechwireless.com

#### CANADA

Tel: +1 514 420 0045  
Fax: +1 514 420 0073  
info.canada@advantechwireless.com

#### EUROPE

UNITED KINGDOM  
Tel: +44 1480 357 600  
Fax: +44 1480 357 601  
info.uk@advantechwireless.com

#### RUSSIA & CIS

Tel: +7 495 971 59 18  
info.russia@advantechwireless.com

#### INDIA

Tel: +91 33 2415 5922  
info.india@advantechwireless.com

#### SOUTH AMERICA

Tel: +1 514 420 0045  
Fax: +1 514 420 0073  
info.latam@advantechwireless.com

#### BRAZIL

Tel: +55 11 3054 5701  
Fax: +55 11 3054 5701  
info.brazil@advantechwireless.com

An ISO 9001 : 2008 Company



Ref.:PB-FCS301-Ku-13150