

*Dual with Trays  
FCS500T*



## Features

- Two hot swappable converters in 1U
- 70 MHz IF or 140 MHz
- 125 kHz step size
- Cost effective solution
- 1:1 Redundancy (option)
- Meets or exceeds IESS 308/309 requirements
- High linearity
- Front panel control (local)
- Full remote control (remote) RS485 or RS232

## Overview

The Advantech Wireless Dual - HP range of converters uses the latest technology in conversion, giving two independent conversion chains in 1 RU package, local and remote control thus providing the ultimate in performance and user friendly operation at a very competitive price.

The spectral purity, low phase noise and stability exceed the requirements of all major international satellite network operators.

The flexible and comprehensive monitor and control features on the HP converter ensure that it will fit into any network management system architecture. The user-friendly front panel or the RS485 remote interface will provide full set-up and fault monitoring facilities. The RS232 will provide the Monitor and Control functions via a PC and will also allow for software downloading.

The converter uses a PLL oscillator either locked to a highly stable internal 10 MHz reference or if the external reference option is fitted and the proper level of signal is present, the PLL oscillator will automatically lock to the external reference.

## Application

The HP range of converters is particularly suited for use in VSAT, SCPC Networks, SNG, DVB-RCS and Hub systems where compact redundancy is required. This makes them an ideal choice for large earth stations requiring cost effective solutions for frequency conversion. The lightweight, rugged and compact design also ensures that the HP converter provides the ideal solution for mobile truck or flyaway DSNG systems. With fully welded aluminum chassis and robust modular internal construction the converter can even meet the demands of military installations. The HP range of converters provides an industry leading MTBF of over 120,000 hours.

## Models

### Up-Converters

ARUD-70L-T	70 MHz to L ( 950-1750MHz) (NINV)
ARUN-140L-T	140MHz to L (950-1750MHz) (NINV)

### Down-Converters

ARDD-L70-T	L ( 950-1750MHz) to 70 MHz (NINV)
ARED-L70-T	L ( 950-1750MHz) to 70 MHz (INV)



## Options

- 140 MHz IF Frequency
- Ethernet port and SNMP Interface
- Low Group Delay (option)
- External/Internal 10 MHz Reference with Autosensing
- 10 MHz Reference for LNB via L-Band, on down converters.

# L-Band Synthesized Frequency Converter

## Technical Specifications

Up-Converter		Down-Converter	
<b>IF Input</b>		<b>RF Input</b>	
Frequency range	70 ± 18 MHz 140 ± 36 MHz (optional)	Frequency range	950 – 1750 MHz
Impedance	50 Ω standard (optional 75Ω)	Impedance	50 Ω
Input Connector	SMA (female)	Input Connector	SMA (female)
Return loss	18 dB	Return loss	16 dB
<b>RF Output</b>		<b>IF Output</b>	
Output power (P1dB)	+5 dBm	Frequency range	70 ± 18 MHz 140 ± 36 MHz (optional)
Frequency range	950 – 1750 MHz	Output level	+5 dBm at P1dB
IMD3 (two tone)	-40 dBc max @ -5 dBm output	Output Connector	SMA (female)
Output connector	SMA (female)	Connector Impedance	50 Ω standard (optional 75Ω)
Connector Impedance	50 Ω	Return Loss	18 dB
Return loss	16 dB		
<b>Transfer Characteristics</b>		<b>Transfer Characteristics</b>	
Conversion Gain	20 dB @ max gain setting	Conversion Gain	30 dB min @ max gain setting
Gain adjustment	20 dB (0.1 dB step size)	Gain adjustment	20 dB (0.1 dB step size)
Gain flatness	1.0 dB p-p max. 36 MHz 1.5 dB p-p max. 72 MHz	Gain flatness	1.0 dB p-p max. 36 MHz 1.5 dB p-p max. 72 MHz
Gain stability	±0.25 dB max. /24 hours ±1 dB over temp. range	Gain stability	±0.25 dB max. / 24 hours ±1 dB over temp. range
Spurious	-55 dBc carrier related @ -5 dBm < -60 dBm non-carrier related	Spurious	-55 dBc @ -5 dBm output
Group delay (over 36 MHz)	10 - 15 ns p-p	Group delay (over 36 MHz)	10 - 15 ns p-p
Group delay (with optional group delay equalizer)	Linear 0.03 ns/MHz Parabolic 0.01 ns/MHz <sup>2</sup> Ripple 1 ns p-p	Group delay (with optional group delay equalizer)	Linear 0.03 ns/MHz Parabolic 0.01 ns/MHz <sup>2</sup> Ripple 1 ns p-p
		Image rejection	50 dB
		Noise Figure	20 dB
Phase noise	Meets or Exceeds IESS 308/309	Phase noise	Meets or Exceeds IESS 308/309
Synthesizer step size	125k kHz	Synthesizer step size	125 kHz
<b>Reference</b>		<b>Mechanical</b>	
External Reference	10 MHz (optional)	Dimensions	Width 19" (482.6 mm)
Internal reference stability	± 2 x 10 <sup>-10</sup> / day		Height 1U 1.75" (44.5 mm)
Aging	± 5 x 10 <sup>-8</sup> / year		Depth 24" (609.6 mm)
<b>Environmental</b>		<b>Power Supply</b>	
Operational	0°C to +50°C standard	Voltage	90 – 265 VAC (47 – 63 Hz)
Storage	-55°C to +85°C	Power	50W
Humidity	Non-condensing	Connector	IEC 603320 10A
Altitude	3,000m AMSL		
		<b>Monitor and Control</b>	
		RS 485	DB9
		RS 232	DB9
		Discrete	DB9
		Ethernet	RJ45 F

**NORTH AMERICA**  
**USA**  
 Tel: +1 703 659 9796  
 Fax: +1 703 635 2212  
 info.usa@advantechwireless.com

**CANADA**  
 Tel: +1 514 420 0045  
 Fax: +1 514 420 0073  
 info.canada@advantechwireless.com

**EUROPE**  
**UNITED KINGDOM**  
 Tel: +44 1480 357 600  
 Fax: +44 1480 357 601  
 info.uk@advantechwireless.com

**RUSSIA & CIS**  
 Tel: +7 495 971 59 18  
 info.russia@advantechwireless.com

**INDIA**  
 Tel: +91 33 2415 5922  
 info.india@advantechwireless.com

**SOUTH AMERICA**  
 Tel: +1 514 420 0045  
 Fax: +1 514 420 0073  
 info.latam@advantechwireless.com

**BRAZIL**  
 Tel: +55 11 3054 5701  
 Fax: +55 11 3054 5701  
 info.brazil@advantechwireless.com

An ISO 9001 : 2008 Company



Ref.: PB-FCS500T-L-13150