LDS70 Series

LED Lighting Power Supply - Class 2

Total Power: 70 Watts **# of Outputs:** Single

Special Features

Voltage operation

Dimming options

Compliance

Class 2 Outputs

Performance

Class C Harmonics

< 1.0 W No-load power> 0.9 Power Factor

• Constant Current & Constant

• Free-Air rated - No forced air

necessary for cooling



Constant voltage:

Control and Protection

< 2%

Short Circuit Overvoltage Overtemperature

Output power:

Ripple voltage:

Current limit:

Protection:

Input Input range nom: 100 - 240 Vac (U models); 120-277 Vac (H models) Input range (max): 90-264 Vac (U models); 90-305 Vac (H models); Derating may apply Input frequency: 47 - 63 Hz < 50 A max., cold start @ 25 °C Inrush current: Leakage current: 750 μA, at 264 Vac 50/60 Hz Input power (no-load): < 1.0 W, at no load Input power (max): < 82 W, at full load Input fusing: Internally fused CISPR 15 EMI/RFI: FCC Part 15 Efficiency (typical): 88% - 230 Vac 87% - 115 Vac Output Constant current: Programmable current levels. Refer to model table for details

No load to Full load operation. Refer to model table for details

70 W maximum (60 W for 12 V). Class 2 rated outputs

Programmable. Refer to model table for details

• IP64 to IP67 Water Protection

• CISPR 15 / FCC Part 15 EMI

Warranty

Standard 5-Year Warranty (Consult Factory for Extended Terms)



Rev.10.24.13 LDS70 Series






Rev.10.24.13 LDS70 Series 2 of 3

Environmental Specifications

Criteria	Specification	Reference
Power Factor	> 0.9	Energy Star
Harmonics	Class C	IEC 61000-3-2
THD - Input Current	< 20%	ANSI C82.11
Surge Immunity	Level 3 6 kV ring wave	IEC 61000-4-5 ANSI C62.41
EMC Compliance		IEC 61000-4-2, -3, -4, -5, -6, -8, -11
Temperature (case)	-40 °C to 90 °C	Operating
Ingress Protection	IP64 through IP67	Refer to model table for details



Mechanical Miscellaneous				
Criteria	Specification	Reference		
Input Wiring	300 mm	3-wire		
Output Wiring	300 mm	4-wire		
Weight	370 grams			

Ordering Information						
Model Number	Rated Output Voltage	Rated Output Current	Current Adjust	Dimming Interface	IP Rating	Status
LDS70-12-U00	12 Vdc	5.0 Adc		None	IP67	Released
LDS70-12-H03	12 Vdc	5.0 Adc		1 - 10 V	IP67	Released
LDS70-58-U00	58 Vdc	1.2 Adc		None	IP67	Released
LDS70-58-U01	58 Vdc	1.2 Adc	DIP Switch	2-level	IP64	Released
LDS70-58-H03	58 Vdc	1.2 Adc		1 - 10 V	IP67	Released
LDS70-58-H04	58Vdc	1.2Adc		Programmable ¹	IP67	Coming Soon


Notes

Current Adjust and Dimming Description

DIP Switch (for model -U01 only)				
Switch 1	Switch 2	-12 Model	-58 Model	
ON	ON	5.00 Adc	1.2 Adc	
OFF	ON	3.75 Adc	0.9 Adc	
ON	OFF	2.50 Adc	0.6 Adc	
OFF	OFF	1.25 Adc	0.3 Adc	

2 Level - External Switch between Purple & Grey Wires (for model -U01 only)		
Switch	Open Current	
CLOSED	At Programmed Level	
OPEN	At 20% of Rated Level	

0 - 10 V Between Purple & Grey Wires (for models -H03 only)



Americas

Rev.10.24.13 LDS70 Series a Allen Way 3 of 3

5810 Van Allen Way Carlsbad, CA 92008 USA

Telephone: +1 760 930 4600 Facsimile: +1 760 930 0698

Europe (UK)

Waterfront Business Park Merry Hill, Dudley West Midlands, DY5 1LX United Kingdom

Telephone: +44 (0) 1384 842 211 Facsimile: +44 (0) 1384 843 355

Asia (HK)

14/F, Lu Plaza 2 Wing Yip Street Kwun Tong, Kowloon Hong Kong

Telephone: +852 2176 3333 Facsimile: +852 2176 3888

For global contact, visit:

www.Emerson.com/EmbeddedPower techsupport.embeddedpower @emerson.com

While every precaution has been taken to ensure accuracy and completeness in this literature, Emerson Network Power assumes no responsibility, and disclaims all liability for damages resulting from use of this information or for any errors or omissions.

Emerson Network Power.

The global leader in enabling business-critical continuity.



EmersonNetworkPower.com

Surge Protection

Emerson and the Emerson Network Power logo are trademarks of Emerson Electric Co. ©2012 Emerson Electric Co. All rights reserved.

¹The Dimming Interface on these highly-flexible models can be programmed via a Graphical User-Interface. The options include 0-10V, 1-10V and Bi-Level dimming. Maximum and minimum current levels and threshold levels are also programmable.