



5300 Beethoven Street, Los Angeles, CA 90066
 TEL: (310)306-5556 • FAX: (310)577-9887
 WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 5303038A
5 - 1000 MHz
15 WATTS
LINEAR POWER RF AMPLIFIER

**Solid State
 Broadband High
 Power RF Amplifier**

The 5303038A is a 15 Watt broadband amplifier that covers the 5 – 1000 MHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR_{RF} amplifiers, the 5303038A comes with an extended multiyear warranty.

	Parameter	Specification @ 25°C
Electrical		
1	Frequency Range	5 – 1000 MHz
2	Saturated Output Power	15 Watts rated
3	Power Output @ 1dB Comp.	5 Watts min
4	Small Signal Gain	+43 dB min
5	Gain Flatness	± 2.25 dB max
6	IP ₃	+45 dBm typical
7	Input VSWR	2:1 max
8	Harmonics	-20 dBc typical @ 5 Watts
9	Spurious Signals	< -60 dBc typical @ 5 Watts
10	Input/Output Impedance	50 Ohms nominal
11	DC Input Current	5.5 Amps max
12	DC Input	28 VDC nominal
13	RF Input	0 dBm max
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	AB
Mechanical		
16	Dimensions	6" x 3" x 1.1"
17	Weight	2 lb. max
18	Connectors	SMA female
19	Grounding	Chassis
20	Cooling	Adequate Heatsink Required
Environmental		
21	Operating Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport

Specifications subject to change without notice.

