

# 1.5mm Travel Thin Type Slide Switch SLM-13-735

**Features**

- ◇ 1.5mm travel.
- ◇ Thin type only 1.4mm height.
- ◇ It is a through hole attachment type.



**Applications**

- ◇ Signal switching for portable audio.

**Products line**

| No | Products number | Poles | Positions | Changeover timing |
|----|-----------------|-------|-----------|-------------------|
| 1  | SLM-13-735      | 1     | 3         | Not specified     |

**Typical specifications**

| Items                         | Specifications   |
|-------------------------------|--|
| Rating (max) (resistive load) | 0.3A 4VDC  |
| Contact resistance            | 70 milliohm  |
| Insulation resistance         | 100 megohm   |
| Withstanding voltage          | 500VAC 1min.   |
| Operating force               | B-A,B-C : 1.96 plus or minus 1.47N<br>A-B,C-B : 1.47 plus or minus 0.98N |
| Operating life                | 10,000 cycles  |
| Operation temperature range   | From -10 to +60 degree Celsius   |
| Storage temperature range     | From -20 to +70 degree Celsius   |

**Dimensions**

Unit : mm

| No | Style                           | PC board mounting hole dimension (TOP VIEW) |
|----|---------------------------------|---|
|    |                                 | Circuit diagram                             |
| 1  | <p>SLM-13-735</p> <p>Travel</p> | <br>  |

## □ Notes

1. The appearance and specifications of the product may be modified to improve its performance without prior notice.
2. This catalog shows only outline specifications. When using the product, please obtain formal specifications.
3. Regardless of the suggested applications of these products being introduced in this catalog, when using them for equipment's and devices requiring a high degree of safety, respective manufacturers shall preserve the safety of the planned equipment's and devices by providing necessary protective circuits and redundancy circuits and reconfirm if safety is being duly preserved.
4. These switches are not washable. Note that if the switches are washed, the lubricant at contact portion and mechanism flows out and it may cause operating failures. Also the remains of the detergent stayed inside of the switch may lead to the failure of contact, insulation and withstanding voltage.
5. Please confirm the performance on actual operation by simulation with actual environment environments for high reliability.
6. Note that if the stress more than specifications are applied to the switch during the operation, it may cause the deformation and defects in electrical performance. Care shall be taken not to apply abnormal stress to the switch.
7. Please solder when the knob stands at the correct switching position. If the soldering is done at the middle position of the stroke there may cause the reduction of the operating force.
8. In case of the soldering by auto-dip, please be sure to carry the testing of mounting before the usage. Also the soldering flux protective agent is recommended to prevent the penetration of flux.
9. In case of the manual soldering, consideration should be given to applying the soldering iron to the tip of the terminals and avoid the abnormal stress to the terminals. Please do not apply pressure for 1 minute after soldering.
10. As the melted flux might penetrate into the switch, please do not wipe off the flux by the cleaning solvent after the soldering
11. If the switches are used in the following environment, the performance and the characteristics may influence.  
Corrosive gas such as  $\text{Cl}_2$ ,  $\text{H}_2\text{S}$ ,  $\text{NO}_2$ ,  $\text{SO}_2$ ,  $\text{NH}_3$ .  
Places attaching water drop moisture, salty water, oil, agent and organic solvent.  
Places of direct sunshine and dusty environment.
12. If the switches are not used immediately, please store them as delivered in the following environment: with temperature at -10 to 60 degree Celsius relative humidity 25 to 75% without water-drop and direct sunshine. There might be the possibility of the chemical reaction by sulfur on the silver plated terminals which lead to the reduction of solderability and creation of the oxidization and the rust, if the switches are stored in the high temperature and high humid environment for the long time (Approx. 6 months)  
After the break of the seal, the remaining of the switches shall be stored in a plastic bag to separate them from the moisture and corrosive gas.