

JD746A

CellAdvisor™ RF Analyzer



Spectrum Analyzer: 100 kHz to 4 GHz

Cable and Antenna Analyzer: 5 MHz to 4 GHz

Power Meter: 10 MHz to 4 GHz

Specification Conditions

The JD746A specifications apply under these conditions:

- The instrument has been turned on for at least 15 minutes
- The instrument is operating within a valid calibration period
- Data with no tolerance are considered typical values
- Cable and antenna measurements apply after calibration to the OSL standard
- Typical and nominal values are defined as:
 - Typical: expected performance of the instrument operating under 20 to 30°C after being at this temperature for 15 minutes
 - Nominal: a general, descriptive term or parameter

Spectrum Analyzer (Standard)

Frequency		
Frequency range	100 kHz to 4 GHz	
Internal 10 MHz Frequency Reference		
Accuracy	±0.05 ppm + aging (0 to 50°C)	
Aging	±0.5 ppm/year	
Frequency Span		
Range	0 Hz (zero span) 10 Hz to 4 GHz	
Resolution	1 Hz	
Resolution Bandwidth (RBW)		
–3 dB bandwidth	1 Hz to 3 MHz	1-3-10 sequence
Accuracy	±10% (nominal)	
Video Bandwidth (VBW)		
–3 dB bandwidth	1 Hz to 3 MHz	1-3-10 sequence
Accuracy	±10% (nominal)	

Single Sideband (SSB) Phase Noise

Fc 1 GHz, RBW 10 kHz, VBW 1 kHz, RMS detector

Carrier offset:

30 kHz	< –90 dBc/Hz (typical)
100 kHz	< –95 dBc/Hz (typical)
1 MHz	< –102 dBc/Hz (typical)

Measurement Range

	DANL to +20 dBm
Input attenuator range	0 to 50 dB, 5 dB steps

Maximum Input Level

Average continuous power	+20 dBm
DC voltage	±50 V DC

Displayed Average Noise Level (DANL)

1 Hz RBW, 1 Hz VBW, 50 Ω termination, 0 dB attenuation, RMS detector

Preamplifier Off:

10 MHz to 2.3 GHz	–140 dBm (–146 dBm, typical)
>2.3 GHz to 3 GHz	–138 dBm (–144 dBm, typical)
>3 GHz to 4 GHz	–135 dBm (–140 dBm, typical)

Preamplifier On:

10 MHz to 2.3 GHz	–155 dBm (–160 dBm, typical)
>2.3 GHz to 3 GHz	–153 dBm (–158 dBm, typical)
>3 GHz to 4 GHz	–150 dBm (–156 dBm, typical)

2

Display Range

Log scale and units (10 divisions displayed)	1 to 20 dB/division in 1 dB steps dBm, dBV, dBmV, dBμV
Linear scale and units (10 divisions displayed)	V, mV, mW, W
Detectors	Normal, positive peak, sample, negative peak, RMS
Number of traces	6
Trace functions	Clear/write, maximum hold, minimum hold, capture, load view on/off

Total Absolute Amplitude Accuracy

Preamplifier off, power level >-50 dBm, auto-coupled (20 to 30°C)

5 MHz to 4 GHz	±1.25 dB, ±0.5 dB (typical)	Attenuation <40 dB
	±1.55 dB, ±1.0 dB (typical)	Attenuation ≥40 dB

Reference Level

Setting range	-120 to +100 dBm
Setting resolution	
Log scale	0.1 dB
Linear scale	1% of reference level

Markers

Marker types	Normal, delta, delta pair, noise, frequency count marker
Number of markers	6
Marker functions	Peak, next peak, peak left, peak right, minimum search marker to center/start/stop

RF Input VSWR

20 MHz to 4 GHz	1.5:1 (typical)
-----------------	-----------------

Second Harmonic Distortion

Mixer level = -25 dBm

10 MHz to 1.3 GHz	<-65 dBc (typical)
>1.3 GHz to 4 GHz	<-70 dBc (typical)

Third-order Inter-modulation (Third-order Intercept: TOI)

200 MHz to 2 GHz	+10 dBm (typical)
>2 GHz to 4 GHz	+12 dBm (typical)

Spurious

Inherent residual response

Input terminated, 0 dB attenuation, preamplifier off, RBW at 10 kHz

20 MHz to 3 GHz	-90 dBm (nominal)
>3 GHz to 4 GHz	-85 dBm (nominal)

Exceptions

	<-80 dBm at 311.94 MHz
	<-84 dBm at 415.92 MHz
	<-85 dBm at 519.90, 1599.00, and 2497.80 MHz

Input related spurious

	<-70 dBc (nominal)
--	--------------------

Dynamic Range

2/3 (TOI-DANL) in 1 Hz RBW	>95 dB
----------------------------	--------

Sweep Time

Range	80 ms to 1000 s	
	24 μs to 200 s	Span = 0 Hz (zero span)
Accuracy	±2%	Span = 0 Hz (zero span)
Sweep mode	Continuous, single	

Gated Sweep

Trigger source	External, video, and GPS
Gate length	1 μs to 100 ms
Gate delay	0 to 100 ms

Trigger

Trigger source	Free run, video, external
Trigger delay	
Range	0 to 200 s
Resolution	6 μs

Measurements*

Channel power
Occupied bandwidth
Spectrum emission mask
Adjacent channel power
Spurious emissions
Field strength
AM/FM audio demodulation
Route map
PIM detect
Dual spectrum

* CW signal generator (Option 003) can be set up simultaneously.

Cable and Antenna Analyzer (Standard)

Frequency

Range	5 MHz to 4 GHz
Resolution	10 kHz
Accuracy	±25 ppm

Data Points

	126, 251, 501, 1001
Measurement speed	1.65 ms/point (nominal)

Measurement Accuracy

Corrected directivity	40 dB (typical)
Reflection uncertainty	±(0.3 + 20log(1 + 10 ^{-EP/20})) (typical) EP = directivity - measured return loss

3

Output Power	
High	0 dBm (typical)
Low	-30 dBm (typical)

Dynamic Range	
Reflection	60 dB

Maximum Input Level	
Average continuous power	+25 dBm (nominal)
DC voltage	±50 V DC

Interference immunity	
On channel	+17 dBm at >1.4 MHz from carrier frequency (nominal)
On frequency	0 dBm within ±10 kHz from the carrier frequency (nominal)

Measurements

Reflection (VSWR)	
VSWR range	1 to 65
Return loss range	0 to 60 dB
Resolution	0.01

Distance to Fault (DTF)	
Vertical VSWR range	1 to 65
Vertical return loss range	1 to 60 dB
Vertical resolution	0.01
Horizontal range	0 to (# of data points - 1) x Horizontal Resolution Maximum = 1500 m (4921 ft)
Horizontal resolution	$(1.5 \times 10^8) \times (V_p) / (\Delta) \times (0.95)$ V_p = propagation velocity Δ = stop freq. - start freq. (Hz)

Cable Loss (1-port)	
Range	0 to 30 dB
Resolution	0.01 dB

1-port Phase	
Range	-180 to +180°
Resolution	0.01°

Smith Chart	
Resolution	0.01

RF Power Meter (Standard)

General Parameters	
Display range	-100 to +100 dBm
Offset range	0 to 60 dB
Resolution	0.01 dB or 0.1xW (x = m, u, p)

Internal RF Power Sensor	
Frequency range	10 MHz to 4 GHz
Span	100 kHz to 100 MHz
Dynamic range	-120 to +20 dBm
Maximum power	+20 dBm
Accuracy	Same as spectrum analyzer

External RF Power Sensors

Directional Power Sensor	JD731B
Frequency range	300 MHz to 3.8 GHz
Dynamic range	0.15 to 150 W (average) 4 to 400 W (peak)
Connector type	Type-N female on both ends
Measurement type	Forward/reverse average power, forward peak power, VSWR

Accuracy	±(4% of reading + 0.05 W) ^{1,2}
Directional Power Sensor	JD733A
Frequency range	150 MHz to 3.5 GHz
Dynamic range	0.1 to 50 W (average) 0.1 to 50 W (peak)
Connector type	Type-N female on both ends
Measurement type	Forward/reverse average power, forward peak power, VSWR

Accuracy	±(4% of reading + 0.05 W) ^{1,2}
----------	--

Terminating Power Sensor	JD732B
Frequency range	20 MHz to 3.8 GHz
Dynamic range	-30 to +20 dBm
Connector type	Type-N male
Measurement type	Average
Accuracy	±7% ¹

Terminating Power Sensor	JD734B
Frequency range	20 MHz to 3.8 GHz
Dynamic range	-30 to +20 dBm
Connector type	Type-N male
Measurement type	Peak
Accuracy	±7% ¹

Terminating Power Sensor	JD736B
Frequency range	20 MHz to 3.8 GHz
Dynamic range	-30 to +20 dBm
Connector type	Type-N male
Measurement type	Average and Peak
Accuracy	±7% ¹

1. CW condition at 25°C ±10°C

2. Forward power

Optical Power Meter (Standard)

Optical Power Meter	
Display range	-100 to +100 dBm
Offset range	0 to 60 dB
Resolution	0.01 dB or 0.1 mW

4

External Optical Power Sensors

Optical Power Sensor	MP-60A
Wavelength range	780 to 1650 nm
Max permitted input level	+10 dBm
Connector input	Universal 2.5 and 1.25 mm
Accuracy	±5%

Optical Power Sensor	MP-80A
Wavelength range	780 to 1650 nm
Max permitted input level	+23 dBm
Connector input	Universal 2.5 and 1.25 mm
Accuracy	±5%

2-Port Transmission Measurements (Option 001)**Frequency**

Frequency range	5 MHz to 4 GHz
Frequency resolution	10 kHz

Output Power

High	0 dBm (typical)
Low	-30 dBm (typical)

Measurement Speed

Vector	2.2 ms/point (nominal)
--------	------------------------

Dynamic Range

Vector	5 MHz to 3 GHz, 80 dB >3 GHz to 4 GHz, 75 dB
Scalar	5 MHz to 4 GHz, >100 dB

Measurements**Insertion Loss/Gain**

Range	-120 to 100 dB
Resolution	0.01 dB

2-Port Phase

Range	-180 to +180°
Resolution	0.01°

Bias-Tee (Option 002)**Voltage**

Voltage range	+12 to +32 V
Voltage resolution	0.1 V

Power

8 W Max

CW Signal Generator (Option 003)**Frequency**

Frequency range	25 MHz to 4 GHz
Frequency reference	±25 ppm Maximum
Frequency resolution	10 kHz

Output Power

Range	0 dBm, -30 to -80 dBm
Step	1 dB
Accuracy	±1.5 dB (15 to 35°C)

GPS Receiver and Antenna (Option 010)**GPS Indicator**

Latitude, longitude, altitude

High-Frequency Accuracy

Spectrum, interference, and signal analyzer		
GPS lock	±25 ppb	
Hold over (for 3 days)	±50 ppb (0 to 50°C)	15 minutes after satellite locked
Connector	SMA, female	

Interference Analyzer (Option 011)**Measurements**

Spectrum analyzer	Sound indicator, AM/FM audio demodulation, interference ID, spectrum recorder	
Spectrogram	Collect up to 72 hours of data	
RSSI	Collect up to 72 hours of data	
Interference finder		
Spectrum replayer		
Dual spectrogram		

Channel Scanner (Option 012)**Frequency Range**

10 MHz to 4 GHz

Measurement Range

-110 to +20 dBm

Measurements

Channel scanner	1 to 20 channels
Frequency scanner	1 to 20 frequencies
Custom scanner	1 to 20 channels or frequencies

Wireless Connectivity (Option 006)**Bluetooth Connectivity**

Personal Area Networking (PAN)
File Transfer Profile (FTP)

General Information

Inputs and Outputs

RF in	Spectrum analyzer
Connector	Type-N, female
Impedance	50 Ω (nominal)
Damage level	>+40 dBm, \pm 50 V DC (nominal)

Reflection/RF out	Cable and antenna analyzer
Connector	Type-N, female
Impedance	50 Ω (nominal)
Damage level	>+37 dBm, \pm 50 V DC (nominal)

RF in	Cable and antenna analyzer
Connector	Type-N, female
Impedance	50 Ω (nominal)
Maximum level	>+25 dBm, \pm 50 V DC (nominal)

External trigger, GPS

Connector	SMA, female
Impedance	50 Ω (nominal)

External ref

Connector	SMA, female
Impedance	50 Ω (nominal)
Input frequency	10 MHz, 13 MHz, 15 MHz
Input range	-5 to +5 dBm

USB

USB host ¹	Type A, 1 port
USB client ²	Type B, 1 port

LAN	RJ45, 10/100Base-T
-----	--------------------

GPIO	RJ45
------	------

Audio jack	3.5 mm headphone jack
------------	-----------------------

External power	5.5 mm barrel connector
----------------	-------------------------

Speaker	Built-in speaker
---------	------------------

Display

Type	Resistive touch screen (as of serial number BEK11791)
Size	8 inch, LED backlight
Resolution	800 x 600

Power

External DC input	12 to 19 V DC
Power consumption	32.5 W 45 W maximum (when charging battery)

Battery

Type	10.8 V, 7800 mA/hr (Lithium ion)
Operating time	>3 hours (typical)
Charge time	2.5 hours (80%), 4 hours (100%)
Charging temperature	0 to 45°C (32 to 113°F) \leq 85% RH
Discharging temperature	-10 to 60°C (14 to 140°F) \leq 85% RH
Storage temperature ³	-20 to 50°C (-4 to 122°F) \leq 85% RH (noncondensing)

Data Storage

Internal ⁴	Minimum 20 MB
External ⁵	Limited by size of USB flash drive

Environmental

Operating temperature

AC Power	0 to 40°C (32 to 104°F) with no derating
Battery	0 to 40°C (32 to 104°F) at charging -10 to 55°C (14 to 131°F) at discharging

Maximum humidity	\leq 85% RH (noncondensing)
------------------	-------------------------------

Shock and vibration	MIL-PRF-28800F class 2
---------------------	------------------------

Storage temperature ⁶	-30 to 71°C (-22 to 160°F)
----------------------------------	----------------------------

EMC

EN 61326-2-1	Complies with European EMC
--------------	----------------------------

Size and Weight (Standard configuration)

Weight (with battery)	<4 kg (8.8 lb)
Size (W x H x D)	295 x 195 x 82 mm (11.6 x 7.7 x 3.2 in)

Warranty

2 years

Calibration Cycle

1 year

1. Connects flash drive and power sensor
2. Connects to PC for data transfer
3. 20 to 85% RH, store battery pack in low-humidity environment; extended exposure to temperatures above 45°C could significantly degrade battery performance and life
4. Up to 700 traces
5. Supports USB 2.0 compatible memory devices
6. With the battery pack removed

Ordering Information

Standard

Description	Part Number
100 kHz to 4 GHz spectrum analyzer	JD746A
5 MHz to 4 GHz cable and antenna analyzer ¹	
10 MHz to 4 GHz RF power meter (internal mode)	

Options

NOTE: Upgrade options for the JD746A use the designation JD746AU before the respective last three-digit option number.

Description	Part Number
2-Port Transmission Measurement ²	JD746A001
Bias-Tee ³	JD746A002
CW Signal Generator	JD746A003
Bluetooth connectivity ⁴	JD746A006
GPS Receiver and Antenna	JD746A010
Interference Analyzer ^{5,6}	JD746A011
Channel Scanner	JD746A012

Standard Accessories

Description	Part Number
AC/DC power adapter ⁷	G710550326
Cross LAN cable (1.5 m) ⁷	G710550335
USB A to B cable (1.8 m) ⁷	GC73050515
>1 GB USB memory ⁷	GC72450518
Rechargeable lithium ion battery ⁷	G710550325
Automotive cigarette lighter 12 V DC adapter ⁷	G710550323
Stylus ⁷	G710550316
JD740A series user's manual and application software — CD	JD740A361

- Requires calibration kit
- Requires dual-port calibration kit
- Requires Option 1
- Includes a pair of Bluetooth USB dongles with 5 dBi dipole antenna (JD70050006)
- Highly recommend adding GPS receiver JD746A010
- Highly recommend adding antennas G70005035x and/or G70005036x
- Standard accessory that can be purchased separately

Optional Calibration Kits

Description	Part Number
Y-calibration kit, Type-N(m), DC to 6 GHz, 50 Ω	JD72450509
Y-calibration kit DIN(m), DC to 4 GHz, 50 Ω	JD72450510
Dual-port Type-N calibration kit, 50 Ω	JD71050507
<ul style="list-style-type: none"> Y-calibration kit, Type-N(m), DC to 4 GHz, 50 Ω Two adapters Type-N(f) to Type-N(f), DC to 4 GHz, 50 Ω Two 1 m RF test cables, Type-N(m) to Type-N(m), DC to 18 GHz, 50 Ω 	
Dual-Port DIN calibration kit, 50 Ω	JD71050508
<ul style="list-style-type: none"> Y-calibration kit DIN(m), DC to 4 GHz, 50 Ω Two 1 m RF test cables, Type-N(m) to Type-N(m), DC to 18 GHz, 50 Ω Adapter Type-N(f) to DIN(f), DC to 4 GHz, 50 Ω Adapter Type-N(f) to DIN(m), DC to 4 GHz, 50 Ω Adapter DIN(f) to DIN(f), DC to 4 GHz, 50 Ω Adapter DIN(m) to DIN(m), DC to 4 GHz, 50 Ω 	

Optional RF Cables

Description	Part Number
1.0 m (3.28 ft) RF cable, DC to 18 GHz, Type-N(m) to Type-N(m), 50 Ω	G710050530
1.5 m (4.92 ft) RF cable, DC to 18 GHz, Type-N(m) to Type-N(f), 50 Ω	G710050531
3.0 m (9.84 ft) RF cable, DC to 18 GHz, Type-N(m) to Type-N(f), 50 Ω	G710050532
1.5 m (4.92 ft) RF cable, DC to 18 GHz, Type-N(m) to SMA(m), 50 Ω	G710050533
1.5 m (4.92 ft) RF cable, DC to 18 GHz, Type-N(m) to QMA(m), 50 Ω	G710050534
1.5 m (4.92 ft) RF cable, DC to 18 GHz, Type-N(m) to SMB(m), 50 Ω	G710050535

Optional Omni Antennas

Description	Part Number
RF omni antenna Type-N(m), 806 MHz to 896 MHz	G700050353
RF omni antenna Type-N(m), 870 MHz to 960 MHz	G700050354
RF omni antenna Type-N(m), 1.71 GHz to 2.17 GHz	G700050355
RF omni antenna Type-N(m), 720 MHz to 800 MHz	G700050356
RF omni antenna Type-N(m), 2.3 GHz to 2.7 GHz	G700050357

Ordering Information (cont'd)

Optional Yagi Antennas

Description	Part Number
RF Yagi antenna Type-N(f), 806 MHz to 896 MHz, 10.2 dBd ⁸	G700050364
RF Yagi antenna Type-N(f), 866 MHz to 960 MHz, 10.2 dBd ⁸	G700050365
RF Yagi antenna Type-N(f), 1.75 GHz to 2.39 GHz, 9.8 dBd ⁹	G700050363
RF Yagi antenna SMA(f), 700 MHz to 4 GHz, 1.85 dBd ⁹	G700050366

Optional RF Power Sensors

Description	Part Number
Directional Power Sensor (peak and average power) Frequency: 300 MHz to 3.8 GHz Power: average 0.15 to 150 W, peak 4 to 400 W	JD731B
Directional Power Sensor (peak and average power) Frequency: 150 MHz to 3.5 GHz Power: average/peak 0.1 to 50 W	JD733A
Terminating Power Sensor (average power) Frequency: 20 MHz to 3.8 GHz Power: -30 to +20 dBm	JD732B
Terminating Power Sensor (peak power) Frequency: 20 MHz to 3.8 GHz Power: -30 to +20 dBm	JD734B
Terminating Power Sensor (peak and average power) Frequency: 20 MHz to 3.8 GHz Power: -30 to +20 dBm	JD736B

Optional Optical Power Sensors

Description	Part Number
USB Optical Power Meter with software, 2.5 and 1.25 mm interfaces, 30-inch USB extender, and carrying pouch	MP-60A
USB Optical Power Meter—High power with software, 2.5 and 1.25 mm interfaces, 30-inch USB extender, and carrying pouch	MP-80A

Optional RF Adapters

Description	Part Number
Adapter Type-N(f) to Type-N(f), DC to 6 GHz, 50 Ω	G710050570
Adapter Type-N(m) to DIN(f), DC to 4 GHz, 50 Ω	G710050571
Adapter DIN(m) to DIN(m), DC to 4 GHz, 50 Ω	G710050572
Adapter Type-N(m) to SMA(f), DC to 18 GHz, 50 Ω	G710050573
Adapter Type-N(m) to BNC(f), DC to 1.5 GHz, 50 Ω	G710050574
Adapter Type-N(f) to Type-N(f), DC to 4 GHz, 50 Ω	G710050575
Adapter Type-N(m) to DIN(m), DC to 4 GHz, 50 Ω	G710050576
Adapter Type-N(f) to DIN(f), DC to 4 GHz, 50 Ω	G710050577
Adapter Type-N(f) to DIN(m), DC to 4 GHz, 50 Ω	G710050578
Adapter DIN(f) to DIN(f), DC to 4 GHz, 50 Ω	G710050579

Optional Miscellaneous

Description	Part Number
Attenuator 40 dB, 100 W, DC to 4 GHz (unidirectional)	G710050581
Soft carrying case	JD74050341
Hard carrying case	JD71050342
Hard carrying case with wheels	JD70050342
CellAdvisor Backpack carrying case	JD70050343
RF directional coupler, 700 MHz to 4 GHz, 30 dB, input/output; Type-N(m) to Type-N(f), tap off; Type-N(f) ¹⁰	G710050585
RF combiner, 700 MHz to 4 GHz, Type-N(f) to Type-N(m) ¹⁰	G710050586
External battery charger	G710550324
JD740A series user's manual – printed version	JD740A362

8. Requires RF cable G710050530

9. Requires RF cable G710050533

10. Highly recommended for LTE testing

Network and Service Enablement Regional Sales

NORTH AMERICA TOLL FREE: 1 855 ASK-JDSU 1 855 275-5378	LATIN AMERICA TEL: +1 954 688-5660 FAX: +1 954 3454668	ASIA PACIFIC TEL:+852 2892 0990 FAX:+852 2892 0770	EMEA TEL:+49 7121 86 2222 FAX:+49 7121 86 1222	www.jdsu.com/nse
---	---	---	---	--