

## FreeSpeech® PA Audio Sensor

Mounts to the front face of a public address (PA) loudspeaker to sense whenever an audio signal is present. Connects to the MUTE SENSOR input of a FreeSpeech® Wireless Mic Receiver ([MP-FS-RX1](#) or [MP-FS-RX2<sup>\[1\]</sup>](#)) allowing all audio signals through the wireless mic receiver to be muted during a PA announcement.

### SPECIFICATIONS

#### Connections

(2) red/black 22 AWG flying leads;  
Connect to MUTE SENSOR port of a MP-FS-RX1 or MP-FS-RX2 receiver<sup>[1]</sup>

#### Controls

**Threshold:** Recessed screwdriver-adjustable rotary control, for setting audio sensitivity

#### Environmental

**Temperature:** 41° to 104°F (5° to 40°C)  
**Humidity:** 10% to 90% RH (non-condensing)

#### Enclosure

**Housing:** Plastic, black  
**Mounting:** Surface mount (adhesive fastener included)

#### Dimensions

**Height:** 1.44 in (37 mm)  
**Width:** 0.72 in (19 mm)  
**Depth:** 0.52 in (14 mm)

#### Weight

0.3 oz (9 g)



#### Notes:

1. Item(s) sold separately or as part of a [MP-FS100\\_PAK](#) or [MP-FS200\\_PAK](#) system package.

This product may be purchased from an authorized Crestron dealer. To find a dealer, please contact the Crestron sales representative for your area. A list of sales representatives is available online at [www.crestron.com/salesreps](http://www.crestron.com/salesreps) or by calling 800-237-2041.

Specifications subject to change without notice. Crestron is not responsible for errors in typography or photography.

The specific patents that cover Crestron products are listed online at: [patents.crestron.com](http://patents.crestron.com).

Crestron, FreeSpeech, and the Crestron logo are either trademarks or registered trademarks of Crestron Electronics, Inc. in the United States and/or other countries. Other trademarks and trade names may be used in this document to refer to either the entities claiming the marks and names or their products. Crestron disclaims any proprietary interest in the marks and names of others.  
©2012 Crestron Electronics, Inc.

### MODELS & ACCESSORIES

#### Available Models

MP-FS-PAS: FreeSpeech® PA Audio Sensor

# MP-FS-PAS FreeSpeech® PA Audio Sensor

