

DATASHEET 1310-3080

Operating Modes Setting

Current:	Voltage:	Resistance:	Power:
0 ... 10 A	0 ... 267 V	0.2 Ω ... 888 Ω	0 ... 1000 W
0 ... 30 A	0 ... 800 V	0.06 Ω ... 296 Ω	0 ... 3000 W



Accuracy of the Manual Setting, without Presetting:

	of setting	of corresponding range
Voltage	±0.2%	±0.05%
Current	±0.2%	±0.05%

Accuracy of Manual Setting with Presetting:

	of setting	of corresponding range
Voltage	±0.6%	±0.05%
Current	±0.6%	±0.05%
Resistance	±1.4%	±0.3% of current range
Power	±1.4%	±0.5%
Current Limitation	±1.4%	±0.3%
Trigger Voltage	±1.4%	±0.3%
Time Setting	±1.4%	±0.5% of B1 or B2
Time ranges for internal modulator		

B1	100ms
B2	1000ms

Accuracy of Display:

	of measured value (real value)	of corresponding range
Voltage	±0.2%	±0.05%
Current	±0.2%	±0.05%

Accuracy of Analog Programming:

0 ... 5V / 0 ... 10V for Current, Voltage, Power

	of setting	of corresponding range
--	------------	------------------------

Voltage	±0.2%	±0.1%
Current	±0.2%	±0.1%
Power	±2%	±0.5%
Current Limitation *	±1%	±0.4%
Trigger Voltage *	±1%	±0.4%

* only when option ZS08 is installed
 Input impedance of the analog inputs: > 10kΩ
 GND max. ±2V against negative load input ¹⁾

Accuracy of Analog Monitor Outputs: 0 ... 10V for Current, Voltage, Power ²⁾

	of the analog signal of the real value	offset voltage
Voltage	±0.2%	±15mV
Current	±0.2%	±15mV
Power	±2%	±30mV

GND max. ±2V against negative load input ¹⁾
 Loading capacity minimum 2kΩ

Accuracy of Setting Programming via Data Interface:

	of setting	of corresponding range
Voltage	±0.2%	±0.05%
Current	±0.2%	±0.05%
Resistance	±1%	±3% of current range
Power	±1%	±0.5%
Current Limitation	±1%	±0.3%
Trigger Voltage	±1%	±0.3%
Resolution Setting	16 bit	

Accuracy of Measurement, Reading via Data Interface:

	of measured value (real value)	of corresponding range
Voltage	±0.1%	±0.05%
Current	±0.2%	±0.05%
Resolution Measurement	18 bit	
Reading Rate	330ms not triggerable	

Accuracy of Measurement, Reading via Data Interface: Option ZS13

	of measured value (real value)	of corresponding range
Voltage	±0.2%	±0.05%
Current	±0.2%	±0.05%
Resolution Measurement	13 bit	
Reading Rate	min. 200µs (into memory) triggerable	

Power

HEIDEN power GmbH
 Am Wiesengrund
 86932 Pürgen
 Germany

Tel.: +49-8196-9988-0
 Fax.: +49-8196-9988-77
 Email: info@heidenpower.com
 www.heidenpower.com

Nominal Power	up to $T_A = 21\text{ °C}$
Derating	-1.2% / °C for $T_A > 21\text{ °C}$
Overload	W


The height of the possible overload P_{max} depends on the temperature of the device and therefore on the dissipated power previously

The possible overload duration t depends on the height of the overload power P_x

Input Impedance	> 50 kΩ at deactivated load input
Input Capacitance	approx. 2μF / 1000W
Operating Temperature	5°C ... 40°C
External Control	<ul style="list-style-type: none"> • Load Switching • Trigger input and output • Range switching • Mode switching • Emergency shutdown


Protection Equipment	<ul style="list-style-type: none"> • Current and power limitation • Over-voltage protection up to 110% of rated voltage ³⁾ • Protection against reverse polarity up to rated current (diode) ⁴⁾ • Over-temperature deactivation • Transient protection
-----------------------------	---

Minimum voltage



Full current up from approx. 1V.
Below 1V linear Derating.

Modulator



Puls t1: 100μs ... 1s
Puls t2: 100μs ... 1s

	(in two ranges) Load level: each 0 ... 100%
Rise and Fall Time ⁶⁾	40 µs
Parallel Operation	up to 3 devices in master-slave operation (hardware-controlled)
Cooling	infinitely variable controlled fans
Noise max. ⁷⁾	72 dB(A)
Case ⁸⁾, Weight	19" / 5 HU, 34 kg
Mains Supply	115/230V ± 10%, 50 ... 60Hz
Power Consumption	160 VA
Permissible Operating Voltages: Negative Load Input - Case	
Standard	125V AC
with Option ZS06	500V AC ⁵⁾
Colour	
Front Panel	RAL7032 (pebble grey)
Sides, Lid	RAL7037 (stone grey)
Electric Safety	DIN EN 61010-1
EMC, CE-Mark	DIN EN 61326-1 DIN EN 61000-3-2 DIN EN 61000-3-3

-
- 1) 500 V with option ZS06 (except a Zero-Volt-Option is installed)
 - 2) for units with 3 and 4 setting ranges the power monitoring signal is referred to the highest range
 - 3) 101% for 800V devices
 - 4) no protection against reverse polarity at installed Zero-Volt-Option
 - 5) except a Zero-Volt-Option is installed
 - 6) Rise and fall times are defined as 10%...90% and 90%...10% of the maximum current (measured in constant current mode - FAST)
 - 7) measured at the front panel at 1m distance
 - 8) 1HU = 44.45mm