

## DATASHEET 1310-4806

### Operating Modes Setting

|                    |                   |                           |                      |
|--------------------|-------------------|---------------------------|----------------------|
| Current:           | Voltage:          | Resistance:               | Power:               |
| <b>0 ... 150 A</b> | <b>0 ... 20 V</b> | <b>0.013 Ω ... 4.44 Ω</b> | <b>0 ... 3600 W</b>  |
| <b>0 ... 450 A</b> | <b>0 ... 60 V</b> | <b>4.4 m Ω ... 1.48 Ω</b> | <b>0 ... 10800 W</b> |



### Accuracy of the Manual Setting, without Presetting:

|         | of setting   | of corresponding range |
|---------|--------------|------------------------|
| Voltage | <b>±0.2%</b> | <b>±0.05%</b>          |
| Current | <b>±0.2%</b> | <b>±0.05%</b>          |

### Accuracy of Manual Setting with Presetting:

|                                    | of setting   | of corresponding range        |
|------------------------------------|--------------|-------------------------------|
| Voltage                            | <b>±0.6%</b> | <b>±0.05%</b>                 |
| Current                            | <b>±0.6%</b> | <b>±0.05%</b>                 |
| Resistance                         | <b>±1.4%</b> | <b>±0.3%</b> of current range |
| Power                              | <b>±1.4%</b> | <b>±0.5%</b>                  |
| Current Limitation                 | <b>±1.4%</b> | <b>±0.3%</b>                  |
| Trigger Voltage                    | <b>±1.4%</b> | <b>±0.3%</b>                  |
| Time Setting                       | <b>±1.4%</b> | <b>±0.5%</b> of B1 or B2      |
| Time ranges for internal modulator |              |                               |

|    |               |
|----|---------------|
| B1 | <b>100ms</b>  |
| B2 | <b>1000ms</b> |

### Accuracy of Display:

|         | of measured value<br>(real value) | of corresponding range |
|---------|-----------------------------------|------------------------|
| Voltage | <b>±0.2%</b>                      | <b>±0.05%</b>          |
| Current | <b>±0.2%</b>                      | <b>±0.05%</b>          |

### Accuracy of Analog Programming:

**0 ... 5V / 0 ... 10V for Current, Voltage, Power**

|  | of setting | of corresponding range |
|--|------------|------------------------|
|--|------------|------------------------|

|                      |              |              |
|----------------------|--------------|--------------|
| Voltage              | <b>±0.2%</b> | <b>±0.1%</b> |
| Current              | <b>±0.2%</b> | <b>±0.1%</b> |
| Power                | <b>±2%</b>   | <b>±0.5%</b> |
| Current Limitation * | <b>±1%</b>   | <b>±0.4%</b> |
| Trigger Voltage *    | <b>±1%</b>   | <b>±0.4%</b> |

\* only when option ZS08 is installed  
 Input impedance of the analog inputs: > 10kΩ  
 GND max. ±2V against negative load input <sup>1)</sup>

### Accuracy of Analog Monitor Outputs: 0 ... 10V for Current, Voltage, Power <sup>2)</sup>

|         | of the analog signal<br>of the real value | offset voltage |
|---------|---|----------------|
| Voltage | <b>±0.2%</b>                              | <b>±15mV</b>   |
| Current | <b>±0.2%</b>                              | <b>±15mV</b>   |
| Power   | <b>±2%</b>                                | <b>±30mV</b>   |

GND max. ±2V against negative load input <sup>1)</sup>  
 Loading capacity minimum 2kΩ

### Accuracy of Setting Programming via Data Interface:

|                    | of setting    | of corresponding range      |
|--------------------|---------------|-----------------------------|
| Voltage            | <b>±0.2%</b>  | <b>±0.05%</b>               |
| Current            | <b>±0.2%</b>  | <b>±0.05%</b>               |
| Resistance         | <b>±1%</b>    | <b>±3%</b> of current range |
| Power              | <b>±1%</b>    | <b>±0.5%</b>                |
| Current Limitation | <b>±1%</b>    | <b>±0.3%</b>                |
| Trigger Voltage    | <b>±1%</b>    | <b>±0.3%</b>                |
| Resolution Setting | <b>16 bit</b> |                             |

### Accuracy of Measurement, Reading via Data Interface:

|                        | of measured value<br>(real value) | of corresponding range |
|------------------------|-----------------------------------|------------------------|
| Voltage                | <b>±0.1%</b>                      | <b>±0.05%</b>          |
| Current                | <b>±0.2%</b>                      | <b>±0.05%</b>          |
| Resolution Measurement | <b>18 bit</b>                     |                        |
| Reading Rate           | <b>330ms</b> not triggerable      |                        |

### Accuracy of Measurement, Reading via Data Interface: Option ZS13

|                        | of measured value<br>(real value)              | of corresponding range |
|------------------------|--|------------------------|
| Voltage                | <b>±0.2%</b>                                   | <b>±0.05%</b>          |
| Current                | <b>±0.2%</b>                                   | <b>±0.05%</b>          |
| Resolution Measurement | <b>13 bit</b>                                  |                        |
| Reading Rate           | <b>min. 200µs</b> (into memory)<br>triggerable |                        |

### Power


HEIDEN power GmbH  
 Am Wiesengrund  
 86932 Pürgen  
 Germany

Tel.: +49-8196-9988-0  
 Fax.: +49-8196-9988-77  
 Email: info@heidenpower.com  
 www.heidenpower.com

Nominal Power

Derating

Overload




The height of the possible overload  $P_{max}$  depends on the temperature of the device and therefore on the dissipated power previously

up to  $T_A = 21\text{ °C}$

-1.2% / °C for  $T_A > 21\text{ °C}$

10800 W



The possible overload duration  $t$  depends on the height of the overload power  $P_x$

**Input Impedance**

> 50 kΩ at deactivated load input

**Input Capacitance**

approx. 2μF / 1000W

**Operating Temperature**

5°C ... 40°C


**External Control**

- Load Switching
- Trigger input and output
- Range switching
- Mode switching
- Emergency shutdown

**Protection Equipment**


- Current and power limitation
- Over-voltage protection up to 110% of rated voltage <sup>3)</sup>
- Protection against reverse polarity up to rated current (diode) <sup>4)</sup>
- Over-temperature deactivation
- Transient protection

**Minimum voltage**



Full current up from approx. 1V.  
Below 1V linear Derating.

**Modulator**



Puls t1: 100μs ... 1s  
Puls t2: 100μs ... 1s

|   |   |
|---|---|
|   | (in two ranges)<br>Load level: each 0 ...<br>100%                     |
| <b>Rise and Fall Time <sup>6)</sup></b>                           | <b>80 µs</b>  |
| <b>Parallel Operation</b>   | up to 3 devices in<br>master-slave operation<br>(hardware-controlled) |
| <b>Cooling</b>  | infinitely variable<br>controlled fans                                |
| <b>Noise max. <sup>7)</sup></b>                                   | <b>73 dB(A)</b>   |
| <b>Case <sup>8)</sup>, Weight</b>                                 | <b>19" / 5 HU, 39 kg</b>  |
| <b>Mains Supply</b>   | 115/230V ± 10%, 50 ...<br>60Hz  |
| <b>Power Consumption</b>  | <b>220 VA</b>   |
| <b>Permissible Operating Voltages: Negative Load Input - Case</b> |   |
| Standard  | 125V AC   |
| with Option ZS06  | 500V AC <sup>5)</sup>   |
| <b>Colour</b>   |   |
| Front Panel   | RAL7032 (pebble grey)   |
| Sides, Lid  | RAL7037 (stone grey)  |
| <b>Electric Safety</b>  | DIN EN 61010-1  |
| <b>EMC, CE-Mark</b>   | DIN EN 61326-1<br>DIN EN 61000-3-2<br>DIN EN 61000-3-3                |

- 
- 1) 500 V with option ZS06 (except a Zero-Volt-Option is installed)
  - 2) for units with 3 and 4 setting ranges the power monitoring signal is referred to the highest range
  - 3) 101% for 800V devices
  - 4) no protection against reverse polarity at installed Zero-Volt-Option
  - 5) except a Zero-Volt-Option is installed
  - 6) Rise and fall times are defined as 10%...90% and 90%...10% of the maximum current (measured in constant current mode - FAST)
  - 7) measured at the front panel at 1m distance
  - 8) 1HU = 44.45mm