

## DATASHEET 1310-4280

### Operating Modes Setting

Current:	Voltage:	Resistance:	Power:
0 ... 15 A	0 ... 267 V	0.133 Ω ... 592 Ω	0 ... 1400 W
0 ... 45 A	0 ... 800 V	0.044 Ω ... 197 Ω	0 ... 4200 W



### Accuracy of the Manual Setting, without Presetting:

	of setting	of corresponding range
Voltage	±0.2%	±0.05%
Current	±0.2%	±0.05%

### Accuracy of Manual Setting with Presetting:

	of setting	of corresponding range
Voltage	±0.6%	±0.05%
Current	±0.6%	±0.05%
Resistance	±1.4%	±0.3% of current range
Power	±1.4%	±0.5%
Current Limitation	±1.4%	±0.3%
Trigger Voltage	±1.4%	±0.3%
Time Setting	±1.4%	±0.5% of B1 or B2
Time ranges for internal modulator		

B1	100ms
B2	1000ms

### Accuracy of Display:

	of measured value (real value)	of corresponding range
Voltage	±0.2%	±0.05%
Current	±0.2%	±0.05%

### Accuracy of Analog Programming:

0 ... 5V / 0 ... 10V for Current, Voltage, Power

	of setting	of corresponding range
--	------------	------------------------

Voltage	<b>±0.2%</b>	<b>±0.1%</b>
Current	<b>±0.2%</b>	<b>±0.1%</b>
Power	<b>±2%</b>	<b>±0.5%</b>
Current Limitation *	<b>±1%</b>	<b>±0.4%</b>
Trigger Voltage *	<b>±1%</b>	<b>±0.4%</b>

\* only when option ZS08 is installed  
 Input impedance of the analog inputs: > 10kΩ  
 GND max. ±2V against negative load input <sup>1)</sup>

### Accuracy of Analog Monitor Outputs: 0 ... 10V for Current, Voltage, Power <sup>2)</sup>

	of the analog signal of the real value	offset voltage
Voltage	<b>±0.2%</b>	<b>±15mV</b>
Current	<b>±0.2%</b>	<b>±15mV</b>
Power	<b>±2%</b>	<b>±30mV</b>

GND max. ±2V against negative load input <sup>1)</sup>  
 Loading capacity minimum 2kΩ

### Accuracy of Setting Programming via Data Interface:

	of setting	of corresponding range
Voltage	<b>±0.2%</b>	<b>±0.05%</b>
Current	<b>±0.2%</b>	<b>±0.05%</b>
Resistance	<b>±1%</b>	<b>±3%</b> of current range
Power	<b>±1%</b>	<b>±0.5%</b>
Current Limitation	<b>±1%</b>	<b>±0.3%</b>
Trigger Voltage	<b>±1%</b>	<b>±0.3%</b>
Resolution Setting	<b>16 bit</b>	

### Accuracy of Measurement, Reading via Data Interface:

	of measured value (real value)	of corresponding range
Voltage	<b>±0.1%</b>	<b>±0.05%</b>
Current	<b>±0.2%</b>	<b>±0.05%</b>
Resolution Measurement	<b>18 bit</b>	
Reading Rate	<b>330ms</b> not triggerable	

### Accuracy of Measurement, Reading via Data Interface: Option ZS13

	of measured value (real value)	of corresponding range
Voltage	<b>±0.2%</b>	<b>±0.05%</b>
Current	<b>±0.2%</b>	<b>±0.05%</b>
Resolution Measurement	<b>13 bit</b>	
Reading Rate	<b>min. 200µs</b> (into memory) triggerable	

### Power

HEIDEN power GmbH  
 Am Wiesengrund  
 86932 Pürgen  
 Germany

Tel.: +49-8196-9988-0  
 Fax.: +49-8196-9988-77  
 Email: info@heidenpower.com  
 www.heidenpower.com

Nominal Power	<b>up to <math>T_A = 21\text{ °C}</math></b>
Derating	<b>-1.2% / °C for <math>T_A &gt; 21\text{ °C}</math></b>
Overload	<b>W</b>


The height of the possible overload  $P_{max}$  depends on the temperature of the device and therefore on the dissipated power previously

The possible overload duration  $t$  depends on the height of the overload power  $P_x$

<b>Input Impedance</b>	> 50 kΩ at deactivated load input
<b>Input Capacitance</b>	approx. 2μF / 1000W
<b>Operating Temperature</b>	5°C ... 40°C
<b>External Control</b>	<ul style="list-style-type: none"> <li>• Load Switching</li> <li>• Trigger input and output</li> <li>• Range switching</li> <li>• Mode switching</li> <li>• Emergency shutdown</li> </ul>


<b>Protection Equipment</b>	<ul style="list-style-type: none"> <li>• Current and power limitation</li> <li>• Over-voltage protection up to 110% of rated voltage <sup>3)</sup></li> <li>• Protection against reverse polarity up to rated current (diode) <sup>4)</sup></li> <li>• Over-temperature deactivation</li> <li>• Transient protection</li> </ul>
-----------------------------	---

### Minimum voltage



Full current up from approx. 1V.  
Below 1V linear Derating.

### Modulator



Puls t1: 100μs ... 1s  
Puls t2: 100μs ... 1s

	(in two ranges) Load level: each 0 ... 100%
<b>Rise and Fall Time</b> <sup>6)</sup>	<b>50 µs</b>
<b>Parallel Operation</b>	up to 3 devices in master-slave operation (hardware-controlled)
<b>Cooling</b>	infinitely variable controlled fans
<b>Noise max.</b> <sup>7)</sup>	<b>73 dB(A)</b>
<b>Case</b> <sup>8)</sup> , <b>Weight</b>	<b>19" / 5 HU, 39 kg</b>
<b>Mains Supply</b>	115/230V ± 10%, 50 ... 60Hz
<b>Power Consumption</b>	<b>220 VA</b>
<b>Permissible Operating Voltages: Negative Load Input - Case</b>	
Standard	125V AC
with Option ZS06	500V AC <sup>5)</sup>
<b>Colour</b>	
Front Panel	RAL7032 (pebble grey)
Sides, Lid	RAL7037 (stone grey)
<b>Electric Safety</b>	DIN EN 61010-1
<b>EMC, CE-Mark</b>	DIN EN 61326-1 DIN EN 61000-3-2 DIN EN 61000-3-3

- 
- 1) 500 V with option ZS06 (except a Zero-Volt-Option is installed)
  - 2) for units with 3 and 4 setting ranges the power monitoring signal is referred to the highest range
  - 3) 101% for 800V devices
  - 4) no protection against reverse polarity at installed Zero-Volt-Option
  - 5) except a Zero-Volt-Option is installed
  - 6) Rise and fall times are defined as 10%...90% and 90%...10% of the maximum current (measured in constant current mode - FAST)
  - 7) measured at the front panel at 1m distance
  - 8) 1HU = 44.45mm