

DATASHEET 1312-8060

Operating Modes Setting

Current:	Voltage:	Resistance:	Power:
0 ... 33 A	0 ... 200	60 Ω ... 200	0 ... 2666 W
0 ... 100 A	0 ... 600 V	20 Ω ... 66.7	0 ... 8000 W



Accuracy of the Manual Setting, without Presetting:

	of setting	of corresponding range
Voltage	±0.2%	±0.05%
Current	±0.2%	±0.05%

Accuracy of Manual Setting with Presetting:

	of setting	of corresponding range
Voltage	±0.6%	±0.05%
Current	±0.6%	±0.05%
Resistance	±1.4%	±0.3% of current range
Power	±1.4%	±0.5%
Current Limitation	±1.4%	±0.3%
Trigger Voltage	±1.4%	±0.3%
Time Setting	±1.4%	±0.5% of B1 or B2
Time ranges for internal modulator		
	B1	100ms
	B2	1000ms

Accuracy of Display:

	of measured value (real value)	of corresponding range
Voltage	±0.2%	±0.05%
Current	±0.2%	±0.05%

**Accuracy of Analog Programming:
0 ... 5V / 0 ... 10V for Current, Voltage, Power**

	of setting	of corresponding range
Voltage	±0.2%	±0.1%
Current	±0.2%	±0.1%

Power	±2%	±0.5%
Current Limitation *	±1%	±0.4%
Trigger Voltage *	±1%	±0.4%

* only when option ZS08 is installed
 Input impedance of the analog inputs: > 10kΩ
 GND max. ±2V against negative load input ¹⁾

Accuracy of Analog Monitor Outputs: 0 ... 10V for Current, Voltage, Power

	of the analog signal of the real value	offset voltage
Voltage	±0.2%	±15mV
Current	±0.2%	±15mV
Power	±2%	±30mV

GND max. ±2V against negative load input ¹⁾
 Loading capacity minimum 2kΩ

Accuracy of Setting Programming via Data Interface:

	of setting	of corresponding range
Voltage	±0.2%	±0.05%
Current	±0.2%	±0.05%
Resistance	±1%	±3% of current range
Power	±1%	±0.5%
Current Limitation	±1%	±0.3%
Trigger Voltage	±1%	±0.3%
Resolution Setting	16 bit	

Accuracy of Measurement, Reading via Data Interface:

	of measured value (real value)	of corresponding range
Voltage	±0.1%	±0.05%
Current	±0.2%	±0.05%
Resolution Measurement	18 bit	
Reading Rate	330ms not triggerable	

Accuracy of Measurement, Reading via Data Interface: Option ZS13

	of measured value (real value)	of corresponding range
Voltage	±0.2%	±0.05%
Current	±0.2%	±0.05%
Resolution Measurement	13 bit	
Reading Rate	min. 200µs (into memory) triggerable	

Cooling

cooling medium

**water or water-
glycol-mixture**


HEIDEN power GmbH
 Am Wiesengrund
 86932 Pürgen
 Germany

Tel.: +49-8196-9988-0
 Fax.: +49-8196-9988-77
 Email: info@heidenpower.com
 www.heidenpower.com

Materials in the cooling circuit	cooper, brass, plastic
Max. Cooling Medium Temperature	12°C for nominal power
Min. Cooling Medium Temperature	5°C
Derating at higher Cooling Medium Temperature	-5% / °C
Pressure for Nominal Power	min. 3 bar
Max. Pressure	5 bar
Cooling Medium Connection	1/2 inch per 8000W
Minimum Input Voltage	approx. 2V for full current
Input Impedance	> 50 kΩ at deactivated load input
Input Capacitance	approx. 2μF / 1000W
Operating Temperature	5°C ... 40°C
External Control	<ul style="list-style-type: none"> • Load switching • Trigger input and output • Range switching • Mode switching • Emergency shutdown


Protection Equipment	<ul style="list-style-type: none"> • Current and power limitation • Over-voltage protection up to 110% of rated voltage • Protection against reverse polarity up to rated current (diode)³⁾ • Over-temperature deactivation • Transient protection
-----------------------------	--

Minimum voltage



Full current up from approx. 2V.
Below 2V linear Derating.

Modulator



Puls t1: 100μs ... 1s
Puls t2: 100μs ... 1s
(in two ranges)
Load level: each 0 ... 100%

Rise and Fall Time ⁵⁾	400 μ s
Parallel Operation	up to 3 devices in master-slave operation (hardware-controlled)
Cooling	liquid cooled
Case ⁴⁾ , Weight	19" / 5 HU, 54 kg
Mains Supply	115/230V \pm 10%, 50 ... 60Hz
Power Consumption	70 VA
Electric Safety	DIN EN 61010-1
EMC, CE-Mark	DIN EN 61326-1 DIN EN 61000-3-2 DIN EN 61000-3-3

Permissible Operating Voltages: Negative Load Input - Case

Standard	125V AC
with Option ZS06	500V AC ³⁾

Colour

Front Panel	RAL7032 (pebble grey)
Sides, Lid	RAL7037 (stone grey)

1) 500 V with option ZS06 (except a Zero-Volt-Option is installed)

2) no protection against reverse polarity at installed Zero-Volt-Option

3) except a Zero-Volt-Option is installed

4) 1HU = 44.45mm

5) Rise and fall times are defined as 10%...90% and 90%...10% of the maximum current (measured in constant current mode - FAST)