

**DATASHEET 1312-40012**

**Operating Modes Setting**

Current:	Voltage:	Resistance:	Power:
<b>0 ... 583 A</b>	<b>0 ... 40</b>	<b>3.4 Ω ... 2.28</b>	<b>0 ... 13333 W</b>
<b>0 ... 1750 A</b>	<b>0 ... 120 V</b>	<b>1.1 Ω ... 0.76</b>	<b>0 ... 40000 W</b>

**Accuracy of the Manual Setting, without Presetting:**

	of setting	of corresponding range
Voltage	<b>±0.2%</b>	<b>±0.05%</b>
Current	<b>±0.2%</b>	<b>±0.05%</b>

**Accuracy of Manual Setting with Presetting:**

	of setting	of corresponding range
Voltage	<b>±0.6%</b>	<b>±0.05%</b>
Current	<b>±0.6%</b>	<b>±0.05%</b>
Resistance	<b>±1.4%</b>	<b>±0.3%</b> of current range
Power	<b>±1.4%</b>	<b>±0.5%</b>
Current Limitation	<b>±1.4%</b>	<b>±0.3%</b>
Trigger Voltage	<b>±1.4%</b>	<b>±0.3%</b>
Time Setting	<b>±1.4%</b>	<b>±0.5%</b> of B1 or B2
Time ranges for internal modulator		
	B1	<b>100ms</b>
	B2	<b>1000ms</b>

**Accuracy of Display:**

	of measured value (real value)	of corresponding range
Voltage	<b>±0.2%</b>	<b>±0.05%</b>
Current	<b>±0.2%</b>	<b>±0.05%</b>

**Accuracy of Analog Programming:  
0 ... 5V / 0 ... 10V for Current, Voltage, Power**

	of setting	of corresponding range
Voltage	<b>±0.2%</b>	<b>±0.1%</b>
Current	<b>±0.2%</b>	<b>±0.1%</b>
Power	<b>±2%</b>	<b>±0.5%</b>
Current Limitation *	<b>±1%</b>	<b>±0.4%</b>
Trigger Voltage *	<b>±1%</b>	<b>±0.4%</b>

*\* only when option ZS08 is installed  
Input impedance of the analog inputs: > 10kΩ*

HEIDEN power GmbH  
Am Wiesengrund  
86932 Pürgen  
Germany

Tel.: +49-8196-9988-0  
Fax.: +49-8196-9988-77  
Email: info@heidenpower.com  
www.heidenpower.com

GND max.  $\pm 2V$  against negative load input <sup>1)</sup>

---

**Accuracy of Analog Monitor Outputs:  
0 ... 10V for Current, Voltage, Power**

	of the analog signal of the real value	offset voltage
Voltage	$\pm 0.2\%$	$\pm 15mV$
Current	$\pm 0.2\%$	$\pm 15mV$
Power	$\pm 2\%$	$\pm 30mV$

GND max.  $\pm 2V$  against negative load input <sup>1)</sup>  
Loading capacity minimum  $2k\Omega$

**Accuracy of Setting  
Programming via Data Interface:**

	of setting	of corresponding range
Voltage	$\pm 0.2\%$	$\pm 0.05\%$
Current	$\pm 0.2\%$	$\pm 0.05\%$
Resistance	$\pm 1\%$	$\pm 3\%$ of current range
Power	$\pm 1\%$	$\pm 0.5\%$
Current Limitation	$\pm 1\%$	$\pm 0.3\%$
Trigger Voltage	$\pm 1\%$	$\pm 0.3\%$
Resolution Setting	<b>16 bit</b>	

---

**Accuracy of Measurement, Reading via Data Interface:**

	of measured value (real value)	of corresponding range
Voltage	$\pm 0.1\%$	$\pm 0.05\%$
Current	$\pm 0.2\%$	$\pm 0.05\%$
Resolution Measurement	<b>18 bit</b>	
Reading Rate	<b>330ms</b> not triggerable	

---

**Accuracy of Measurement, Reading via Data Interface:  
Option ZS13**

	of measured value (real value)	of corresponding range
Voltage	$\pm 0.2\%$	$\pm 0.05\%$
Current	$\pm 0.2\%$	$\pm 0.05\%$
Resolution Measurement	<b>13 bit</b>	
Reading Rate	<b>min. 200<math>\mu s</math></b> (into memory) triggerable	

---

**Cooling**

cooling medium	<b>water or water-glycol-mixture</b>
Materials in the cooling circuit	<b>cooper, brass, plastic</b>
Max. Cooling Medium Temperature	<b>12°C for nominal power</b>
Min. Cooling Medium Temperature	<b>5°C</b>
Derating at higher Cooling Medium Temperature	<b>-5% / °C</b>


HEIDEN power GmbH  
Am Wiesengrund  
86932 Pürgen  
Germany

Tel.: +49-8196-9988-0  
Fax.: +49-8196-9988-77  
Email: info@heidenpower.com  
www.heidenpower.com

Pressure for Nominal Power	<b>min. 3 bar</b>
Max. Pressure	<b>5 bar</b>
Cooling Medium Connection	<b>1/2 inch per 8000W</b>
Minimum Input Voltage	<b>approx. 2V for full current</b>
<b>Input Impedance</b>	> 50 k $\Omega$ at deactivated load input
<b>Input Capacitance</b>	approx. 2 $\mu$ F / 1000W
<b>Operating Temperature</b>	5°C ... 40°C
<b>External Control</b>	<ul style="list-style-type: none"> <li>• Load switching</li> <li>• Trigger input and output</li> <li>• Range switching</li> <li>• Mode switching</li> <li>• Emergency shutdown</li> </ul>


<b>Protection Equipment</b>	<ul style="list-style-type: none"> <li>• Current and power limitation</li> <li>• Over-voltage protection up to 110% of rated voltage</li> <li>• Protection against reverse polarity up to rated current (diode)<sup>3)</sup></li> <li>• Over-temperature deactivation</li> <li>• Transient protection</li> </ul>
-----------------------------	--

**Minimum voltage**



Full current up from approx. 2V.  
Below 2V linear Derating.

**Modulator**



Puls t1: 100 $\mu$ s ... 1s  
Puls t2: 100 $\mu$ s ... 1s  
(in two ranges)  
Load level: each 0 ... 100%

**Rise and Fall Time<sup>3)</sup>**

500  $\mu$ s

**Parallel Operation**

up to 3 devices in master-slave operation  
(hardware-controlled)

**Cooling**

liquid cooled

**Case <sup>4)</sup>, Weight** **19" / 17 HU, 247 kg**

**Mains Supply** 115/230V ± 10%, 50 ...  
60Hz

**Power Consumption** **240 VA**

**Electric Safety** DIN EN 61010-1

**EMC, CE-Mark** DIN EN 61326-1  
DIN EN 61000-3-2  
DIN EN 61000-3-3

**Permissible Operating Voltages: Negative Load Input - Case**

Standard 125V AC

with Option ZS06 500V AC <sup>3)</sup>

**Colour**

Front Panel RAL7032 (pebble grey)

Sides, Lid RAL7037 (stone grey)

---

1) 500 V with option ZS06 (except a Zero-Volt-Option is installed)

2) no protection against reverse polarity at installed Zero-Volt-Option

3) except a Zero-Volt-Option is installed

4) 1HU = 44.45mm

5) Rise and fall times are defined as 10%...90% and 90%...10% of the maximum current (measured in constant current mode - FAST)