

Brazen Tek

Where Technology & Creativity Meet

CONTROLLED VIDEO SWITCHER




Controlled Video Switcher CVS is an analog-mixing, 8 video input with 1 video output device meant for switching and monitoring several channels simultaneously. It can be integrated into the existing system by adding an external supply such as an AC adapter or using the existing 5V supply.

FEATURES

- Tiny size (3.7"x 2.7")
- Requires 5V for pulsing, but can also meet your needs (typically 12V)
- High Quality color video path
- Carries composite video: NTSC, PAL or SECAM
- Made in USA

Brazen Tek

Where Technology & Creativity Meet



SPECIFICATIONS

VIDEO

INPUT CONNECTOR TYPE:	BNC
INPUTS (8):	COMPOSITE VIDEO
INPUT LEVEL:	1VPP, 2VPP MAX
INPUT IMPEDANCE:	75Ω ± 10%
FREQUENCY RESPONSE:	0-5MHz ± 0.5 dB 5-15MHz +1.0 dB
OUTPUT CONNECTOR TYPE:	BNC
OUTPUT (1):	COMPOSITE VIDEO
OUTPUT IMPEDANCE:	75% ± 10%
GAIN IN/OUT:	UNITY INTO 75Ω ± 10%

ELECTRICAL

AC OPERATION:	USE 5VDC AC ADAPTER
DC POWER IN:	5V NORMAL >5V (<20V) CUSTOM
DC POWER DRAW:	<2.5VA

MECHANICAL

SIZE (Inches):	3.7 x 2.7 x 1.5
WEIGHT:	<1 LBS

Note: All specifications are subject to change without prior notice

Important Notes

1. This document is provided for reference purposes only. Brazen Tek neither makes warranties or representations with respect to the accuracy or completeness of the information contained in this document nor grants any license to any intellectual property rights.
2. Brazen Tek shall have no liability for damages or infringement of any intellectual property or other rights arising out of the use of any information in this document, including, but not limited to, product data, diagrams, charts, programs, algorithms, and application circuit examples.
3. This application note or the technology described in this document is not for the purpose of military applications such as the development of weapons of mass destruction or for the purpose of any other military use.
4. Brazen Tek assumes no liability whatsoever for any damages incurred as a result of errors or omissions in the information included in this document.
5. When using or otherwise relying on the information in this document, you should evaluate the information in light of the total system before deciding about the applicability of such information to the intended application. Brazen Tek makes no representations, warranties or guaranties regarding the suitability of its products for any particular application and specifically disclaims any liability arising out of the application and use of the information in this document.
12. This document may not be reproduced or duplicated, in any form, in whole or in part, without prior written approval from Brazen Tek.