



## MultiPro 2000 Scan Converter

### The State-of-the-Art VGA-to-TV Scan Converter With Remote Mouse

Based on AITech's widely successful scan converters, the MultiPro 2000 pushes the performance threshold by superior image resolution, flexibility and functionality at an affordable price.

#### The Technology

MultiPro 2000 uses extremely complex and effective patented digital signal processing technology to convert the computer's VGA signal to the NTSC or PAL standard. With this technology you can now enjoy Flic-Free™ graphics and crisp clear images. The MultiPro 2000 accepts a VGA signal (up to 1024x768) from a PC or Mac and converts it to an NTSC or PAL signal for displaying on a TV of any size or recording to a VCR.

#### Portability and Remote Mouse

The MultiPro 2000 is light and compact and is easily portable. Setup consists of plugging in three cables, which takes less than a minute. Wherever you go, from the boardroom to the hotel room, or in a production studio, MultiPro 2000 brings the PC, television and your audience together!

The Presentation Remote MCE (Media Center Edition) is a full-featured hand-held wireless USB mouse. It gives you all the functionality of a regular mouse, but it is designed to send the control signal by wireless infrared up to 30 feet away from your PC.

#### Plug and Play

Installation is as easy as 1-2-3. No software drivers are required to use your MultiPro 2000! No settings to make in your computer!

Just 3 connections: the MultiPro 2000 output cable to the TV or display device; the MultiPro 2000 to the VGA connector on the rear of your computer; the mouse cable to your PC's USB port. Now you are all set to impress your audience with that winning presentation.

#### Features

- External VGA-to-TV Digital Scan Converter
- Superior image quality with resolutions up to 1024x768 × 16.7 million colors. Wider horizontal and vertical frequencies (24 kHz~56 kHz and 50 Hz~85 Hz respectively)
- Simultaneous display on PC and TV
- Plug n' Play - no settings to make in your system
- Four line buffer technology for sharp flicker free images on your TV screen
- 3 channel 10-bit output D/A converter
- Simultaneous Composite and S-Video outputs

#### Input

- 15-pin VGA analog RGB signal
- Multiple input frequencies
  - 640x480 @ 60-85Hz, 800x600 @ 65-85 Hz, 1024x768 @ 60-70 Hz

#### Output

- S-Video (S-VHS) & Composite (RCA) (cables included)
- VGA bypass

#### System Requirements

- IBM PC or compatible computer (with MS-DOS or all versions of Windows) or Mac computers
- VGA-output port
- Video input device such as video monitor, TV, or VCR

**Limited Warranty:** One year

**P/N:** 06-066-079-51

AITech International  
World Headquarters  
1288 Kifer Rd. #203  
Sunnyvale CA 94086

www.AITech.com  
TEL: 408-991-9699  
FAX: 408-991-9691

