



Part Number		Reverse Stand-Off Voltage	Breakdown Voltage		Test Current	Reverse Leakage		Max. Clamp Voltage	Peak Pulse Current	Package
UNI	BI	V_{RWM} V	Min. V	Max. V	I_T mA	UNI $I_{R@VRWM}$ μA	BI μA	$V_C@I_{PP}$ V	I_{PP} A	
600W Transient Voltage Suppressor										
P6KE6.8	P6KE6.8C	5.50	6.12	7.48	10	1000	2000	10.8	56.0	DO-15
P6KE7.5	P6KE7.5C	6.05	6.75	8.25	10	500	1000	11.7	51.0	DO-15
P6KE8.2	P6KE8.2C	6.63	7.38	9.02	10	200	400	12.5	48.0	DO-15
P6KE9.1	P6KE9.1C	7.37	8.19	10.0	1.0	50	100	13.8	44.0	DO-15
P6KE10	P6KE10C	8.10	9.00	11.0	1.0	10	20	15.0	40.0	DO-15
P6KE11	P6KE11C	8.92	9.90	12.1	1.0	5	10	16.2	37.0	DO-15
P6KE12	P6KE12C	9.72	10.8	13.2	1.0	5	5	17.3	35.0	DO-15
P6KE13	P6KE13C	10.5	11.7	14.3	1.0	5	5	19.0	32.0	DO-15
P6KE15	P6KE15C	12.1	13.5	16.5	1.0	5	5	22.0	27.0	DO-15
P6KE16	P6KE16C	12.9	14.4	17.6	1.0	5	5	23.5	26.0	DO-15
P6KE18	P6KE18C	14.5	16.2	19.8	1.0	5	5	26.5	23.0	DO-15
P6KE20	P6KE20C	16.2	18.0	22.0	1.0	5	5	29.1	21.0	DO-15
P6KE22	P6KE22C	17.8	19.8	24.2	1.0	5	5	31.9	19.0	DO-15
P6KE24	P6KE24C	19.4	21.6	26.4	1.0	5	5	34.7	17.0	DO-15
P6KE27	P6KE27C	21.8	24.3	29.7	1.0	5	5	39.1	15.0	DO-15
P6KE30	P6KE30C	24.3	27.0	33.0	1.0	5	5	43.5	14.0	DO-15
P6KE33	P6KE33C	26.8	29.7	36.3	1.0	5	5	47.7	12.6	DO-15
P6KE36	P6KE36C	29.1	32.4	39.6	1.0	5	5	52.0	11.6	DO-15
P6KE39	P6KE39C	31.6	35.1	42.9	1.0	5	5	56.4	10.6	DO-15
P6KE43	P6KE43C	34.8	38.7	47.3	1.0	5	5	61.9	9.6	DO-15
P6KE47	P6KE47C	38.1	42.3	51.7	1.0	5	5	67.8	8.9	DO-15
P6KE51	P6KE51C	41.3	45.9	56.1	1.0	5	5	73.5	8.2	DO-15
P6KE56	P6KE56C	45.6	50.4	61.6	1.0	5	5	80.5	7.4	DO-15
P6KE62	P6KE62C	50.2	55.8	68.2	1.0	5	5	89.0	6.8	DO-15
P6KE68	P6KE68C	55.1	61.2	74.8	1.0	5	5	98.0	6.1	DO-15
P6KE75	P6KE75C	60.7	67.5	82.5	1.0	5	5	108	5.5	DO-15
P6KE82	P6KE82C	66.4	73.8	90.2	1.0	5	5	118	5.1	DO-15
P6KE91	P6KE91C	73.7	81.9	100	1.0	5	5	131	4.5	DO-15
P6KE100	P6KE100C	81.0	90.0	110	1.0	5	5	144	4.2	DO-15
P6KE110	P6KE110C	89.2	99.0	121	1.0	5	5	158	3.8	DO-15
P6KE120	P6KE120C	97.2	108	132	1.0	5	5	173	3.5	DO-15
P6KE130	P6KE130C	105	117	143	1.0	5	5	187	3.2	DO-15
P6KE150	P6KE150C	121	135	165	1.0	5	5	215	2.8	DO-15
P6KE160	P6KE160C	130	144	176	1.0	5	5	230	2.6	DO-15
P6KE170	P6KE170C	136	153	187	1.0	5	5	244	2.5	DO-15
P6KE180	P6KE180C	146	162	198	1.0	5	5	258	2.3	DO-15
P6KE200	P6KE200C	162	180	220	1.0	5	5	287	2.1	DO-15
P6KE220	P6KE220C	175	198	242	1.0	5	5	344	1.8	DO-15
P6KE250	P6KE250C	202	225	275	1.0	5	5	360	1.7	DO-15
P6KE300	P6KE300C	243	270	330	1.0	5	5	430	1.4	DO-15
P6KE350	P6KE350C	284	315	385	1.0	5	5	504	1.2	DO-15
P6KE400	P6KE400C	324	360	440	1.0	5	5	574	1.05	DO-15
P6KE440	P6KE440C	356	396	484	1.0	5	5	631	0.99	DO-15