

Accessory / Terminal & Tools

Part No.	Wire Range		Dimension			Package		Tools			
	AWG	mm ²	D1	D2	L	pcs/bag	bags/box				
DN00506F	22	0.5	1	2.1	6	1000	10	DNT01-2210B 22~12 AWG 0.5~4 mm ² 			
DN00508F					8						
DN00510F					10						
DN00706F	20	0.75	1.2	2.3	6						
DN00708F					8						
DN00710F					10						
DN01006F	18	1	1.4	2.5	6						
DN01008F					8						
DN01010F					10						
DN01012F					12						
DN01507F	16	1.5	1.7	2.8	7				5	DNT01-1006B 10~6 AWG 6~16 mm ² 	
DN01508F					8						
DN01510F					10						
DN01512F					12						
DN02507F	14	2.5	2.2	3.4	7						
DN02508F					8						
DN02510F					10						
DN02512F					12						
DN04008F	12	4	2.8	4	8	2	DNT01-0401B 4~1 AWG 25~50 mm ² 				
DN04009F					9						
DN04010F					10						
DN04012F					12						
DN04015F					15						
DN04018F	18										
DN06010F	10	6	3.5	4.7	10			500	1		
DN06012F					12						
DN06015F					15						
DN06018F					18						
DN10012F	7	10	4.5	5.8	12						
DN10015F					15						
DN10018F					18						
DN16012F	5	16	5.8	7.5	12					200	DNT01-2502F 25~12 AWG 1.5~10 mm ² 
DN16015F					15						
DN16018F					18						
DN25015F	4	25	7.3	9.5	15						
DN25016F					16						
DN25018F					18						
DN25020F					20						
DN25022F					22						
DN35016F	2	35	8.3	11	16						
DN35018F					18						
DN35020F					20						
DN35025F					25						
DN50018F	1	50	10.3	13	18	50	1				
DN50020F					20						
DN50025F					25						
DN70022F	2/0	70	13.5	15.3	22						
DN70025F					25						
DN70032F					32						
DN95025F	3/0	95	14.7	16.6	25			20	1		
DN95032F					32						
DN96030F	4/0	120	16.7	18.6	30						
DN96032F					32						
DN96034F					34						
DN97032F					32						
DN97038F	250kcmil	150	19.5	21.5	38						