




Accessory / Terminal & Tools



Part No.	Wire Range		Dimension							Package		Tools
	AWG	mm ²	W	F	L	E	Ød	ØD	T	pcs/bag	bags/box	
DNK3-109	22~16	0.5~1.5	2.8	9	13.5	4.5	1.7	3.4	0.8	1000	1	
DNK3-110			2.2	10.5	15							
DNK3-111			1.9	11.4	15.9							
DNK3-113			2.3	13	17.5							
DNK3-113W			3	13	17.5					500		
DNK3-114			3	14.5	19							
DNK3-116			2.3	16.8	21.3							
DNK3-118			2.2	18.5	23							
DNK3-209	16~14	1.5~2.5	2.8	9	13.5	4.5	2.4	4.2	0.8	1000	1	
DNK3-210			2.5	10.5	15							
DNK3-211			2.2	11.5	16							
DNK3-213			2.2	13	17.5					500		
DNK3-213B			3.54	13	17.5							
DNK3-217			2.5	16.9	21.4							
DNK3-512	12~10	4~6	4	13	19	6	3.5	5.6	1	200	2	
DNK3-516			3	16.4	22.4						1	
DNK3-518			4.5	18.2	24.2					1		