



PORTAGIG™

FIREWIRE 800

Tiny. Bus Powered. Go.

The PortaGig hard drive makes portable recording and editing easy. With its tiny bus-powered enclosure, it's small enough to fit into a pocket, and powerful enough to support high track-count audio sessions. With FireWire 800 and USB 2.0 interfaces, PortaGig 800 is compatible with Mac, Windows and Linux systems supporting FireWire or USB. Designed with a fanless, light aluminum enclosure, it allows you to work on the road easily and reliably. If bus power is not available or is insufficient, you can use the included power supply.

Features:

- Up to 500GB in a tiny enclosure
- 7,200 and 5,400 RPM models available
- Solid State Disk models available
- Weighs less than 10 Ounces
- All models Tested and approved with Digidesign Pro Tools™ to support over 70 tracks of 24bit / 48k audio, with edits
- SSD supports 128 tracks at 24bit / 48k
- Small, portable, aluminum case
- Runs quietly with fanless design
- Applications: Field recording, storing and exchanging A/V, graphics, prepress, and desktop publishing files.
- Includes universal power supply
- Included carrying case

Specs:

- **Capacity (7,200 + 5,400 RPM):** 160GB, 250GB, 320GB, 500GB
- **Capacity (Solid State Drive):** 64GB, 128GB, 256GB
- **Interfaces:** (2) FireWire 800 and (1) USB 2.0
- **Bridging Chip:** Oxford 934
- **Average read seek time (HDD models):** 8 msec
- **Average read seek time (SSD models):** 0.1 msec
- **Max Transfer rate (FireWire 800):** 800 Mb/sec (100 MB/sec)
- **Sustained transfer rate (HDD):** up to 76 MB/sec
- **Sustained transfer rate (SSD):** up to 85 MB/sec
- **Dimensions (HxWxD):** .86" x 3.3" x 5.2" inches
- **Weight:** 0.6 lbs for HDD, 0.5 lbs for SSD
- **Power supply:** universal auto switching 100-240V
- **Requirements:** Mac OS 8.6/9.x/10.x, Windows 2000/XP/Vista
- **Format:** HFS+, can be formatted for other OS
- **Approvals:** CE
- **Warranty:** 3 Years, 1 Year Overnight Advance Replacement
- **Includes:** FireWire 800 (9pin to 9pin) cable, USB cable, sleeve, power supply. Manual is downloadable from Glyph web site.

www.glyphtech.com
800-335-0345

