

Encore Controller LC

The Encore Controller LC is designed for advanced applications involving up to 64 input videos and from 1-32 screens.



The Encore Controller LC supports up to 64 inputs and 32 destinations, comprised of Encore Video Processors, ScreenPRO-II and ImagePRO processors. Designed for both single screen and wide screen blended destinations, the LC offers 900 presets and special User Keys to ease programming and "on the fly" switching. The Controller LC also supports stacked Encore Video Processor configurations, which enable you to control up to 12 layers on a single screen.

BARCO

Visibly yours

Product specifications**Encore Controller LC**

Encore Processors supported	32
Widescreen support	Yes
External router control	Yes
Inputs supported	64
Destinations supported	32
Available presets	900
Layers supported	1 DSK, 12 scaled inputs (PIP or Key), 1 transition background
User-selectable transition functions	Yes
Available destinations	8
Available user-defineable keys	100
Joystick & T-bar	Yes
Machine control	Yes
320 x 240 graphic displays	2
Light sticks	3
PS/2 keyboard support	Yes
Communication	Ethernet, RS 232, USB
Program sequencing	Yes
Field upgradable	Yes
Ethernet control interfaces	Yes
Tally support	8