

## Wall Mount Docking Station for TPMC-3X

The TPMC-3X-DSW is a wall-mountable docking station and battery charger designed specifically for use with the Isys® TPMC-3X Handheld WiFi Touch Screen. It mounts to a 1-gang standard electrical box or plaster ring, and is finished using any off-the-shelf decorative face plate (not included). It features a magnetic catch for easy docking and extra stability. Power may be provided by the Cresnet® control bus<sup>[1]</sup>, or any Crestron 24V DC regulated power source.

Available in white or black. Not compatible with the TPMC-3X-LP.

### SPECIFICATIONS

#### Connectors

---

**PWR:** (1) 4-pin 3.5mm detachable terminal block;  
24 Volt DC power input, Cresnet® compatible<sup>[1]</sup>

**Ground:** (1) Flying lead, grounding wire

#### Power Requirements

---

**Cresnet Power Usage:** 11 Watts (0.425 Amps @ 24 Volts DC)

#### Environmental

---

**Temperature:** 40° to 104°F (5° to 40°C)

**Humidity:** 10% to 90% RH (non-condensing)

**Heat Dissipation:** 38 BTU/Hr

#### Enclosure

---

1-gang mountable in a standard electrical box; requires decorative-style faceplate (not included)

#### Dimensions

---

**Height:** 4.12 in (105 mm)

**Width:** 1.72 in (44 mm)

**Depth:** 2.60 in (66 mm)

#### Weight

---

6 oz (155 g)



### MODELS & ACCESSORIES

#### Available Models

---

**TPMC-3X-DSW:** Wall Mount Docking Station for TPMC-3X, Black Smooth  
**TPMC-3X-DSW-W-S:** Wall Mount Docking Station for TPMC-3X, White Smooth

#### Available Accessories

---

**PW-2407RU:** 18 Watt Cresnet® Power Supply, US/International

**CRESNET-NP:** Cresnet® Control Cable, non-plenum

**CRESNET-P:** Cresnet® Control Cable, plenum

Notes:

1. For power only; does not enable wired communication.

This product may be purchased from an authorized Crestron dealer. To find a dealer, please contact the Crestron sales representative for your area. A list of sales representatives is available online at [www.crestron.com/salesreps](http://www.crestron.com/salesreps) or by calling 800-237-2041.

Specifications subject to change without notice. Crestron is not responsible for errors in typography or photography.

The specific patents that cover Crestron products are listed online at: [patents.crestron.com](http://patents.crestron.com).

Cresnet, Crestron, Isys, and the Crestron logo are either trademarks or registered trademarks of Crestron Electronics, Inc. in the United States and/or other countries. Other trademarks and trade names may be used in this document to refer to either the entities claiming the marks and names or their products. Crestron disclaims any proprietary interest in the marks and names of others. ©2012 Crestron Electronics, Inc.